

Control Commands

Model No. PT-RZ14K



- Please refer to the Operating Instructions for the serial command format, limitations, connection and other details.
- シリアルコマンドのフォーマット、制限事項、接続方法およびその他詳細につきましては、各モデルの取扱説明書をご覧ください。
- 有关串行控制命令的格式、限制事项、连接方法以及其他详情、请参阅各机型的使用说明书。

Panasonic

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ24K SERIES	
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RZ14K	
BASIC OPERATION REMOTE CONTROL	POWER	ON OFF (STANDBY)		PON POF	QPW	001 000	✓ ✓	
	INPUT SELECT	HDMI1 HDMI2 DisplayPort		IIS:HD1 IIS:HD2 IIS:DP1	QIN	HD1 HD2 DP1	✓ ✓ ✓	
	INPUT SELECT (SDM SLOT)	SLOT1 : 12G SDI SLOT1 : Digital Link SLOT1 : PressIT SLOT1 : 3rd Party Board SLOT1 : 12G SDI OPT1 SLOT1 : 12G SDI OPT2		IIS:DM1 ,SD1 IIS:DM1 ,DL1 IIS:DM1 ,WP1 IIS:DM1 ,TP1 IIS:DM1 ,OP1 IIS:DM1 ,OP2	QIN	DM1 ,SD1 DM1 ,DL1 DM1 ,WP1 DM1 ,TP1 DM1 ,OP1 DM1 ,OP2	✓ ✓ ✓ ✓ ✓ ✓	
	INPUT SELECT (SDM SLOT : DIGITAL LINK)	COMPUTER1 COMPUTER2 VIDEO HDMI1 HDMI2 S-VIDEO		IIS:DM1 ,DL1:PC1 IIS:DM1 ,DL1:PC2 IIS:DM1 ,DL1:VID IIS:DM1 ,DL1:HD1 IIS:DM1 ,DL1:HD2 IIS:DM1 ,DL1:SVD	QIN	DM1 ,DL1:PC1 DM1 ,DL1:PC2 DM1 ,DL1:VID DM1 ,DL1:HD1 DM1 ,DL1:HD2 DM1 ,DL1:SVD	✓ ✓ ✓ ✓ ✓ ✓	
	FREEZE	OFF ON		OFZ:0 OFZ:1	QFZ	0 1	✓ ✓	
	MENU KEY			OMN			✓	
	ENTER KEY			OEN			✓	
	UP KEY			OCU			✓	
	DOWN KEY			ODC			✓	
	LEFT KEY			OCL			✓	
	RIGHT KEY			OCR			✓	
	DEFAULT KEY			OST			✓	
	SHUTTER	OFF ON		OSH:0 OSH:1	QSH	0 1	✓ ✓	
	SHUTTER(Toggle)	OFF ON		OSH	QSH	0 1	✓ ✓	
	FUNCTION KEY			FC1			✓	
	SYSTEM SELECTOR KEY			OSL			✓	
	ASPECT KEY			VS1			✓	
	NUMERIC KEY	0 1 2 3 4 5 6 7 8 9		ONK:0 ONK:1 ONK:2 ONK:3 ONK:4 ONK:5 ONK:6 ONK:7 ONK:8 ONK:9			✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓	
	LENS HOME POSITION	EXECUTE		VXX:LNSI1=+00001			✓	
	ACTIVE FOCUS OPTIMIZER-ACTIVE FOCUS	OFF ON		VXX:AFOI1=+00000 VXX:AFOI1=+00001	QVX:AFOI1	AFOI1=+00000 AFOI1=+00001	✓ ✓	
	ACTIVE FOCUS OPTIMIZER-FOCUS OFFSET BRIGHT	-00299 +00299		VXX:FOBI1=-00299 VXX:FOBI1=+00299	QVX:FOBI1	FOBI1=-00299 FOBI1=+00299	-299 +299	
	ACTIVE FOCUS OPTIMIZER-FOCUS OFFSET DARK	-00299 +00299		VXX:FODI1=-00299 VXX:FODI1=+00299	QVX:FODI1	FODI1=-00299 FODI1=+00299	-299 +299	
	ACTIVE FOCUS OPTIMIZER-INITIALIZE	EXECUTE		VXX:FOI1=+00001			✓	
	LENS SHIFT-HORIZONTAL	SLOW+ SLOW- NORMAL+ NORMAL- FAST+ FAST-		VXX:LNSI2=+00000 VXX:LNSI2=+00001 VXX:LNSI2=+00100 VXX:LNSI2=+00101 VXX:LNSI2=+00200 VXX:LNSI2=+00201			✓ ✓ ✓ ✓ ✓ ✓	
	LENS SHIFT-VERTICAL	SLOW+ SLOW- NORMAL+ NORMAL- FAST+ FAST-		VXX:LNSI3=+00000 VXX:LNSI3=+00001 VXX:LNSI3=+00100 VXX:LNSI3=+00101 VXX:LNSI3=+00200 VXX:LNSI3=+00201			✓ ✓ ✓ ✓ ✓ ✓	
	LENS FOCUS	SLOW+ SLOW- NORMAL+ NORMAL- FAST+ FAST-		VXX:LNSI4=+00000 VXX:LNSI4=+00001 VXX:LNSI4=+00100 VXX:LNSI4=+00101 VXX:LNSI4=+00200 VXX:LNSI4=+00201			✓ ✓ ✓ ✓ ✓ ✓	
	LENS ZOOM	SLOW+ SLOW- NORMAL+ NORMAL- FAST+ FAST-		VXX:LNSI5=+00000 VXX:LNSI5=+00001 VXX:LNSI5=+00100 VXX:LNSI5=+00101 VXX:LNSI5=+00200 VXX:LNSI5=+00201			✓ ✓ ✓ ✓ ✓ ✓	
	LENS POSITION	HORIZONTAL(H) VERTICAL(V) FOCUS(F) ZOOM(Z) H/V H/V F H/V F Z		VXX:LNSI7=*HORIZONTAL VXX:LNSI8=*VERTICAL VXX:LNSI9=*FOCUS VXX:LNSIA=*ZOOM VXX:LNSSB=*H*V VXX:LNSSC=*H*V*F VXX:LNSSD=*H*V*F*Z	QVX:LNSI7 QVX:LNSI8 QVX:LNSI9 QVX:LNSIA QVX:LNSSB QVX:LNSSC QVX:LNSSD	LNSI7=*HORIZONTAL LNSI8=*VERTICAL LNSI9=*FOCUS LNSIA=*ZOOM LNSSB=*H*V LNSSC=*H*V*F LNSSD=*H*V*F*Z	✓ ✓ ✓ ✓ ✓ ✓ ✓	
		*HORIZONTAL(H)	min. max.	-***** +*****			-***** +*****	*by lens type(-4960) *by lens type(+4960)
		*VERTICAL(V)	min. max.	-***** +*****			-***** +*****	*by lens type(-4300) *by lens type(+4300)
		*FOCUS(F)	min. max.	+***** +*****			+***** +*****	0 3520
		*ZOOM(Z)	min. max.	+***** +*****			+***** +*****	*by lens type *by lens type
	STATUS KEY			STS				✓
	LENS FOCUS KEY			OLF				✓
	LENS SHIFT KEY			OLH				✓
	LENS ZOOM KEY			OLZ				✓
	DIGITAL LINK KEY			DLK				✓
	INPUT MENU KEY			IPT				✓
	SELF DIAGNOSIS				QVX:ERRS1 QVX:ERRS2	ERRS1=***** ERRS2=*****		✓ ✓
	PICTURE MODE	DYNAMIC NATURAL STANDARD CINEMA GRAPHIC DICOM SIM. USER		VPM:DYN VPM:NAT VPM:STD VPM:CIN VPM:GRA VPM:DIC VPM:USR	QPM	DYN NAT STD CIN GRA DIC USR	✓ ✓ ✓ ✓ ✓ ✓ ✓	
	PICTURE MODE-NAME SETTING USER	PICTUREMODE		VXX:NCGS0=PICTUREMODE	QVX:NCGS0	NCGS0=PICTUREMODE		✓
	PICTURE MODE-NAME CLEAR USER	PICTUREMODE		VXX:NCLIO=+00000				✓
	CONTRAST	+1 +63		VCN:001 VCN:063	QVR	001 063	✓ ✓	
	BRIGHTNESS	+1 +63		VBR:001 VBR:063	QVB	001 063	✓ ✓	
	COLOR	+1 +63		VCO:001 VCO:063	QVC	001 063	✓ ✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ24K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RZ14K
SYSTEM	DYNAMIC CONTRAST/MANUAL IRIS (MANUAL INTENSITY)	OFF		OAI:M000	QAI:M	000	✓
		1		OAI:M001		001	✓
		255		OAI:M255		255	✓
	DYNAMIC CONTRAST (DYNAMIC GAMMA)	OFF		OAI:D0	QAI:D	0	✓
		1		OAI:D1		1	✓
		2		OAI:D2		2	✓
	COLOR SPACE	NATIVE		VXX:CSPI1=+00000	QVX:CSPI1	CSPI1=+00000	✓
		ITU-709		VXX:CSPI1=+00001		CSPI1=+00001	✓
		DCI-P3		VXX:CSPI1=+00002		CSPI1=+00002	✓
	SYSTEM SELECTOR (HDMI/DIGITAL LINK/DisplayPort/SLOT-HDMI/SLOT-DIGITAL LINK/SLOT-DisplayPort/SLOT-2nd Party Board)	RGB		ORF:0	QRF	0	✓
YpBPr			ORF:1	1		✓	
AUTO			ORF:2	2		✓	
GEOMETRY	GEOMETRY	OFF		VXX:GMIO=+00000	QVX:GMIO	GMIO=+00000	✓
		KEYSTONE		VXX:GMIO=+00001		GMIO=+00001	✓
		CURVED		VXX:GMIO=+00002		GMIO=+00002	✓
		PC-1		VXX:GMIO=+00003		GMIO=+00003	✓
		PC-2		VXX:GMIO=+00004		GMIO=+00004	✓
		PC-3		VXX:GMIO=+00005		GMIO=+00005	✓
	CORNER-CORRECTION		VXX:GMIO=+00010	GMIO=+00010	✓		
	GEOMETRY-KEYSTONE-LENS THROW RATIO	0.7	0.1 step	VXX:GMKS0=+00.7	QVX:GMKS0	GMKS0=+00.7	✓
	16.5		VXX:GMKS0=+16.5	GMKS0=+16.5		✓	
	GEOMETRY-KEYSTONE-VERTICAL BALANCE	-60		VXX:GMKI4=-00060	QVX:GMKI4	GMKI4=-00060	✓
+60		VXX:GMKI4=+00060	GMKI4=+00060	✓			
GEOMETRY-KEYSTONE-HORIZONTAL BALANCE	-30		VXX:GMKI7=-00030	QVX:GMKI7	GMKI7=-00030	✓	
+30		VXX:GMKI7=+00030	GMKI7=+00030		✓		
GEOMETRY-KEYSTONE-VERTICAL KEYSTONE	-40.0 (-45.0)*	0.2 step	VXX:GMKS8=-40.0	QVX:GMKS8	GMKS8=-40.0	✓	
+40.0 (+45.0)*		VXX:GMKS8=+40.0	GMKS8=+40.0		✓		
GEOMETRY-KEYSTONE-HORIZONTAL KEYSTONE	-15.0 (-40.0)*	0.2 step	VXX:GMKS9=-15.0	QVX:GMKS9	GMKS9=-15.0	✓	
+15.0 (+40.0)*		VXX:GMKS9=+15.0	GMKS9=+15.0		✓		
GEOMETRY-CURVED-LENS THROW RATIO	0.7	0.1 step	VXX:GMCS0=+00.7	QVX:GMCS0	GMCS0=+00.7	✓	
16.5		VXX:GMCS0=+16.5	GMCS0=+16.5		✓		
GEOMETRY-CURVED-VERTICAL ARC	-50 (-100)*		VXX:GMCI3=-00050	QVX:GMCI3	GMCI3=-00050	✓	
+50 (+100)*		VXX:GMCI3=+00050	GMCI3=+00050		✓		
GEOMETRY-CURVED-HORIZONTAL ARC	-50 (-100)*		VXX:GMCI7=-00050	QVX:GMCI7	GMCI7=-00050	✓	
+50 (+100)*		VXX:GMCI7=+00050	GMCI7=+00050		✓		
GEOMETRY-CURVED-VERTICAL BALANCE	-60		VXX:GMCI2=-00060	QVX:GMCI2	GMCI2=-00060	✓	
+60		VXX:GMCI2=+00060	GMCI2=+00060		✓		
GEOMETRY-CURVED-HORIZONTAL BALANCE	-30		VXX:GMCI6=-00030	QVX:GMCI6	GMCI6=-00030	✓	
+30		VXX:GMCI6=+00030	GMCI6=+00030		✓		
GEOMETRY-CURVED-VERTICAL KEYSTONE	-40.0 (-45.0)*	0.2 step	VXX:GMCS8=-40.0	QVX:GMCS8	GMCS8=-40.0	✓	
+40.0 (+45.0)*		VXX:GMCS8=+40.0	GMCS8=+40.0		✓		
GEOMETRY-CURVED-HORIZONTAL KEYSTONE	-15.0 (-40.0)*	0.2 step	VXX:GMCS9=-15.0	QVX:GMCS9	GMCS9=-15.0	✓	
+15.0 (+40.0)*		VXX:GMCS9=+15.0	GMCS9=+15.0		✓		
GEOMETRY-CURVED-MAINTAIN ASPECT RATIO	OFF		VXX:GMCIA=+00000	QVX:GMCIA	GMCIA=+00000	✓	
ON		VXX:GMCIA=+00001	GMCIA=+00001		✓		
GEOMETRY-CORNER CORRECTION-UPPER LEFT(V)	min.		VXX:GMFI1=+00000	QVX:GMFI1	GMFI1=+00000	0	
max.		VXX:GMFI1=+00300	GMFI1=+00300		+300		
GEOMETRY-CORNER CORRECTION-UPPER RIGHT(V)	min.		VXX:GMFI2=+00000	QVX:GMFI2	GMFI2=+00000	0	
max.		VXX:GMFI2=+00300	GMFI2=+00300		+300		
GEOMETRY-CORNER CORRECTION-LOWER LEFT(V)	min.		VXX:GMFI3=-00300	QVX:GMFI3	GMFI3=-00300	-300	
max.		VXX:GMFI3=+00000	GMFI3=+00000		0		
GEOMETRY-CORNER CORRECTION-LOWER RIGHT(V)	min.		VXX:GMFI4=-00300	QVX:GMFI4	GMFI4=-00300	-300	
max.		VXX:GMFI4=+00000	GMFI4=+00000		0		
GEOMETRY-CORNER CORRECTION-LINEARITY(V)	min.		VXX:GMFI5=-00127	QVX:GMFI5	GMFI5=-00127	-127	
max.		VXX:GMFI5=+00127	GMFI5=+00127		+127		
GEOMETRY-CORNER CORRECTION-UPPER LEFT(H)	min.		VXX:GMFI6=+00000	QVX:GMFI6	GMFI6=+00000	0	
max.		VXX:GMFI6=+00480	GMFI6=+00480		+480		
GEOMETRY-CORNER CORRECTION-UPPER RIGHT(H)	min.		VXX:GMFI7=-00480	QVX:GMFI7	GMFI7=-00480	-480	
max.		VXX:GMFI7=+00000	GMFI7=+00000		0		
GEOMETRY-CORNER CORRECTION-LOWER LEFT(H)	min.		VXX:GMFI8=+00000	QVX:GMFI8	GMFI8=+00000	0	
max.		VXX:GMFI8=+00480	GMFI8=+00480		+480		
GEOMETRY-CORNER CORRECTION-LOWER RIGHT(H)	min.		VXX:GMFI9=-00480	QVX:GMFI9	GMFI9=-00480	-480	
max.		VXX:GMFI9=+00000	GMFI9=+00000		0		
GEOMETRY-CORNER CORRECTION-LINEARITY(H)	min.		VXX:GMFIA=-00127	QVX:GMFIA	GMFIA=-00127	-127	
max.		VXX:GMFIA=+00127	GMFIA=+00127		+127		
GEOMETRY-CORNER/PINCUSHION-PINCUSHION UPPER	min.		VXX:GMFIB=-00100	QVX:GMFIB	GMFIB=-00100	✓	
max.		VXX:GMFIB=+00100	GMFIB=+00100		✓		
GEOMETRY-CORNER/PINCUSHION-PINCUSHION LOWER	min.		VXX:GMFIC=-00100	QVX:GMFIC	GMFIC=-00100	✓	
max.		VXX:GMFIC=+00100	GMFIC=+00100		✓		
GEOMETRY-CORNER/PINCUSHION-PINCUSHION LEFT	min.		VXX:GMFID=-00100	QVX:GMFID	GMFID=-00100	✓	
max.		VXX:GMFID=+00100	GMFID=+00100		✓		
GEOMETRY-CORNER/PINCUSHION-PINCUSHION RIGHT	min.		VXX:GMFIE=-00100	QVX:GMFIE	GMFIE=-00100	✓	
max.		VXX:GMFIE=+00100	GMFIE=+00100		✓		
GEOMETRY-CORNER/PINCUSHION-LINEARITY	AUTO		VXX:GMFIF=+00000	QVX:GMFIF	GMFIF=+00000	✓	
MANUAL		VXX:GMFIF=+00001	GMFIF=+00001		✓		
GEOMETRY - FREE GRID(ON/OFF)	OFF		VXX:GMGI1=+00000	QVX:GMGI1	GMGI1=+00000	✓	
ON		VXX:GMGI1=+00001	GMGI1=+00001		✓		
GEOMETRY - FREE GRID - INITIALIZE			VXX:GMGI2=+00001			✓	
GEOMETRY - FREE GRID - GRID RESOLUTION	2x2		VXX:GMGI3=+00002	QVX:GMGI3	GMGI3=+00002	✓	
	3x3		VXX:GMGI3=+00003		GMGI3=+00003	✓	
	5x5		VXX:GMGI3=+00005		GMGI3=+00005	✓	
	9x9		VXX:GMGI3=+00009		GMGI3=+00009	✓	
	17x17		VXX:GMGI3=+00017		GMGI3=+00017	✓	
GEOMETRY - FREE GRID - GRID COLOR	OFF		VXX:GMGI4=+00000	QVX:GMGI4	GMGI4=+00000	✓	
	WHITE		VXX:GMGI4=+00001		GMGI4=+00001	✓	
	BLACK		VXX:GMGI4=+00002		GMGI4=+00002	✓	
	RED		VXX:GMGI4=+00003		GMGI4=+00003	✓	
	GREEN		VXX:GMGI4=+00004		GMGI4=+00004	✓	
	BLUE		VXX:GMGI4=+00005		GMGI4=+00005	✓	
	CYAN		VXX:GMGI4=+00006		GMGI4=+00006	✓	
	MAGENTA		VXX:GMGI4=+00007		GMGI4=+00007	✓	
	YELLOW		VXX:GMGI4=+00008		GMGI4=+00008	✓	
	GEOMETRY - FREE GRID - CONTROL POINTS	POINT			VXX:GMGI5=+00000	QVX:GMGI5	GMGI5=+00000
HORIZONTAL LINE		VXX:GMGI5=+00001	GMGI5=+00001	✓			
VERTICAL LINE		VXX:GMGI5=+00002	GMGI5=+00002	✓			
GEOMETRY - FREE GRID - GRID WIDTH	1		VXX:GMGI7=+00001	QVX:GMGI7	GMGI7=+00001	✓	
10		VXX:GMGI7=+00010	GMGI7=+00010		✓		
GEOMETRY - FREE GRID - CONTROL POINTS COLOR	WHITE		VXX:GMGI8=+00001	QVX:GMGI8	GMGI8=+00001	✓	
	BLACK		VXX:GMGI8=+00002		GMGI8=+00002	✓	
	RED		VXX:GMGI8=+00003		GMGI8=+00003	✓	
	GREEN		VXX:GMGI8=+00004		GMGI8=+00004	✓	
	BLUE		VXX:GMGI8=+00005		GMGI8=+00005	✓	
	CYAN		VXX:GMGI8=+00006		GMGI8=+00006	✓	
	MAGENTA		VXX:GMGI8=+00007		GMGI8=+00007	✓	
	YELLOW		VXX:GMGI8=+00008		GMGI8=+00008	✓	
CONVERGENCE	OFF		VXX:CNV1=+00000	QVX:CNV1	CNV1=+00000	✓	
ON		VXX:CNV1=+00001	CNV1=+00001		✓		
CONVERGENCE - UPPER LEFT VERTICAL			VXX:CNVS2=*:*****	QVX:CNVS2	CNVS2=*:*****	✓	
		VXX:CNVS2=R:*****	CNVS2=R:*****		✓		
		VXX:CNVS2=G:*****	CNVS2=G:*****		✓		
		VXX:CNVS2=B:*****	CNVS2=B:*****		✓		

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ24K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RZ14K
CONVERGENCE	CONVERGENCE - UPPER LEFT HORIZONTAL			VXX: CNVS2=*:+00.00		CNVS2=*:+00.00	✓
				VXX: CNVS2=*:+03.75		CNVS2=*:+03.75	✓
				VXX: CNVS3=*****	QVX: CNVS3	CNVS3=*****	✓
				VXX: CNVS3=R:*****		CNVS3=R:*****	✓
				VXX: CNVS3=G:*****		CNVS3=G:*****	✓
	CONVERGENCE - UPPER RIGHT VERTICAL			VXX: CNVS3=B:*****		CNVS3=B:*****	✓
				VXX: CNVS3=*:+00.00		CNVS3=*:+00.00	✓
				VXX: CNVS3=*:+03.75		CNVS3=*:+03.75	✓
				VXX: CNVS4=*****	QVX: CNVS4	CNVS4=*****	✓
				VXX: CNVS4=R:*****		CNVS4=R:*****	✓
CONVERGENCE - UPPER RIGHT HORIZONTAL			VXX: CNVS4=G:*****		CNVS4=G:*****	✓	
			VXX: CNVS4=B:*****		CNVS4=B:*****	✓	
			VXX: CNVS4=*:+00.00		CNVS4=*:+00.00	✓	
			VXX: CNVS4=*:+03.75		CNVS4=*:+03.75	✓	
			VXX: CNVS5=*****	QVX: CNVS5	CNVS5=*****	✓	
CONVERGENCE - LOWER LEFT VERTICAL			VXX: CNVS5=R:*****		CNVS5=R:*****	✓	
			VXX: CNVS5=G:*****		CNVS5=G:*****	✓	
			VXX: CNVS5=B:*****		CNVS5=B:*****	✓	
			VXX: CNVS5=*:-03.75		CNVS5=*:-03.75	✓	
			VXX: CNVS5=*:+00.00		CNVS5=*:+00.00	✓	
CONVERGENCE - LOWER LEFT HORIZONTAL			VXX: CNVS6=*****	QVX: CNVS6	CNVS6=*****	✓	
			VXX: CNVS6=R:*****		CNVS6=R:*****	✓	
			VXX: CNVS6=G:*****		CNVS6=G:*****	✓	
			VXX: CNVS6=B:*****		CNVS6=B:*****	✓	
			VXX: CNVS6=*:+00.00		CNVS6=*:+00.00	✓	
CONVERGENCE - LOWER RIGHT VERTICAL			VXX: CNVS6=*:+03.75		CNVS6=*:+03.75	✓	
			VXX: CNVS7=*****	QVX: CNVS7	CNVS7=*****	✓	
			VXX: CNVS7=R:*****		CNVS7=R:*****	✓	
			VXX: CNVS7=G:*****		CNVS7=G:*****	✓	
			VXX: CNVS7=B:*****		CNVS7=B:*****	✓	
CONVERGENCE - LOWER RIGHT HORIZONTAL			VXX: CNVS7=*:-03.75		CNVS7=*:-03.75	✓	
			VXX: CNVS7=*:+00.00		CNVS7=*:+00.00	✓	
			VXX: CNVS8=*****	QVX: CNVS8	CNVS8=*****	✓	
			VXX: CNVS8=R:*****		CNVS8=R:*****	✓	
			VXX: CNVS8=G:*****		CNVS8=G:*****	✓	
SHIFT-HORIZONTAL			VXX: CNVS8=B:*****		CNVS8=B:*****	✓	
			VXX: CNVS8=*:-03.75		CNVS8=*:-03.75	✓	
			VXX: CNVS8=*:+00.00		CNVS8=*:+00.00	✓	
			VXX: CNVS9=*****	QVX: CNVS9	CNVS9=*****	✓	
			VXX: CNVS9=R:*****		CNVS9=R:*****	✓	
SHIFT-VERTICAL			VXX: CNVS9=G:*****		CNVS9=G:*****	✓	
			VXX: CNVS9=B:*****		CNVS9=B:*****	✓	
			VXX: CNVS9=*:-03.75		CNVS9=*:-03.75	✓	
			VXX: CNVS9=*:+00.00		CNVS9=*:+00.00	✓	
			VTH:0000	QTH	0000	✓	
ASPECT	0		VTH:4095		4095	✓	
	+4095		VTV:0000	QTV	0000	✓	
ZOOM-HORIZONTAL	0		VTV:4094		4094	✓	
	+4094		VSE:0	QSE	0	✓	
ZOOM-VERTICAL	AUTO/VID AUTO/DEFAULT		VSE:1		1	✓	
	NORMAL(4:3)		VSE:2		2	✓	
ZOOM-BOTH	WIDE(16:9)		VSE:5		5	✓	
	NATIVE(through)		VSE:6		6	✓	
ZOOM-INTERLOCKED	FULL(HV FIT)		VSE:9		9	✓	
	H-FIT		VSE:10		10	✓	
ZOOM-MODE	V-FIT		OZH:050	QZH	050	✓	
			OZH:999		999	✓	
DIGITAL CINEMA REALITY	50		OZV:050	QZV	050	✓	
	999		OZV:999		999	✓	
BLANKING-UPPER	50		OZO:050	QZO	050	✓	
	999		OZO:999		999	✓	
BLANKING-LOWER	OFF		OZS:0	QZS	0	✓	
	ON		OZS:1		1	✓	
BLANKING-RIGHT	INTERNAL		OZT:0	QZT	0	✓	
	FULL		OZT:1		1	✓	
BLANKING-LEFT	OFF		OPD:0	QPD	0	✓	
	ON		OPD:1		1	✓	
CUSTOM MASKING *	30p/25p FIXED		OPD:2		2	✓	
			DBU:0000	QLU	0000	0	
EDGE BLENDING	min.		DBU:2398		2398	1198	
	max.		DBB:0000	QLB	0000	0	
EDGE BLENDING-UPPER ON/OFF	min.		DBB:2398		2398	1198	
	max.		DBR:0000	QLR	0000	0	
EDGE BLENDING-LOWER ON/OFF	min.		DBR:3838		3838	1918	
	max.		DBL:0000	QLL	0000	0	
EDGE BLENDING-LEFT ON/OFF	min.		DBL:3838		3838	1918	
	max.		VXX:MSK11=+00000	QVX:MSK11	MSK11=+00000	✓	
EDGE BLENDING-RIGHT ON/OFF	OFF		VXX:MSK11=+00001		MSK11=+00001	✓	
	ON		VXX:MSK11=+00002		MSK11=+00002	✓	
EDGE BLENDING-START-UPPER	PC-1		VXX:MSK11=+00003		MSK11=+00003	✓	
	PC-2		VXX:EDB10=+00000	QVX:EDB10	EDB10=+00000	✓	
EDGE BLENDING-START-LOWER	PC-3		VXX:EDB10=+00001		EDB10=+00001	✓	
	OFF		VXX:EDB10=+00002		EDB10=+00002	✓	
EDGE BLENDING-START-MIDDLE	ON		VGU:0	QGU	0	✓	
	USER		VGU:1		1	✓	
EDGE BLENDING-START-LEFT	OFF		VGB:0	QGB	0	✓	
	ON		VGB:1		1	✓	
EDGE BLENDING-START-RIGHT	OFF		VGL:0	QGL	0	✓	
	ON		VGL:1		1	✓	
EDGE BLENDING-WIDTH-UPPER	OFF		VGR:0	QGR	0	✓	
	ON		VGR:1		1	✓	
EDGE BLENDING-WIDTH-LOWER	min.		VEU:0000	QEU	0000	0	
	max.		VEU:2272		2272	1023	
EDGE BLENDING-WIDTH-MIDDLE	min.		VEB:0000	QEB	0000	0	
	max.		VEB:2272		2272	1199	
EDGE BLENDING-WIDTH-LEFT	min.		VEL:0000	QEL	0000	0	
	max.		VEL:3712		3712	1023	
EDGE BLENDING-WIDTH-RIGHT	min.		VER:0000	QER	0000	0	
	max.		VER:3712		3712	1919	
EDGE BLENDING-MARKER-ON/OFF	min.		VXX:EUIW0=+00000	QVX:EUIW0	EUIW0=+00000	0	
	max.		VXX:EUIW0=+02272		EUIW0=+02272	1023	
EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL	min.		VXX:EBW10=+00000	QVX:EBW10	EBW10=+00000	0	
	max.		VXX:EBW10=+02272		EBW10=+02272	1199	
EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL-INTERLOCKED	min.		VXX:ELW10=+00000	QVX:ELW10	ELW10=+00000	0	
	max.		VXX:ELW10=+03712		ELW10=+03712	1023	
EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL-INTERLOCKED	min.		VXX:ERW10=+00000	QVX:ERW10	ERW10=+00000	0	
	max.		VXX:ERW10=+03712		ERW10=+03712	1919	
EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL-INTERLOCKED	OFF		VGM:0	QGM	0	✓	
	ON		VGM:1		1	✓	
EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL-INTERLOCKED	0 (W,R,G,B)		VJI:000,000,000,000	QJI	000,000,000,000	✓	
	255 (W,R,G,B)		VJI:255,255,255,255		255,255,255,255	✓	
EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL-INTERLOCKED	OFF		VXX:EBI11=+00000	QVX:EBI11	EBI11=+00000	✓	
	ON		VXX:EBI11=+00001		EBI11=+00001	✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ24K SERIES	
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RZ14K	
ADVANCED	EDGE BLENDING-BLACK BORDER LEVEL	0 (W,R,G,B) 255 (W,R,G,B)		VJO:000,000,000,000 VJO:255,255,255,255	QJO	000,000,000,000 255,255,255,255	✓ ✓	
	EDGE BLENDING-BLACK BORDER LEVEL-INTERLOCKED	OFF ON		VXX:EBI12=+00000 VXX:EBI12=+00001	QVX:EBI12	EBI12=+00000 EBI12=+00001	✓ ✓	
	EDGE BLENDING-BLACK BORDER WIDTH-UPPER	min. max.		VJU:0000 VJU:2272	QJU	0000 2272	0 1023	
	EDGE BLENDING-BLACK BORDER WIDTH-LOWER	min. max.		VJB:0000 VJB:2272	QJB	0000 2272	0 1199	
	EDGE BLENDING-BLACK BORDER WIDTH-LEFT	min. max.		VJL:0000 VJL:3712	QJL	0000 3712	0 1023	
	EDGE BLENDING-BLACK BORDER WIDTH-RIGHT	min. max.		VJR:0000 VJR:3712	QJR	0000 3712	0 1919	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE -	OFF ON		VXX:EBF11=+00000 VXX:EBF11=+00001	QVX:EBF11	EBF11=+00000 EBF11=+00001	✓ ✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE -	OFF ON		VXX:EBF12=+00000 VXX:EBF12=+00001	QVX:EBF12	EBF12=+00000 EBF12=+00001	✓ ✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - LEFT	OFF ON		VXX:EBF13=+00000 VXX:EBF13=+00001	QVX:EBF13	EBF13=+00000 EBF13=+00001	✓ ✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE -	OFF ON		VXX:EBF14=+00000 VXX:EBF14=+00001	QVX:EBF14	EBF14=+00000 EBF14=+00001	✓ ✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - UPPER - ADJUSTMENT POINTS	2 3 5 9 17		VXX:EFPI1=+00002 VXX:EFPI1=+00003 VXX:EFPI1=+00005 VXX:EFPI1=+00009 VXX:EFPI1=+00017	QVX:EFPI1	EFPI1=+00002 EFPI1=+00003 EFPI1=+00005 EFPI1=+00009 EFPI1=+00017	✓ ✓ ✓ ✓ ✓	
	- UPPER - INITIALIZE	EXECUTE		VXX:EFI11=+00001			✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - LEFT - ADJUSTMENT POINTS	2 3 5 9 17		VXX:EFPI2=+00002 VXX:EFPI2=+00003 VXX:EFPI2=+00005 VXX:EFPI2=+00009 VXX:EFPI2=+00017	QVX:EFPI2	EFPI2=+00002 EFPI2=+00003 EFPI2=+00005 EFPI2=+00009 EFPI2=+00017	✓ ✓ ✓ ✓ ✓	
	- LEFT - INITIALIZE	EXECUTE		VXX:EFI12=+00001			✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - LEFT - ADJUSTMENT POINTS	2 3 5 9 17		VXX:EFPI3=+00002 VXX:EFPI3=+00003 VXX:EFPI3=+00005 VXX:EFPI3=+00009 VXX:EFPI3=+00017	QVX:EFPI3	EFPI3=+00002 EFPI3=+00003 EFPI3=+00005 EFPI3=+00009 EFPI3=+00017	✓ ✓ ✓ ✓ ✓	
	- LEFT - INITIALIZE	EXECUTE		VXX:EFI13=+00001			✓	
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - RIGHT - ADJUSTMENT POINTS	2 3 5 9 17		VXX:EFPI4=+00002 VXX:EFPI4=+00003 VXX:EFPI4=+00005 VXX:EFPI4=+00009 VXX:EFPI4=+00017	QVX:EFPI4	EFPI4=+00002 EFPI4=+00003 EFPI4=+00005 EFPI4=+00009 EFPI4=+00017	✓ ✓ ✓ ✓ ✓	
	- RIGHT - INITIALIZE	EXECUTE		VXX:EFI14=+00001			✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-UPPER	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS0=000,000,000,000 VXX:EBBS0=255,255,255,255	QVX:EBBS0	EBBS0=000,000,000,000 EBBS0=255,255,255,255	✓ ✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LOWER	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS1=000,000,000,000 VXX:EBBS1=255,255,255,255	QVX:EBBS1	EBBS1=000,000,000,000 EBBS1=255,255,255,255	✓ ✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LEFT	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS2=000,000,000,000 VXX:EBBS2=255,255,255,255	QVX:EBBS2	EBBS2=000,000,000,000 EBBS2=255,255,255,255	✓ ✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-RIGHT	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS3=000,000,000,000 VXX:EBBS3=255,255,255,255	QVX:EBBS3	EBBS3=000,000,000,000 EBBS3=255,255,255,255	✓ ✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-UPPER INTERLOCKED	OFF ON		VXX:EBI13=+00000 VXX:EBI13=+00001	QVX:EBI13	EBI13=+00000 EBI13=+00001	✓ ✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LOWER INTERLOCKED	OFF ON		VXX:EBI14=+00000 VXX:EBI14=+00001	QVX:EBI14	EBI14=+00000 EBI14=+00001	✓ ✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LEFT INTERLOCKED	OFF ON		VXX:EBI15=+00000 VXX:EBI15=+00001	QVX:EBI15	EBI15=+00000 EBI15=+00001	✓ ✓	
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-RIGHT INTERLOCKED	OFF ON		VXX:EBI16=+00000 VXX:EBI16=+00001	QVX:EBI16	EBI16=+00000 EBI16=+00001	✓ ✓	
	EDGE BLENDING-MODE	SOFTEDGE/BLACK LEVEL BLACK LEVEL ONLY		VXX:EBMI1=+00000 VXX:EBMI1=+00001	QVX:EBMI1	EBMI1=+00000 EBMI1=+00001	✓ ✓	
	EDGE BLENDING-AUTO TESTPATTERN	OFF ON		VXX:EATI1=+00000 VXX:EATI1=+00001	QVX:EATI1	EATI1=+00000 EATI1=+00001	✓ ✓	
	FRAME RESPONSE	NORMAL FIXED		VXX:FDYI0=+00000 VXX:FDYI0=+00005	QVX:FDYI0	FDYI0=+00000 FDYI0=+00005	✓ ✓	
	FRAME DELAY	0.00 100.00		VXX:FDYS1=+0.00 VXX:FDYS1=+100.00	QVX:FDYS1	FDYS1=+0.00 FDYS1=+100.00	✓ ✓	
	FILM DETECTION	OFF ON		VXX:FDTI1=+00000 VXX:FDTI1=+00001	QVX:FDTI1	FDTI1=+00000 FDTI1=+00001	✓ ✓	
	RASTER POSITION-HORIZONTAL	-2048 +2047		VRH:2952 VRH:7047	QRH	2952 7047	✓ ✓	
	RASTER POSITION-VERTICAL	-2048 +2047		VRV:2952 VRV:7047	QRV	2952 7047	✓ ✓	
	DISPLAY LANGUAGE	LANGUAGE	English German French Spanish Italian Japanese Chinese Russian Korea Portuguse		OLG:ENG OLG:DEU OLG:FRA OLG:ESP OLG:ITL OLG:JPN OLG:CHI OLG:RUS OLG:KOR OLG:POR	QLG	ENG DEU FRA ESP ITL JPN CHI RUS KOR POR	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
		3D SYSTEM SETTING	SINGLE DUAL(LEFT) DUAL(RIGHT)		VXX:DSYI1=+00000 VXX:DSYI1=+00001 VXX:DSYI1=+00002	QVX:DSYI1	DSYI1=+00000 DSYI1=+00001 DSYI1=+00002	✓ ✓ ✓
		3D SYNC SETTING	OFF 1 2 3 4 5 6 7 8 9 10 11		VXX:DSNI1=+00000 VXX:DSNI1=+00001 VXX:DSNI1=+00002 VXX:DSNI1=+00003 VXX:DSNI1=+00004 VXX:DSNI1=+00005 VXX:DSNI1=+00006 VXX:DSNI1=+00007 VXX:DSNI1=+00008 VXX:DSNI1=+00009 VXX:DSNI1=+00010 VXX:DSNI1=+00011	QVX:DSNI1	DSNI1=+00000 DSNI1=+00001 DSNI1=+00002 DSNI1=+00003 DSNI1=+00004 DSNI1=+00005 DSNI1=+00006 DSNI1=+00007 DSNI1=+00008 DSNI1=+00009 DSNI1=+00010 DSNI1=+00011	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
		3D SYNC SETTING-STEREO SYNC OUTPUT DELAY	0 25000	10 step	VXX:DSNI2=+00000 VXX:DSNI2=+25000	QVX:DSNI2	DSNI2=+00000 DSNI2=+25000	✓ ✓
		3D SIMUL INPUT SETTING-L:HDMI1/R:HDMI2	OFF AUTO		VXX:DSMI4=+00000 VXX:DSMI4=+00002	QVX:DSMI4	DSMI4=+00000 DSMI4=+00002	✓ ✓
		3D INPUT FORMAT	AUTO NATIVE(2D) SIDE BY SIDE TOP AND BOTTOM FRAME SEQUENTIAL		VXX:DIFI1=+00000 VXX:DIFI1=+00001 VXX:DIFI1=+00003 VXX:DIFI1=+00004 VXX:DIFI1=+00006	QVX:DIFI1	DIFI1=+00000 DIFI1=+00001 DIFI1=+00003 DIFI1=+00004 DIFI1=+00006	✓ ✓ ✓ ✓ ✓
		3D LEFT/RIGHT SWAP	NORMAL SWAPPED		VXX:DSWI1=+00000 VXX:DSWI1=+00001	QVX:DSWI1	DSWI1=+00000 DSWI1=+00001	✓ ✓
		3D COLOR MATCHING	SHARED 2D/3D SEPARATE 2D/3D		VXX:DCMI1=+00000 VXX:DCMI1=+00001	QVX:DCMI1	DCMI1=+00000 DCMI1=+00001	✓ ✓
		3D DARK TIME SETTING	0.5		VXX:DDTS1=+0.5	QVX:DDTS1	DDTS1=+0.5	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ24K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RZ14K
	3D TEST MODE	1.0		VXX:DDTS1=+1.0		DDTS1=+1.0	✓
		1.5		VXX:DDTS1=+1.5		DDTS1=+1.5	✓
		2.0		VXX:DDTS1=+2.0		DDTS1=+2.0	✓
		2.5		VXX:DDTS1=+2.5		DDTS1=+2.5	✓
		2.7		VXX:DDTS1=+2.7		DDTS1=+2.7	✓
	3D SAFETY PRECAUTIONS MESSAGE	NORMAL		VXX:DTSI1=+0000	QVX:DTSI1	DTSI1=+0000	✓
		SIDE BY SIDE		VXX:DTSI1=+0001		DTSI1=+0001	✓
		LEFT/LEFT		VXX:DTSI1=+0002		DTSI1=+0002	✓
		RIGHT/RIGHT		VXX:DTSI1=+0003		DTSI1=+0003	✓
		LEFT/BLACK		VXX:DTSI1=+0004		DTSI1=+0004	✓
	BLACK/RIGHT		VXX:DTSI1=+0005		DTSI1=+0005	✓	
	COLOR MATCHING	OFF		VXX:CMAI0=+0000	QVX:CMAI0	CMAI0=+0000	✓
		3COLORS		VXX:CMAI0=+0001		CMAI0=+0001	✓
		7COLORS		VXX:CMAI0=+0002		CMAI0=+0002	✓
		MEASURED		VXX:CMAI0=+0004		CMAI0=+0004	✓
	COLOR MATCHING-RESET MODE	NATIVE		VXX:CRM11=+0000	QVX:CRM11	CRM11=+0000	✓
		PICTURE		VXX:CRM11=+0001		CRM11=+0001	✓
		REC709		VXX:CRM11=+0002		CRM11=+0002	✓
	COLOR MATCHING-3COLORS-RED	0 (R,G,B)		VMR:0000,0000,0000	QMR	0000,0000,0000	✓
		2048,2048,2048(R,G,B)		VMR:2048,2048,2048		2048,2048,2048	✓
	COLOR MATCHING-3COLORS-GREEN	0 (R,G,B)		VMG:0000,0000,0000	QMG	0000,0000,0000	✓
	2048,2048,2048(R,G,B)		VMG:2048,2048,2048		2048,2048,2048	✓	
COLOR MATCHING-3COLORS-BLUE	0 (R,G,B)		VMB:0000,0000,0000	QMB	0000,0000,0000	✓	
	2048,2048,2048(R,G,B)		VMB:2048,2048,2048		2048,2048,2048	✓	
COLOR MATCHING-3COLORS-AUTO TESTPATTERN	OFF		VXX:CATI0=+0000	QVX:CATI0	CATI0=+0000	✓	
	ON		VXX:CATI0=+0001		CATI0=+0001	✓	
COLOR MATCHING-3COLORS-RESET	EXECUTE		VXX:CRET1=+0001			✓	
COLOR MATCHING-7COLORS-RED	0 (R,G,B)		VXX:C7CS0=0000,0000,0000	QVX:C7CS0	C7CS0=0000,0000,0000	✓	
	2048(R,G,B)		VXX:C7CS0=2048,2048,2048		C7CS0=2048,2048,2048	✓	
COLOR MATCHING-7COLORS-GREEN	0 (R,G,B)		VXX:C7CS1=0000,0000,0000	QVX:C7CS1	C7CS1=0000,0000,0000	✓	
	2048(R,G,B)		VXX:C7CS1=2048,2048,2048		C7CS1=2048,2048,2048	✓	
COLOR MATCHING-7COLORS-BLUE	0 (R,G,B)		VXX:C7CS2=0000,0000,0000	QVX:C7CS2	C7CS2=0000,0000,0000	✓	
	2048(R,G,B)		VXX:C7CS2=2048,2048,2048		C7CS2=2048,2048,2048	✓	
COLOR MATCHING-7COLORS-CYAN	0 (R,G,B)		VXX:C7CS3=0000,0000,0000	QVX:C7CS3	C7CS3=0000,0000,0000	✓	
	2048(R,G,B)		VXX:C7CS3=2048,2048,2048		C7CS3=2048,2048,2048	✓	
COLOR MATCHING-7COLORS-MAGENTA	0 (R,G,B)		VXX:C7CS4=0000,0000,0000	QVX:C7CS4	C7CS4=0000,0000,0000	✓	
	2048(R,G,B)		VXX:C7CS4=2048,2048,2048		C7CS4=2048,2048,2048	✓	
COLOR MATCHING-7COLORS-YELLOW	0 (R,G,B)		VXX:C7CS5=0000,0000,0000	QVX:C7CS5	C7CS5=0000,0000,0000	✓	
	2048(R,G,B)		VXX:C7CS5=2048,2048,2048		C7CS5=2048,2048,2048	✓	
COLOR MATCHING-7COLORS-WHITE	0 (R,G,B)		VXX:C7CS6=0000,0000,0000	QVX:C7CS6	C7CS6=0000,0000,0000	✓	
	2048(R,G,B)		VXX:C7CS6=2048,2048,2048		C7CS6=2048,2048,2048	✓	
COLOR MATCHING-7COLORS-AUTO TESTPATTERN	OFF		VXX:CATI1=+0000	QVX:CATI1	CATI1=+0000	✓	
	ON		VXX:CATI1=+0001		CATI1=+0001	✓	
COLOR MATCHING-7COLORS-RESET	EXECUTE		VXX:CRET2=+0001			✓	
COLOR MATCHING-MEASURED MODE-MEASURED DATA BLACK	0,1,1 (Y,x,y)		VXX:CMMS0=0000,0001,0001	QVX:CMMS0	CMMS0=0000,0001,0001	✓	
	65535,999,999(Y,x,y)		VXX:CMMS0=65535,9999,9999		CMMS0=65535,9999,9999	✓	
COLOR MATCHING-MEASURED MODE-MEASURED DATA RED	0,1,1 (Y,x,y)		VXX:CMMS1=00000,0001,0001	QVX:CMMS1	CMMS1=00000,0001,0001	✓	
	65535,999,999(Y,x,y)		VXX:CMMS1=65535,9999,9999		CMMS1=65535,9999,9999	✓	
COLOR MATCHING-MEASURED MODE-MEASURED DATA GREEN	0,1,1 (Y,x,y)		VXX:CMMS2=00000,0001,0001	QVX:CMMS2	CMMS2=00000,0001,0001	✓	
	65535,999,999(Y,x,y)		VXX:CMMS2=65535,9999,9999		CMMS2=65535,9999,9999	✓	
COLOR MATCHING-MEASURED MODE-MEASURED DATA BLUE	0,1,1 (Y,x,y)		VXX:CMMS3=00000,0001,0001	QVX:CMMS3	CMMS3=00000,0001,0001	✓	
	65535,999,999(Y,x,y)		VXX:CMMS3=65535,9999,9999		CMMS3=65535,9999,9999	✓	
COLOR MATCHING-MEASURED MODE-MEASURED DATA WHITE	0,1,1 (Y,x,y)		VXX:CMMS4=00000,0001,0001	QVX:CMMS4	CMMS4=00000,0001,0001	✓	
	65535,999,999(Y,x,y)		VXX:CMMS4=65535,9999,9999		CMMS4=65535,9999,9999	✓	
COLOR MATCHING-MEASURED MODE-TARGET DATA RED	0,1,1 (Y,x,y)		VXX:CMTS0=00000,0001,0001	QVX:CMTS0	CMTS0=00000,0001,0001	✓	
	65535,999,999(Y,x,y)		VXX:CMTS0=65535,9999,9999		CMTS0=65535,9999,9999	✓	
COLOR MATCHING-MEASURED MODE-TARGET DATA GREEN	0,1,1 (Y,x,y)		VXX:CMTS1=00000,0001,0001	QVX:CMTS1	CMTS1=00000,0001,0001	✓	
	65535,999,999(Y,x,y)		VXX:CMTS1=65535,9999,9999		CMTS1=65535,9999,9999	✓	
COLOR MATCHING-MEASURED MODE-TARGET DATA BLUE	0,1,1 (Y,x,y)		VXX:CMTS2=00000,0001,0001	QVX:CMTS2	CMTS2=00000,0001,0001	✓	
	65535,999,999(Y,x,y)		VXX:CMTS2=65535,9999,9999		CMTS2=65535,9999,9999	✓	
COLOR MATCHING-MEASURED MODE-TARGET DATA CYAN	0,1,1 (Y,x,y)		VXX:CMTS3=00000,0001,0001	QVX:CMTS3	CMTS3=00000,0001,0001	✓	
	65535,999,999(Y,x,y)		VXX:CMTS3=65535,9999,9999		CMTS3=65535,9999,9999	✓	
COLOR MATCHING-MEASURED MODE-TARGET DATA MAGENTA	0,1,1 (Y,x,y)		VXX:CMTS4=00000,0001,0001	QVX:CMTS4	CMTS4=00000,0001,0001	✓	
	65535,999,999(Y,x,y)		VXX:CMTS4=65535,9999,9999		CMTS4=65535,9999,9999	✓	
COLOR MATCHING-MEASURED MODE-TARGET DATA YELLOW	0,1,1 (Y,x,y)		VXX:CMTS5=00000,0001,0001	QVX:CMTS5	CMTS5=00000,0001,0001	✓	
	65535,999,999(Y,x,y)		VXX:CMTS5=65535,9999,9999		CMTS5=65535,9999,9999	✓	
COLOR MATCHING-MEASURED MODE-TARGET DATA WHITE	0,1,1 (Y,x,y)		VXX:CMTS6=00000,0001,0001	QVX:CMTS6	CMTS6=00000,0001,0001	✓	
	65535,999,999(Y,x,y)		VXX:CMTS6=65535,9999,9999		CMTS6=65535,9999,9999	✓	
COLOR MATCHING-MEASURED MODE-AUTO TESTPATTERN	OFF		VXX:CATI3=+0000	QVX:CATI3	CATI3=+0000	✓	
	ON		VXX:CATI3=+0001		CATI3=+0001	✓	
COLOR MATCHING-MEASURED MODE-BACKUP INPUT SETTING-BACKUP INPUT	EXECUTE		VXX:CRET3=+0001			✓	
BACKUP INPUT SETTING-BACKUP INPUT MODE	PRIMARY		VXX:BACI1=+00001	QVX:BACI1	BACI1=+00001	✓	
	SECONDARY		VXX:BACI1=+00002		BACI1=+00002	✓	
	TOGGLE		VXX:BACI1=+00010		BACI1=+00010	✓	
BACKUP INPUT SETTING-AUTOMATIC SWITCHING	OFF		VXX:BACI6=+00000	QVX:BACI6	BACI6=+00000	✓	
	HDMI1 / HDMI2		VXX:BACI6=+00002		BACI6=+00002	✓	
	HDMI1 / SDI(SLOT1)		VXX:BACI6=+10111		BACI6=+10111	✓	
BACKUP INPUT SETTING-BACKUP INPUT STATUS	DISABLE		VXX:BACI3=+00001	QVX:BACI3	BACI3=+00001	✓	
	ENABLE		VXX:BACI3=+00002		BACI3=+00002	✓	
HDMI IN-HDMI1 SIGNAL LEVEL	INACTIVE		VXX:BACI4=+00000	QVX:BACI4	BACI4=+00000	✓	
	ACTIVE		VXX:BACI4=+00001		BACI4=+00001	✓	
HDMI IN-HDMI1 SIGNAL LEVEL	0-1023		VXX:HSLI1=+00000	QVX:HSLI1	HSLI1=+00000	✓	
	64-940		VXX:HSLI1=+00001		HSLI1=+00001	✓	
	AUTO		VXX:HSLI1=+00002		HSLI1=+00002	✓	
HDMI IN-HDMI2 SIGNAL LEVEL	0-1023		VXX:HSLI2=+00000	QVX:HSLI2	HSLI2=+00000	✓	
	64-940		VXX:HSLI2=+00001		HSLI2=+00001	✓	
	AUTO		VXX:HSLI2=+00002		HSLI2=+00002	✓	
HDMI IN-HDMI1 AUTO GAMMA SELECT	DISABLE		VXX:HAGI1=+00000	QVX:HAGI1	HAGI1=+00000	✓	
	ENABLE		VXX:HAGI1=+00001		HAGI1=+00001	✓	
HDMI IN-HDMI2 AUTO GAMMA SELECT	DISABLE		VXX:HAGI2=+00000	QVX:HAGI2	HAGI2=+00000	✓	
	ENABLE		VXX:HAGI2=+00001		HAGI2=+00001	✓	
HDMI IN-HDMI1 AUTO COLOR SPACE SELECT	DISABLE		VXX:HACI1=+00000	QVX:HACI1	HACI1=+00000	✓	
	ENABLE		VXX:HACI1=+00001		HACI1=+00001	✓	
HDMI IN-HDMI2 AUTO COLOR SPACE SELECT	DISABLE		VXX:HACI2=+00000	QVX:HACI2	HACI2=+00000	✓	
	ENABLE		VXX:HACI2=+00001		HACI2=+00001	✓	
HDMI IN-HDMI1 EQUALIZER	0		VXX:HEQI1=+00000	QVX:HEQI1	HEQI1=+00000	✓	
	1		VXX:HEQI1=+00001		HEQI1=+00001	✓	
	2		VXX:HEQI1=+00002		HEQI1=+00002	✓	
	3		VXX:HEQI1=+00003		HEQI1=+00003	✓	
	4		VXX:HEQI1=+00004		HEQI1=+00004	✓	
	5		VXX:HEQI1=+00005		HEQI1=+00005	✓	
	6		VXX:HEQI1=+00006		HEQI1=+00006	✓	
HDMI IN-HDMI2 EQUALIZER	0		VXX:HEQI2=+00000	QVX:HEQI2	HEQI2=+00000	✓	
	1		VXX:HEQI2=+00001		HEQI2=+00001	✓	
	2		VXX:HEQI2=+00002		HEQI2=+00002	✓	
	3		VXX:HEQI2=+00003		HEQI2=+00003	✓	
	4		VXX:HEQI2=+00004		HEQI2=+00004	✓	
	5		VXX:HEQI2=+00005		HEQI2=+00005	✓	
	6		VXX:HEQI2=+00006		HEQI2=+00006	✓	
	7		VXX:HEQI2=+00007		HEQI2=+00007	✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ24K SERIES							
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RZ14K							
HDMI IN-HDMI1 EDID SELECT	4K/60p 4K/30p 2K 4K/60p/HDR			VXX:HESI1=+0000	QVX:HESI1	HESI1=+0000	✓							
				VXX:HESI1=+00001		HESI1=+00001	✓							
				VXX:HESI1=+00002		HESI1=+00002	✓							
				VXX:HESI1=+00010		HESI1=+00010	✓							
	HDMI IN-HDMI2 EDID SELECT	4K/60p 4K/30p 2K 4K/60p/HDR			VXX:HESI2=+00000	QVX:HESI2	HESI2=+00000	✓						
					VXX:HESI2=+00001		HESI2=+00001	✓						
					VXX:HESI2=+00002		HESI2=+00002	✓						
					VXX:HESI2=+00010		HESI2=+00010	✓						
	HDMI IN-HDMI1 EDID MODE	DEFAULT SCREEN FIT USER			VXX:EDMI3=+00000	QVX:EDMI3	EDMI3=+00000	✓						
					VXX:EDMI3=+00001		EDMI3=+00001	✓						
					VXX:EDMI3=+00010		EDMI3=+00010	✓						
	HDMI IN-HDMI2 EDID MODE	DEFAULT SCREEN FIT USER			VXX:EDMI6=+00000	QVX:EDMI6	EDMI6=+00000	✓						
VXX:EDMI6=+00001					EDMI6=+00001		✓							
VXX:EDMI6=+00010					EDMI6=+00010		✓							
HDMI IN-HDMI* EDID RESOLUTION	HDMI1 HDMI2			VXX:EDRS3=*****;*****;	QVX:EDRS3	EDRS3=*****;*****;	✓							
				VXX:EDRS6=*****;*****;		QVX:EDRS6	EDRS6=*****;*****;	✓						
* PARAMETER				VXX:*****=1024:0768:p		*****=1024:0768:p	✓							
				VXX:*****=1280:0720:p		*****=1280:0720:p	✓							
				VXX:*****=1280:0800:p		*****=1280:0800:p	✓							
				VXX:*****=1280:1024:p		*****=1280:1024:p	✓							
				VXX:*****=1366:0768:p		*****=1366:0768:p	✓							
				VXX:*****=1400:1050:p		*****=1400:1050:p	✓							
				VXX:*****=1440:0900:p		*****=1440:0900:p	✓							
				VXX:*****=1600:0900:p		*****=1600:0900:p	✓							
				VXX:*****=1600:1200:p		*****=1600:1200:p	✓							
				VXX:*****=1680:1050:p		*****=1680:1050:p	✓							
				VXX:*****=1920:1080:p		*****=1920:1080:p	✓							
				VXX:*****=1920:1080:i		*****=1920:1080:i	✓							
				VXX:*****=1920:1200:p		*****=1920:1200:p	✓							
				VXX:*****=2048:1080:p		*****=2048:1080:p	✓							
				VXX:*****=2560:1080:p		*****=2560:1080:p	✓							
				VXX:*****=2560:1440:p		*****=2560:1440:p	✓							
				VXX:*****=2560:1600:p		*****=2560:1600:p	✓							
				VXX:*****=3440:1440:p		*****=3440:1440:p	✓							
				VXX:*****=3840:2400:p		*****=3840:2400:p	✓							
				HDMI IN-HDMI* EDID VERTICAL SCAN FREQUENCY		HDMI1 HDMI2			VXX:EDVI3=*****	QVX:EDVI3	EDVI3=*****	✓		
									VXX:EDVI6=*****		QVX:EDVI6	EDVI6=*****	✓	
						* PARAMETER				VXX:*****=+12000		*****=+12000	✓	
										VXX:*****=+10000		*****=+10000	✓	
										VXX:*****=+06000		*****=+06000	✓	
										VXX:*****=+05000		*****=+05000	✓	
										VXX:*****=+04800		*****=+04800	✓	
										VXX:*****=+03000		*****=+03000	✓	
										VXX:*****=+02500		*****=+02500	✓	
VXX:*****=+02400	*****=+02400	✓												
HDMI IN-HDMI* EDID RESOLUTION / VERTICAL SCAN FREQUENCY	HDMI1 HDMI2				VXX:EDHS1=*****;*****;					QVX:EDHS1		EDHS1=*****;*****;	✓	
					VXX:EDHS2=*****;*****;							QVX:EDHS2	EDHS2=*****;*****;	✓
	* PARAMETER1									VXX:*****=1024:0768;*;*****			*****=1024:0768;*;*****	✓
										VXX:*****=1280:0720;*;*****			*****=1280:0720;*;*****	✓
										VXX:*****=1280:0800;*;*****			*****=1280:0800;*;*****	✓
										VXX:*****=1280:1024;*;*****			*****=1280:1024;*;*****	✓
				VXX:*****=1366:0768;*;*****		*****=1366:0768;*;*****	✓							
				VXX:*****=1400:1050;*;*****		*****=1400:1050;*;*****	✓							
VXX:*****=1440:0900;*;*****				*****=1440:0900;*;*****		✓								
VXX:*****=1600:0900;*;*****				*****=1600:0900;*;*****		✓								
VXX:*****=1600:1200;*;*****				*****=1600:1200;*;*****		✓								
VXX:*****=1680:1050;*;*****				*****=1680:1050;*;*****		✓								
VXX:*****=1920:1080;*;*****				*****=1920:1080;*;*****		✓								
VXX:*****=1920:1200;*;*****				*****=1920:1200;*;*****		✓								
VXX:*****=2048:1080;*;*****				*****=2048:1080;*;*****		✓								
VXX:*****=2560:1080;*;*****				*****=2560:1080;*;*****		✓								
VXX:*****=2560:1440;*;*****				*****=2560:1440;*;*****		✓								
VXX:*****=2560:1600;*;*****				*****=2560:1600;*;*****		✓								
VXX:*****=3440:1440;*;*****	*****=3440:1440;*;*****	✓												
VXX:*****=3840:2400;*;*****	*****=3840:2400;*;*****	✓												
* PARAMETER2				VXX:*****=*****;p;*****		*****=*****;p;*****	✓							
				VXX:*****=*****;j;*****		*****=*****;j;*****	✓							
				VXX:*****=*****;*;12000		*****=*****;*;12000	✓							
				VXX:*****=*****;*;10000		*****=*****;*;10000	✓							
				VXX:*****=*****;*;06000		*****=*****;*;06000	✓							
				VXX:*****=*****;*;05000		*****=*****;*;05000	✓							
				VXX:*****=*****;*;04800		*****=*****;*;04800	✓							
				VXX:*****=*****;*;03000		*****=*****;*;03000	✓							
				VXX:*****=*****;*;02500		*****=*****;*;02500	✓							
				VXX:*****=*****;*;02400		*****=*****;*;02400	✓							
				HDMI IN-HDMI* EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY		HDMI1 HDMI2			VXX:ESHS1=*****;*****;	QVX:ESHS1	ESHS1=*****;*****;	✓		
									VXX:ESHS2=*****;*****;		QVX:ESHS2	ESHS2=*****;*****;	✓	
						* PARAMETER1				VXX:*****=1024:0768;*;*****		*****=1024:0768;*;*****	✓	
										VXX:*****=1280:0720;*;*****		*****=1280:0720;*;*****	✓	
										VXX:*****=1280:0800;*;*****		*****=1280:0800;*;*****	✓	
										VXX:*****=1280:1024;*;*****		*****=1280:1024;*;*****	✓	
VXX:*****=1366:0768;*;*****	*****=1366:0768;*;*****	✓												
VXX:*****=1400:1050;*;*****	*****=1400:1050;*;*****	✓												
VXX:*****=1440:0900;*;*****	*****=1440:0900;*;*****	✓												
VXX:*****=1600:0900;*;*****	*****=1600:0900;*;*****	✓												
VXX:*****=1600:1200;*;*****	*****=1600:1200;*;*****	✓												
VXX:*****=1680:1050;*;*****	*****=1680:1050;*;*****	✓												
VXX:*****=1920:1080;*;*****	*****=1920:1080;*;*****	✓												
VXX:*****=1920:1200;*;*****	*****=1920:1200;*;*****	✓												
VXX:*****=2048:1080;*;*****	*****=2048:1080;*;*****	✓												
VXX:*****=2560:1080;*;*****	*****=2560:1080;*;*****	✓												
VXX:*****=2560:1440;*;*****	*****=2560:1440;*;*****	✓												
VXX:*****=2560:1600;*;*****	*****=2560:1600;*;*****	✓												
VXX:*****=3440:1440;*;*****	*****=3440:1440;*;*****	✓												
VXX:*****=3840:2400;*;*****	*****=3840:2400;*;*****	✓												
* PARAMETER2				VXX:*****=*****;p;*****		*****=*****;p;*****	✓							
				VXX:*****=*****;j;*****		*****=*****;j;*****	✓							
				VXX:*****=*****;*;12000		*****=*****;*;12000	✓							
				VXX:*****=*****;*;10000		*****=*****;*;10000	✓							
				VXX:*****=*****;*;06000		*****=*****;*;06000	✓							
				VXX:*****=*****;*;05000		*****=*****;*;05000	✓							
				VXX:*****=*****;*;04800		*****=*****;*;04800	✓							
				VXX:*****=*****;*;03000		*****=*****;*;03000	✓							
				VXX:*****=*****;*;02500		*****=*****;*;02500	✓							
				VXX:*****=*****;*;02400		*****=*****;*;02400	✓							
DisplayPort IN-SIGNAL LEVEL	AUTO 0-1023 64-940			VXX:DPLI1=+00000	QVX:DPLI1	DPLI1=+00000	✓							
				VXX:DPLI1=+00001		DPLI1=+00001	✓							
				VXX:DPLI1=+00002		DPLI1=+00002	✓							
DisplayPort IN -AUTO GAMMA SELECT	DISABLE ENABLE			VXX:DAGI1=+00000	QVX:DAGI1	DAGI1=+00000	✓							
				VXX:DAGI1=+00001		DAGI1=+00001	✓							
DisplayPort IN - AUTO COLOR SPACE SELECT	DISABLE ENABLE			VXX:DACI1=+00000	QVX:DACI1	DACI1=+00000	✓							
				VXX:DACI1=+00001		DACI1=+00001	✓							
DisplayPort IN-EDID SELECT	4K/60p			VXX:DESI1=+00000	QVX:DESI1	DESI1=+00000	✓							

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ24K SERIES												
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RZ14K												
DisplayPort IN-EDID MODE	4K/30p 2K 4K/60p/HDR			VXX: DESI1=+00001		DESI1=+00001	✓												
				VXX: DESI1=+00002		DESI1=+00002	✓												
				VXX: DESI1=+00010		DESI1=+00010	✓												
	DEFAULT SCREEN FIT USER			VXX: EDMI8=+00000	QVX: EDMI8	EDMI8=+00000	✓												
				VXX: EDMI8=+00001		EDMI8=+00001	✓												
				VXX: EDMI8=+00010		EDMI8=+00010	✓												
	DisplayPort IN-EDID RESOLUTION	1024x768p 1280x720p 1280x800p 1400x1050p 1600x900p 1600x1200p 1920x1080p 1920x1200p 2048x1080p 2560x1080p 2560x1440p 2560x1600p 3440x1440p 3840x2400p			VXX: EDRS8=1024:0768:p	QVX: EDRS8	EDRS8=1024:0768:p	✓											
					VXX: EDRS8=1280:0720:p		EDRS8=1280:0720:p	✓											
					VXX: EDRS8=1280:0800:p		EDRS8=1280:0800:p	✓											
					VXX: EDRS8=1400:1050:p		EDRS8=1400:1050:p	✓											
					VXX: EDRS8=1600:0900:p		EDRS8=1600:0900:p	✓											
					VXX: EDRS8=1600:1200:p		EDRS8=1600:1200:p	✓											
					VXX: EDRS8=1920:1080:p		EDRS8=1920:1080:p	✓											
					VXX: EDRS8=1920:1200:p		EDRS8=1920:1200:p	✓											
					VXX: EDRS8=2048:1080:p		EDRS8=2048:1080:p	✓											
					VXX: EDRS8=2560:1080:p		EDRS8=2560:1080:p	✓											
					VXX: EDRS8=2560:1440:p		EDRS8=2560:1440:p	✓											
					VXX: EDRS8=2560:1600:p		EDRS8=2560:1600:p	✓											
					VXX: EDRS8=3440:1440:p		EDRS8=3440:1440:p	✓											
					VXX: EDRS8=3840:2400:p		EDRS8=3840:2400:p	✓											
					DisplayPort IN-EDID VERTICAL SCAN FREQUENCY	240Hz 120Hz 100Hz 60Hz 50Hz 48Hz 30Hz 25Hz 24Hz			VXX: EDVI8=+24000	QVX: EDVI8	EDVI8=+24000	✓							
	VXX: EDVI8=+12000		EDVI8=+12000	✓															
	VXX: EDVI8=+10000		EDVI8=+10000	✓															
	VXX: EDVI8=+06000		EDVI8=+06000	✓															
VXX: EDVI8=+05000		EDVI8=+05000	✓																
VXX: EDVI8=+04800		EDVI8=+04800	✓																
VXX: EDVI8=+03000		EDVI8=+03000	✓																
VXX: EDVI8=+02500		EDVI8=+02500	✓																
VXX: EDVI8=+02400		EDVI8=+02400	✓																
DisplayPort IN-EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER * PARAMETER1 * PARAMETER2			VXX: EDPS1=*****:*****					QVX: EDPS1	EDPS1=*****:*****	✓								
				VXX: EDPS1=1024:0768:*****		EDPS1=1024:0768:*****	✓												
				VXX: EDPS1=1280:0720:*****		EDPS1=1280:0720:*****	✓												
				VXX: EDPS1=1280:0800:*****		EDPS1=1280:0800:*****	✓												
				VXX: EDPS1=1400:1050:*****		EDPS1=1400:1050:*****	✓												
				VXX: EDPS1=1600:0900:*****		EDPS1=1600:0900:*****	✓												
				VXX: EDPS1=1600:1200:*****		EDPS1=1600:1200:*****	✓												
				VXX: EDPS1=1920:1080:*****		EDPS1=1920:1080:*****	✓												
				VXX: EDPS1=1920:1200:*****		EDPS1=1920:1200:*****	✓												
				VXX: EDPS1=2048:1080:*****		EDPS1=2048:1080:*****	✓												
				VXX: EDPS1=2560:1080:*****		EDPS1=2560:1080:*****	✓												
				VXX: EDPS1=2560:1440:*****		EDPS1=2560:1440:*****	✓												
				VXX: EDPS1=2560:1600:*****		EDPS1=2560:1600:*****	✓												
				VXX: EDPS1=3440:1440:*****		EDPS1=3440:1440:*****	✓												
				VXX: EDPS1=3840:2400:*****		EDPS1=3840:2400:*****	✓												
				VXX: EDPS1=*****:p:*****		EDPS1=*****:p:*****	✓												
				VXX: EDPS1=*****:j:*****		EDPS1=*****:j:*****	✓												
				VXX: EDPS1=*****:12000		EDPS1=*****:12000	✓												
				VXX: EDPS1=*****:10000		EDPS1=*****:10000	✓												
				VXX: EDPS1=*****:06000		EDPS1=*****:06000	✓												
VXX: EDPS1=*****:05000		EDPS1=*****:05000	✓																
VXX: EDPS1=*****:04800		EDPS1=*****:04800	✓																
VXX: EDPS1=*****:03000		EDPS1=*****:03000	✓																
VXX: EDPS1=*****:02500		EDPS1=*****:02500	✓																
VXX: EDPS1=*****:02400		EDPS1=*****:02400	✓																
DisplayPort IN-EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER * PARAMETER1 * PARAMETER2			VXX: ESHS1=*****:*****	QVX: ESHS1	ESHS1=*****:*****	✓												
				VXX: ESHS1=1024:0768:*****		ESHS1=1024:0768:*****	✓												
				VXX: ESHS1=1280:0720:*****		ESHS1=1280:0720:*****	✓												
				VXX: ESHS1=1280:0800:*****		ESHS1=1280:0800:*****	✓												
				VXX: ESHS1=1400:1050:*****		ESHS1=1400:1050:*****	✓												
				VXX: ESHS1=1600:0900:*****		ESHS1=1600:0900:*****	✓												
				VXX: ESHS1=1600:1200:*****		ESHS1=1600:1200:*****	✓												
				VXX: ESHS1=1920:1080:*****		ESHS1=1920:1080:*****	✓												
				VXX: ESHS1=1920:1200:*****		ESHS1=1920:1200:*****	✓												
				VXX: ESHS1=2048:1080:*****		ESHS1=2048:1080:*****	✓												
				VXX: ESHS1=2560:1080:*****		ESHS1=2560:1080:*****	✓												
				VXX: ESHS1=2560:1440:*****		ESHS1=2560:1440:*****	✓												
				VXX: ESHS1=2560:1600:*****		ESHS1=2560:1600:*****	✓												
				VXX: ESHS1=3440:1440:*****		ESHS1=3440:1440:*****	✓												
				VXX: ESHS1=3840:2400:*****		ESHS1=3840:2400:*****	✓												
				VXX: ESHS1=*****:p:*****		ESHS1=*****:p:*****	✓												
				VXX: ESHS1=*****:j:*****		ESHS1=*****:j:*****	✓												
				VXX: ESHS1=*****:12000		ESHS1=*****:12000	✓												
				VXX: ESHS1=*****:10000		ESHS1=*****:10000	✓												
				VXX: ESHS1=*****:06000		ESHS1=*****:06000	✓												
VXX: ESHS1=*****:05000		ESHS1=*****:05000	✓																
VXX: ESHS1=*****:04800		ESHS1=*****:04800	✓																
VXX: ESHS1=*****:03000		ESHS1=*****:03000	✓																
VXX: ESHS1=*****:02500		ESHS1=*****:02500	✓																
VXX: ESHS1=*****:02400		ESHS1=*****:02400	✓																
SLOT : SDI RESOLUTION	* PARAMETER * PARAMETER1, 2 * PARAMETER3			VXX: *****=VXX: *****+*****	QVX: *****=QVX: *****	*****=*****+*****	✓												
				VXX: SLSS1=VXX: SRSS1=+*****		SLSS1=SRSS1=+*****	✓												
				VXX: *****=VXX: *****+00000		*****=*****+00000	✓												
				VXX: *****=VXX: *****+00005		*****=*****+00005	✓												
				VXX: *****=VXX: *****+00006		*****=*****+00006	✓												
				VXX: *****=VXX: *****+00009		*****=*****+00009	✓												
				VXX: *****=VXX: *****+00011		*****=*****+00011	✓												
				VXX: *****=VXX: *****+00013		*****=*****+00013	✓												
				SLOT - SDI IN - AUTO GAMMA SELECT	DISABLE ENABLE			VXX: SLSS1=VXX: SAGI1=+00000	QVX: SLSS1=SAGI1	SLSS1=SAGI1=+00000	✓								
								VXX: SLSS1=VXX: SAGI1=+00001		SLSS1=SAGI1=+00001	✓								
								SLOT - SDI IN - AUTO COLOR SPACE SELECT	DISABLE ENABLE			VXX: SLSS1=VXX: SACT1=+00000	QVX: SLSS1=SACT1	SLSS1=SACT1=+00000	✓				
												VXX: SLSS1=VXX: SACT1=+00001		SLSS1=SACT1=+00001	✓				
												SLOT : SDI : SDI 4K DIVISION	* PARAMETER * PARAMETER1, 2 (ET-MDN12G10) * PARAMETER3			VXX: *****=VXX: *****+*****	QVX: *****=QVX: *****	*****=*****+*****	✓
																VXX: SLSS1=VXX: SKSI1=+*****		SLSS1=SKSI1=+*****	✓
																VXX: *****=VXX: *****+00000		*****=*****+00000	✓
																VXX: *****=VXX: *****+00001		*****=*****+00001	✓
																VXX: *****=VXX: *****+00002		*****=*****+00002	✓
																VXX: *****=VXX: *****+*****		*****=*****+*****	✓
				SLOT : SDI : SDI SYSTEM SELECTOR	* PARAMETER * PARAMETER1, 2 * PARAMETER3											VXX: *****=VXX: *****+*****	QVX: *****=QVX: *****	*****=*****+*****	✓
																VXX: SLSS1=VXX: SYSS1=1:1:*****	QVX: SLSS1=QVX: SYSS1=1:1	SLSS1=SYSS1=1:1:*****	✓
VXX: *****=VXX: SYSS1=*:*****:00000		*****=SYSS1=*:*****:00000	✓																
VXX: *****=VXX: SYSS1=*:*****:00001		*****=SYSS1=*:*****:00001	✓																
SLOT : SDI : BIT DEPTH	* PARAMETER * PARAMETER1, 2 * PARAMETER3			VXX: *****=VXX: *****+*****	QVX: *****=QVX: *****	*****=*****+*****	✓												
				VXX: SLSS1=VXX: SBTT1=+*****		SLSS1=SBTT1=+*****	✓												
				VXX: *****=VXX: *****+00000		*****=*****+00000	✓												
				VXX: *****=VXX: *****+00001		*****=*****+00001	✓												
SLOT : SDI : SIGNAL LEVEL	* PARAMETER * PARAMETER1, 2 * PARAMETER3			VXX: *****=VXX: *****+*****	QVX: *****=QVX: *****	*****=*****+*****	✓												
				VXX: SLSS1=VXX: SSSL1=+*****		SLSS1=SSL1=+*****	✓												
				VXX: *****=VXX: *****+00000		*****=*****+00000	✓												
				VXX: *****=VXX: *****+00001		*****=*****+00001	✓												
				VXX: *****=VXX: *****+00002		*****=*****+00002	✓												

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ24K SERIES	
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RZ14K	
DISPLAY OPTION	SLOT : DIGITAL LINK : SIGNAL LEVEL	0-1023 64-940 AUTO		VXX:SLSS1=VXX:DKLI1=+00000 VXX:SLSS1=VXX:DKLI1=+00001 VXX:SLSS1=VXX:DKLI1=+00002	QVX:SLSS1=QVX:DKLI1	SLSS1=DKLI1=+00000 SLSS1=DKLI1=+00001 SLSS1=DKLI1=+00002	✓ ✓ ✓	
	SLOT : DIGITAL LINK : AUTO GAMMA SELECT	DISABLE ENABLE		VXX:SLSS1=VXX:LAGI1=+00000 VXX:SLSS1=VXX:LAGI1=+00001	QVX:SLSS1=QVX:LAGI1	SLSS1=LAGI1=+00000 SLSS1=LAGI1=+00001	✓ ✓	
	SLOT : DIGITAL LINK : AUTO COLOR SPACE SELECT	DISABLE ENABLE		VXX:SLSS1=VXX:LACI1=+00000 VXX:SLSS1=VXX:LACI1=+00001	QVX:SLSS1=QVX:LACI1	SLSS1=LACI1=+00000 SLSS1=LACI1=+00001	✓ ✓	
	SLOT : DIGITAL LINK : EDID SELECT	4K/60p/SDR 4K/30p 2K 4K/30p/HDR		VXX:SLSS1=VXX:LESI1=+00000 VXX:SLSS1=VXX:LESI1=+00001 VXX:SLSS1=VXX:LESI1=+00002 VXX:SLSS1=VXX:LESI1=+00011	QVX:SLSS1=QVX:LESI1	SLSS1=LESI1=+00000 SLSS1=LESI1=+00001 SLSS1=LESI1=+00002 SLSS1=LESI1=+00011	✓ ✓ ✓ ✓	
	SLOT : DIGITAL LINK : EDID MODE	DEFAULT SCREEN FIT USER		VXX:SLSS1=VXX:EDMI4=+00000 VXX:SLSS1=VXX:EDMI4=+00001 VXX:SLSS1=VXX:EDMI4=+00010	QVX:SLSS1=QVX:EDMI4	SLSS1=EDMI4=+00000 SLSS1=EDMI4=+00001 SLSS1=EDMI4=+00010	✓ ✓ ✓	
	SLOT : DIGITAL LINK : EDID RESOLUTION		1024x768 1280x720 1280x800 1280x1024 1366x768 1400x1050 1440x900 1600x900 1600x1200 1680x1050 1920x1080 1920x1200 2048x1080 2560x1080 2560x1440 2560x1600 3840x2400	* PARAMETER	VXX:SLSS1=VXX:EDRS4=1024:0768:* VXX:SLSS1=VXX:EDRS4=1280:0720:* VXX:SLSS1=VXX:EDRS4=1280:0800:* VXX:SLSS1=VXX:EDRS4=1280:1024:* VXX:SLSS1=VXX:EDRS4=1366:0768:* VXX:SLSS1=VXX:EDRS4=1400:1050:* VXX:SLSS1=VXX:EDRS4=1440:0900:* VXX:SLSS1=VXX:EDRS4=1600:0900:* VXX:SLSS1=VXX:EDRS4=1600:1200:* VXX:SLSS1=VXX:EDRS4=1680:1050:* VXX:SLSS1=VXX:EDRS4=1920:1080:* VXX:SLSS1=VXX:EDRS4=1920:1200:* VXX:SLSS1=VXX:EDRS4=2048:1080:* VXX:SLSS1=VXX:EDRS4=2560:1080:* VXX:SLSS1=VXX:EDRS4=2560:1440:* VXX:SLSS1=VXX:EDRS4=2560:1600:* VXX:SLSS1=VXX:EDRS4=3840:2400:*	QVX:SLSS1=QVX:EDRS4	SLSS1=EDRS4=1024:0768:* SLSS1=EDRS4=1280:0720:* SLSS1=EDRS4=1280:0800:* SLSS1=EDRS4=1280:1024:* SLSS1=EDRS4=1366:0768:* SLSS1=EDRS4=1400:1050:* SLSS1=EDRS4=1440:0900:* SLSS1=EDRS4=1600:0900:* SLSS1=EDRS4=1600:1200:* SLSS1=EDRS4=1680:1050:* SLSS1=EDRS4=1920:1080:* SLSS1=EDRS4=1920:1200:* SLSS1=EDRS4=2048:1080:* SLSS1=EDRS4=2560:1080:* SLSS1=EDRS4=2560:1440:* SLSS1=EDRS4=2560:1600:* SLSS1=EDRS4=3840:2400:*	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
				* PARAMETER1	Progressive Interface	VXX:SLSS1=VXX:EDRS4=*****:p VXX:SLSS1=VXX:EDRS4=*****:i	SLSS1=EDRS4=*****:p SLSS1=EDRS4=*****:i	✓ ✓
	SLOT : DIGITAL LINK : EDID VERTICAL SCAN FREQUENCY			* PARAMETER	VXX:SLSS1=VXX:EDVI4=+*****	QVX:SLSS1=QVX:EDVI4	SLSS1=EDVI4=+*****	✓
			120Hz 100Hz 60Hz 50Hz 48Hz 30Hz 25Hz 24Hz	* PARAMETER1	VXX:SLSS1=VXX:EDVI4=+12000 VXX:SLSS1=VXX:EDVI4=+10000 VXX:SLSS1=VXX:EDVI4=+06000 VXX:SLSS1=VXX:EDVI4=+05000 VXX:SLSS1=VXX:EDVI4=+04800 VXX:SLSS1=VXX:EDVI4=+03000 VXX:SLSS1=VXX:EDVI4=+02500 VXX:SLSS1=VXX:EDVI4=+02400		SLSS1=EDVI4=+12000 SLSS1=EDVI4=+10000 SLSS1=EDVI4=+06000 SLSS1=EDVI4=+05000 SLSS1=EDVI4=+04800 SLSS1=EDVI4=+03000 SLSS1=EDVI4=+02500 SLSS1=EDVI4=+02400	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	SLOT : DIGITAL LINK : EDID RESOLUTION / VERTICAL SCAN FREQUENCY		1024x768 1280x720 1280x800 1280x1024 1366x768 1400x1050 1440x900 1600x900 1600x1200 1680x1050 1920x1080 1920x1200 2048x1080 2560x1080 2560x1440 2560x1600 3840x2400	* PARAMETER	VXX:SLSS1=VXX:EDLS1=1024:0768:*:***** VXX:SLSS1=VXX:EDLS1=1280:0720:*:***** VXX:SLSS1=VXX:EDLS1=1280:0800:*:***** VXX:SLSS1=VXX:EDLS1=1280:1024:*:***** VXX:SLSS1=VXX:EDLS1=1366:0768:*:***** VXX:SLSS1=VXX:EDLS1=1400:1050:*:***** VXX:SLSS1=VXX:EDLS1=1440:0900:*:***** VXX:SLSS1=VXX:EDLS1=1600:0900:*:***** VXX:SLSS1=VXX:EDLS1=1600:1200:*:***** VXX:SLSS1=VXX:EDLS1=1680:1050:*:***** VXX:SLSS1=VXX:EDLS1=1920:1080:*:***** VXX:SLSS1=VXX:EDLS1=1920:1200:*:***** VXX:SLSS1=VXX:EDLS1=2048:1080:*:***** VXX:SLSS1=VXX:EDLS1=2560:1080:*:***** VXX:SLSS1=VXX:EDLS1=2560:1440:*:***** VXX:SLSS1=VXX:EDLS1=2560:1600:*:***** VXX:SLSS1=VXX:EDLS1=3840:2400:*:*****	QVX:SLSS1=QVX:EDLS1	SLSS1=EDLS1=1024:0768:*:***** SLSS1=EDLS1=1280:0720:*:***** SLSS1=EDLS1=1280:0800:*:***** SLSS1=EDLS1=1280:1024:*:***** SLSS1=EDLS1=1366:0768:*:***** SLSS1=EDLS1=1400:1050:*:***** SLSS1=EDLS1=1440:0900:*:***** SLSS1=EDLS1=1600:0900:*:***** SLSS1=EDLS1=1600:1200:*:***** SLSS1=EDLS1=1680:1050:*:***** SLSS1=EDLS1=1920:1080:*:***** SLSS1=EDLS1=1920:1200:*:***** SLSS1=EDLS1=2048:1080:*:***** SLSS1=EDLS1=2560:1080:*:***** SLSS1=EDLS1=2560:1440:*:***** SLSS1=EDLS1=2560:1600:*:***** SLSS1=EDLS1=3840:2400:*:*****	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
				* PARAMETER1	Progressive Interface	VXX:SLSS1=VXX:EDLS1=*****:p VXX:SLSS1=VXX:EDLS1=*****:i	SLSS1=EDLS1=*****:p SLSS1=EDLS1=*****:i	✓ ✓
			120Hz 100Hz 60Hz 50Hz 48Hz 30Hz 25Hz 24Hz	* PARAMETER2	VXX:SLSS1=VXX:EDLS1=*****:*:12000 VXX:SLSS1=VXX:EDLS1=*****:*:10000 VXX:SLSS1=VXX:EDLS1=*****:*:06000 VXX:SLSS1=VXX:EDLS1=*****:*:05000 VXX:SLSS1=VXX:EDLS1=*****:*:04800 VXX:SLSS1=VXX:EDLS1=*****:*:03000 VXX:SLSS1=VXX:EDLS1=*****:*:02500 VXX:SLSS1=VXX:EDLS1=*****:*:02400		SLSS1=EDLS1=*****:*:12000 SLSS1=EDLS1=*****:*:10000 SLSS1=EDLS1=*****:*:06000 SLSS1=EDLS1=*****:*:05000 SLSS1=EDLS1=*****:*:04800 SLSS1=EDLS1=*****:*:03000 SLSS1=EDLS1=*****:*:02500 SLSS1=EDLS1=*****:*:02400	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	SLOT : DIGITAL LINK : EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY		1024x768 1280x720 1280x800 1280x1024 1366x768 1400x1050 1440x900 1600x900 1600x1200 1680x1050 1920x1080 1920x1200 2048x1080 2560x1440 2560x1080 2560x1600 3840x2400	* PARAMETER		QVX:SLSS1=QVX:ESLS1	SLSS1=ESLS1=1024:0768:*:***** SLSS1=ESLS1=1280:0720:*:***** SLSS1=ESLS1=1280:0800:*:***** SLSS1=ESLS1=1280:1024:*:***** SLSS1=ESLS1=1366:0768:*:***** SLSS1=ESLS1=1400:1050:*:***** SLSS1=ESLS1=1440:0900:*:***** SLSS1=ESLS1=1600:0900:*:***** SLSS1=ESLS1=1600:1200:*:***** SLSS1=ESLS1=1680:1050:*:***** SLSS1=ESLS1=1920:1080:*:***** SLSS1=ESLS1=1920:1200:*:***** SLSS1=ESLS1=2048:1080:*:***** SLSS1=ESLS1=2560:1440:*:***** SLSS1=ESLS1=2560:1080:*:***** SLSS1=ESLS1=2560:1600:*:***** SLSS1=ESLS1=3840:2400:*:*****	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
				* PARAMETER1	Progressive Interface		SLSS1=ESLS1=*****:i:***** SLSS1=ESLS1=*****:p:*****	✓ ✓
			120Hz 100Hz 60Hz 50Hz 48Hz 30Hz 25Hz 24Hz	* PARAMETER2			SLSS1=ESLS1=*****:*:12000 SLSS1=ESLS1=*****:*:10000 SLSS1=ESLS1=*****:*:06000 SLSS1=ESLS1=*****:*:05000 SLSS1=ESLS1=*****:*:04800 SLSS1=ESLS1=*****:*:03000 SLSS1=ESLS1=*****:*:02500 SLSS1=ESLS1=*****:*:02400	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	SLOT : DIGITAL LINK : DIGITAL LINK OUT	DISABLE ENABLE			VXX:SLSS1=VXX:DLOI1=+00000 VXX:SLSS1=VXX:DLOI1=+00001	QVX:SLSS1=QVX:DLOI1	SLSS1=DLOI1=+00000 SLSS1=DLOI1=+00001	✓ ✓
	SLOT : 12G SDI OPT : RESOLUTION			* PARAMETER	VXX:*****=VXX:*****:*****	QVX:*****=QVX:*****	*****=*****+*****	✓
			12G SDI OPT1 12G SDI OPT2	* PARAMETER1, 2	VXX:SLSS1=VXX:ORET1=+***** VXX:SLSS1=VXX:ORET2=+*****		SLSS1=ORET1=+***** SLSS1=ORET2=+*****	✓ ✓
			AUTO 1280x720p 1920x1080i 1920x1080p 1920x1080F 2048x1080p 3840x2160p 4096x2160p	* PARAMETER3	VXX:*****=VXX:*****+00000 VXX:*****=VXX:*****+00003 VXX:*****=VXX:*****+00005 VXX:*****=VXX:*****+00006 VXX:*****=VXX:*****+00007 VXX:*****=VXX:*****+00009 VXX:*****=VXX:*****+00011 VXX:*****=VXX:*****+00013		*****=*****+00000 *****=*****+00003 *****=*****+00005 *****=*****+00006 *****=*****+00007 *****=*****+00009 *****=*****+00011 *****=*****+00013	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	SLOT : 12G SDI OPT : SYSTEM SELECTOR			* PARAMETER	VXX:*****=VXX:*****:*****	QVX:*****=QVX:*****	*****=*****+*****	✓
			12G SDI OPT1 12G SDI OPT2	* PARAMETER1, 2	VXX:SLSS1=VXX:OSYI1=+***** VXX:SLSS1=VXX:OSYI2=+*****		SLSS1=OSYI1=+***** SLSS1=OSYI2=+*****	✓ ✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ24K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	
		* PARAMETER3	AUTO	VXX:*****=VXX:*****=+00000		*****=*****+00000	✓
			RGB	VXX:*****=VXX:*****=+00001		*****=*****+00001	✓
SLOT : 12G SDI OPT : BIT DEPTH		* PARAMETER	YPbPr 4:4:4	VXX:*****=VXX:*****=+00002		*****=*****+00002	✓
			YPbPr 4:2:2	VXX:*****=VXX:*****=+00003		*****=*****+00003	✓
		* PARAMETER1, 2	12G SDI OPT1	VXX:*****=VXX:*****=	QVX:*****=QVX:*****	*****=*****+*****	✓
			12G SDI OPT2	VXX:SLSS1=VXX:OBTT1=*****		SLSS1=OBTT1=+*****	✓
		* PARAMETER3	AUTO	VXX:*****=VXX:*****=+00000		*****=*****+00000	✓
			12-bit	VXX:*****=VXX:*****=+00001		*****=*****+00001	✓
SLOT : 12G SDI OPT : SIGNAL LEVEL		* PARAMETER	10-bit	VXX:*****=VXX:*****=+00002		*****=*****+00002	✓
				VXX:*****=VXX:*****=	QVX:*****=QVX:*****	*****=*****+*****	✓
		* PARAMETER1, 2	12G SDI OPT1	VXX:SLSS1=VXX:OSLI1=*****		SLSS1=OSLI1=+*****	✓
			12G SDI OPT2	VXX:SLSS1=VXX:OSLI2=*****		SLSS1=OSLI2=+*****	✓
		* PARAMETER3	64-940	VXX:*****=VXX:*****=+00000		*****=*****+00000	✓
			4-1019	VXX:*****=VXX:*****=+00001		*****=*****+00001	✓
SLOT : 12G SDI OPT : AUTO GAMMA SELECT		DISABLE	AUTO	VXX:SLSS1=VXX:OAGI1=+00000	QVX:SLSS1=OAGI1	SLSS1=OAGI1=+00000	✓
			ENABLE	VXX:SLSS1=VXX:OAGI1=+00001		SLSS1=OAGI1=+00001	✓
SLOT : 12G SDI OPT : AUTO COLOR SPACE SELECT		DISABLE		VXX:SLSS1=VXX:OACI1=+00000	QVX:SLSS1=OACI1	SLSS1=OACI1=+00000	✓
			ENABLE	VXX:SLSS1=VXX:OACI1=+00001		SLSS1=OACI1=+00001	✓
SLOT : 12G SDI OPT : SDI OPT OUT		* PARAMETER		VXX:OOMS1=; ; *****	QVX:OOMS1=; ; *	OOMS1=; ; *****	✓
			* PARAMETER1	SLOT1	VXX:OOMS1=1; ; *****		OOMS1=1; ; *****
		* PARAMETER1	SLOT2	VXX:OOMS1=2; ; *****		OOMS1=2; ; *****	✓
			SFP2	VXX:OOMS1=; ; 2; *****		OOMS1=; ; 2; *****	✓
		* PARAMETER3	DISABLE	VXX:OOMS1=; ; *; 00000		OOMS1=; ; *; 00000	✓
			ENABLE	VXX:OOMS1=; ; *; 00001		OOMS1=; ; *; 00001	✓
SLOT : PressIT : SIGNAL LEVEL		64-940		VXX:SLSS1=VXX:WSLI1=+00000	QVX:SLSS1=QVX:WSLI1	SLSS1=WSLI1=+00000	✓
			0-1023	VXX:SLSS1=VXX:WSLI1=+00001		SLSS1=WSLI1=+00001	✓
SLOT : 3rd Party Board : SIGNAL LEVEL		AUTO		VXX:SLSS1=VXX:WSLI1=+00002		SLSS1=WSLI1=+00002	✓
			64-940	VXX:SLSS1=VXX:USLI1=+00000	QVX:SLSS1=QVX:USLI1	SLSS1=USLI1=+00000	✓
		0-1023		VXX:SLSS1=VXX:USLI1=+00001		SLSS1=USLI1=+00001	✓
			AUTO	VXX:SLSS1=VXX:USLI1=+00002		SLSS1=USLI1=+00002	✓
SLOT : 3rd Party Board : AUTO GAMMA SELECT		DISABLE		VXX:SLSS1=VXX:UAGI1=+00000	QVX:SLSS1=QVX:UAGI1	SLSS1=UAGI1=+00000	✓
			ENABLE	VXX:SLSS1=VXX:UAGI1=+00001		SLSS1=UAGI1=+00001	✓
SLOT : 3rd Party Board : AUTO COLOR SPACE SELECT		DISABLE		VXX:SLSS1=VXX:UACI1=+00000	QVX:SLSS1=QVX:UACI1	SLSS1=UACI1=+00000	✓
			ENABLE	VXX:SLSS1=VXX:UACI1=+00001		SLSS1=UACI1=+00001	✓
SLOT : 3rd Party Board : EQUALIZER		0		VXX:SLSS1=VXX:UEQI1=+00000	QVX:SLSS1=QVX:UEQI1	SLSS1=VXX:UEQI1=+00000	✓
			1	VXX:SLSS1=VXX:UEQI1=+00001		SLSS1=VXX:UEQI1=+00001	✓
		2		VXX:SLSS1=VXX:UEQI1=+00002		SLSS1=VXX:UEQI1=+00002	✓
			3	VXX:SLSS1=VXX:UEQI1=+00003		SLSS1=VXX:UEQI1=+00003	✓
		4		VXX:SLSS1=VXX:UEQI1=+00004		SLSS1=VXX:UEQI1=+00004	✓
			5	VXX:SLSS1=VXX:UEQI1=+00005		SLSS1=VXX:UEQI1=+00005	✓
		6		VXX:SLSS1=VXX:UEQI1=+00006		SLSS1=VXX:UEQI1=+00006	✓
			7	VXX:SLSS1=VXX:UEQI1=+00007		SLSS1=VXX:UEQI1=+00007	✓
SLOT : 3rd Party Board : EDID SELECT		4K/60p/SDR		VXX:SLSS1=VXX:UESI1=+00000	QVX:SLSS1=QVX:UESI1	SLSS1=UESI1=+00000	✓
			4K/30p	VXX:SLSS1=VXX:UESI1=+00001		SLSS1=UESI1=+00001	✓
		2K		VXX:SLSS1=VXX:UESI1=+00002		SLSS1=UESI1=+00002	✓
			4K/60p/HDR	VXX:SLSS1=VXX:UESI1=+00010		SLSS1=UESI1=+00010	✓
SLOT : 3rd Party Board : EDID MODE		DEFAULT		VXX:SLSS1=VXX:EDMIB=+00000	QVX:SLSS1=QVX:EDMIB	SLSS1=EDMIB=+00000	✓
			SCREEN FIT	VXX:SLSS1=VXX:EDMIB=+00001		SLSS1=EDMIB=+00001	✓
		USER		VXX:SLSS1=VXX:EDMIB=+00010		SLSS1=EDMIB=+00010	✓
			SLOT : 3rd Party Board : EDID RESOLUTION	1024x768	VXX:SLSS1=VXX:EDRSB=1024:0768;*	QVX:SLSS1=QVX:EDRSB	SLSS1=EDRSB=1024:0768;*
		1280x720		VXX:SLSS1=VXX:EDRSB=1280:0720;*		SLSS1=EDRSB=1280:0720;*	✓
			1280x800	VXX:SLSS1=VXX:EDRSB=1280:0800;*		SLSS1=EDRSB=1280:0800;*	✓
		1280x1024		VXX:SLSS1=VXX:EDRSB=1280:1024;*		SLSS1=EDRSB=1280:1024;*	✓
			1366x768	VXX:SLSS1=VXX:EDRSB=1366:0768;*		SLSS1=EDRSB=1366:0768;*	✓
		1400x1050		VXX:SLSS1=VXX:EDRSB=1400:1050;*		SLSS1=EDRSB=1400:1050;*	✓
			1440x900	VXX:SLSS1=VXX:EDRSB=1440:0900;*		SLSS1=EDRSB=1440:0900;*	✓
		1600x900		VXX:SLSS1=VXX:EDRSB=1600:0900;*		SLSS1=EDRSB=1600:0900;*	✓
			1600x1200	VXX:SLSS1=VXX:EDRSB=1600:1200;*		SLSS1=EDRSB=1600:1200;*	✓
		1680x1050		VXX:SLSS1=VXX:EDRSB=1680:1050;*		SLSS1=EDRSB=1680:1050;*	✓
			1920x1080	VXX:SLSS1=VXX:EDRSB=1920:1080;*		SLSS1=EDRSB=1920:1080;*	✓
		1920x1200		VXX:SLSS1=VXX:EDRSB=1920:1200;*		SLSS1=EDRSB=1920:1200;*	✓
			2048x1080	VXX:SLSS1=VXX:EDRSB=2048:1080;*		SLSS1=EDRSB=2048:1080;*	✓
		2560x1080		VXX:SLSS1=VXX:EDRSB=2560:1080;*		SLSS1=EDRSB=2560:1080;*	✓
			2560x1440	VXX:SLSS1=VXX:EDRSB=2560:1440;*		SLSS1=EDRSB=2560:1440;*	✓
		2560x1600		VXX:SLSS1=VXX:EDRSB=2560:1600;*		SLSS1=EDRSB=2560:1600;*	✓
			3440x1440	VXX:SLSS1=VXX:EDRSB=3440:1440;*		SLSS1=EDRSB=3440:1440;*	✓
		3840x2400		VXX:SLSS1=VXX:EDRSB=3840:2400;*		SLSS1=EDRSB=3840:2400;*	✓
			* PARAMETER1	Progressive Interface	VXX:SLSS1=VXX:EDRSB=*****;p		SLSS1=EDRSB=*****;p
		* PARAMETER		VXX:SLSS1=VXX:EDRSB=*****;i		SLSS1=EDRSB=*****;i	✓
			SLOT : 3rd Party Board : EDID VERTICAL SCAN FREQUENCY		VXX:SLSS1=VXX:EDVIB=+*****	QVX:SLSS1=QVX:EDVIB	SLSS1=EDVIB=+*****
		120Hz		VXX:SLSS1=VXX:EDVIB=+12000		SLSS1=EDVIB=+12000	✓
			100Hz	VXX:SLSS1=VXX:EDVIB=+10000		SLSS1=EDVIB=+10000	✓
		60Hz		VXX:SLSS1=VXX:EDVIB=+06000		SLSS1=EDVIB=+06000	✓
			50Hz	VXX:SLSS1=VXX:EDVIB=+05000		SLSS1=EDVIB=+05000	✓
		48Hz		VXX:SLSS1=VXX:EDVIB=+04800		SLSS1=EDVIB=+04800	✓
			30Hz	VXX:SLSS1=VXX:EDVIB=+03000		SLSS1=EDVIB=+03000	✓
		25Hz		VXX:SLSS1=VXX:EDVIB=+02500		SLSS1=EDVIB=+02500	✓
			24Hz	VXX:SLSS1=VXX:EDVIB=+02400		SLSS1=EDVIB=+02400	✓
SLOT : 3rd Party Board : EDID RESOLUTION / VERTICAL SCAN FREQUENCY		1024x768		VXX:SLSS1=VXX:EDUS1=1024:0768;*;*****	QVX:SLSS1=QVX:EDUS1	SLSS1=EDUS1=1024:0768;*;*****	✓
			1280x720	VXX:SLSS1=VXX:EDUS1=1280:0720;*;*****		SLSS1=EDUS1=1280:0720;*;*****	✓
		1280x800		VXX:SLSS1=VXX:EDUS1=1280:0800;*;*****		SLSS1=EDUS1=1280:0800;*;*****	✓
			1280x1024	VXX:SLSS1=VXX:EDUS1=1280:1024;*;*****		SLSS1=EDUS1=1280:1024;*;*****	✓
		1366x768		VXX:SLSS1=VXX:EDUS1=1366:0768;*;*****		SLSS1=EDUS1=1366:0768;*;*****	✓
			1400x1050	VXX:SLSS1=VXX:EDUS1=1400:1050;*;*****		SLSS1=EDUS1=1400:1050;*;*****	✓
		1440x900		VXX:SLSS1=VXX:EDUS1=1440:0900;*;*****		SLSS1=EDUS1=1440:0900;*;*****	✓
			1600x900	VXX:SLSS1=VXX:EDUS1=1600:0900;*;*****		SLSS1=EDUS1=1600:0900;*;*****	✓
		1600x1200		VXX:SLSS1=VXX:EDUS1=1600:1200;*;*****		SLSS1=EDUS1=1600:1200;*;*****	✓
			1680x1050	VXX:SLSS1=VXX:EDUS1=1680:1050;*;*****		SLSS1=EDUS1=1680:1050;*;*****	✓
		1920x1080		VXX:SLSS1=VXX:EDUS1=1920:1080;*;*****		SLSS1=EDUS1=1920:1080;*;*****	✓
			1920x1200	VXX:SLSS1=VXX:EDUS1=1920:1200;*;*****		SLSS1=EDUS1=1920:1200;*;*****	✓
		2048x1080		VXX:SLSS1=VXX:EDUS1=2048:1080;*;*****		SLSS1=EDUS1=2048:1080;*;*****	✓
			2560x1080	VXX:SLSS1=VXX:EDUS1=2560:1080;*;*****		SLSS1=EDUS1=2560:1080;*;*****	✓
		2560x1440		VXX:SLSS1=VXX:EDUS1=2560:1440;*;*****		SLSS1=EDUS1=2560:1440;*;*****	✓
			2560x1600	VXX:SLSS1=VXX:EDUS1=2560:1600;*;*****		SLSS1=EDUS1=2560:1600;*;*****	✓
		3440x1440		VXX:SLSS1=VXX:EDUS1=3440:1440;*;*****		SLSS1=EDUS1=3440:1440;*;*****	✓
			3840x2400	VXX:SLSS1=VXX:EDUS1=3840:2400;*;*****		SLSS1=EDUS1=3840:2400;*;*****	✓
		* PARAMETER1	Progressive Interface	VXX:SLSS1=VXX:EDUS1=*****;p		SLSS1=EDUS1=*****;p	✓
				VXX:SLSS1=VXX:EDUS1=*****;i		SLSS1=EDUS1=*****;i	✓
SLOT : 3rd Party Board : EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY		120Hz		VXX:SLSS1=VXX:EDUS1=*****;*:12000	QVX:SLSS1=QVX:ESUS1	SLSS1=EDUS1=*****;*:12000	✓
			100Hz	VXX:SLSS1=VXX:EDUS1=*****;*:10000		SLSS1=EDUS1=*****;*:10000	✓
		60Hz		VXX:SLSS1=VXX:EDUS1=*****;*:06000		SLSS1=EDUS1=*****;*:06000	✓
			50Hz	VXX:SLSS1=VXX:EDUS1=*****;*:05000		SLSS1=EDUS1=*****;*:05000	✓
		48Hz		VXX:SLSS1=VXX:EDUS1=*****;*:04800		SLSS1=EDUS1=*****;*:04800	✓
			30Hz	VXX:SLSS1=VXX:EDUS1=*****;*:03000		SLSS1=EDUS1=*****;*:03000	✓
		25Hz		VXX:SLSS1=VXX:EDUS1=*****;*:02500		SLSS1=EDUS1=*****;*:02500	✓
			24Hz	VXX:SLSS1=VXX:EDUS1=*****;*:02400		SLSS1=EDUS1=*****;*:02400	✓
		1024x768		VXX:SLSS1=VXX:EDUS1=*****;*:12000		SLSS1=EDUS1=*****;*:12000	✓
			1280x720	VXX:SLSS1=VXX:EDUS1=*****;*:10000		SLSS1=EDUS1=*****;*:10000	✓
		1280x800		VXX:SLSS1=VXX:EDUS1=*****;*:06000		SLSS1=EDUS1=*****;*:06000	✓
			1280x1024	VXX:SLSS1=VXX:EDUS1=*****;*:05000		SLSS1=EDUS1=*****;*:05000	✓
		48Hz		VXX:SLSS1=VXX:EDUS1=*****;*:04800		SLSS1=EDUS1=*****;*:04800	✓
			30Hz	VXX:SLSS1=VXX:EDUS1=*****;*:03000		SLSS1=EDUS1=*****;*:03000	✓
		25Hz		VXX:SLSS1=VXX:EDUS1=*****;*:02500		SLSS1=EDUS1=*****;*:02500	✓
			24Hz	VXX:SLSS1=VXX:EDUS1=*****;*:02400		SLSS1=EDUS1=*****;*:02400	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ14K
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	
		* PARAMETER	1366x768			SLSS1=ESUS1=1366:0768:*:*****	✓
			1400x1050			SLSS1=ESUS1=1400:1050:*:*****	✓
			1440x900			SLSS1=ESUS1=1440:0900:*:*****	✓
			1600x900			SLSS1=ESUS1=1600:0900:*:*****	✓
			1600x1200			SLSS1=ESUS1=1600:1200:*:*****	✓
			1680x1050			SLSS1=ESUS1=1680:1050:*:*****	✓
			1920x1080			SLSS1=ESUS1=1920:1080:*:*****	✓
			1920x1200			SLSS1=ESUS1=1920:1200:*:*****	✓
			2048x1080			SLSS1=ESUS1=2048:1080:*:*****	✓
			2560x1080			SLSS1=ESUS1=2560:1080:*:*****	✓
		2560x1440			SLSS1=ESUS1=2560:1440:*:*****	✓	
		2560x1600			SLSS1=ESUS1=2560:1600:*:*****	✓	
		3440x1440			SLSS1=ESUS1=3440:1440:*:*****	✓	
		3840x2400			SLSS1=ESUS1=3840:2400:*:*****	✓	
		* PARAMETER1	Progressive Interface			SLSS1=ESUS1=*****:p:*****	✓
			120Hz			SLSS1=ESUS1=*****:i:*****	✓
			120Hz			SLSS1=ESUS1=*****:s:12000	✓
			60Hz			SLSS1=ESUS1=*****:s:12000	✓
			50Hz			SLSS1=ESUS1=*****:s:06000	✓
			48Hz			SLSS1=ESUS1=*****:s:04800	✓
	30Hz			SLSS1=ESUS1=*****:s:03000	✓		
	25Hz			SLSS1=ESUS1=*****:s:02500	✓		
	24Hz			SLSS1=ESUS1=*****:s:02400	✓		
MULTI PROJECTOR SYNC - MODE	OFF MAIN SUB		VXX:MPSI1=+00000 VXX:MPSI1=+00001 VXX:MPSI1=+00002	QVX:MPSI1	MPSI1=+00000 MPSI1=+00001 MPSI1=+00002	✓ ✓ ✓	
MULTI PROJECTOR SYNC - LINK STATUS	NO LINK LINKED			QVX:MPSI2	MPSI2=+00000 MPSI2=+00001	✓ ✓	
FRAME SYNC SETTING(MULTI PROJECTOR SYNC) - CONTRAST SYNC.	OFF ON		VXX:CSYI1=+00000 VXX:CSYI1=+00001	QVX:CSYI1	CSYI1=+00000 CSYI1=+00001	✓ ✓	
MULTI PROJECTOR SYNC - SHUTTER SYNC.	OFF ON		VXX:SSYI1=+00000 VXX:SSYI1=+00001	QVX:SSYI1	SSYI1=+00000 SSYI1=+00001	✓ ✓	
INPUT GUIDE	OFF ON (SIMPLE)		OID:0 OID:1	QDI	0 1	✓ ✓	
OSD POSITION	UPPER LEFT CETRE LEFT LOWER LEFT TOP CENTER CENTER LOEER CENTER UPPER RIGHT CENTER RIGHT LOWER RIGHT		ODP:1 ODP:2 ODP:3 ODP:4 ODP:5 ODP:6 ODP:7 ODP:8 ODP:9	QDP	1 2 3 4 5 6 7 8 9	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓	
OSD ROTATION	OFF CLOCKWISE COUNTER CLOCKWISE		VXX:OSRI1=+00000 VXX:OSRI1=+00001 VXX:OSRI1=+00002	QVX:OSRI1	OSRI1=+00000 OSRI1=+00001 OSRI1=+00002	✓ ✓ ✓	
OSD MEMORY	OFF ON		VXX:OMYI0=+00000 VXX:OMYI0=+00001	QVX:OMYI0	OMYI0=+00000 OMYI0=+00001	✓ ✓	
ON SCREEN	OFF ON		OOS:0 OOS:1	QOS	0 1	✓ ✓	
WARNING MESSAGE	OFF ON		VXX:WMDIO=+00000 VXX:WMDIO=+00001	QVX:WMDIO	WMDIO=+00000 WMDIO=+00001	✓ ✓	
OSD DESIGN	1(YELLOW) 2(BLUE) 3(WHITE) 4(GREEN) 5(PEACH) 6(BROWN)		MOD:0 MOD:1 MOD:2 MOD:3 MOD:4 MOD:5	QOD	0 1 2 3 4 5	✓ ✓ ✓ ✓ ✓ ✓	
MENU MODE	NORMAL SIMPLE		VXX:MMDI1=+00000 VXX:MMDI1=+00001	QVX:MMDI1	MMDI1=+00000 MMDI1=+00001	✓ ✓	
SCREEN SETTING	16:10 16:9 4:3		VSF:0 VSF:1 VSF:2	QSF	0 1 2	✓ ✓ ✓	
SCREEN POSITION-VERTICAL	min. max.		VXX:VSPIO=-00120 VXX:VSPIO=+00120	QVX:VSPIO	VSPIO=-00120 VSPIO=+00120	-60 60	
SCREEN POSITION-HORIZONTAL	min. max.		VXX:HSPIO=-00320 VXX:HSPIO=+00320	QVX:HSPIO	HSPIO=-00320 HSPIO=+00320	-160 160	
SCREEN MARKER	OFF ON		VXX:SSMI1=+00000 VXX:SSMI1=+00001	QVX:SSMI1	SSMI1=+00000 SSMI1=+00001	✓ ✓	
SCREEN MARKER - UPPER	min. max.		VXX:SCMI1=+00000 VXX:SCMI1=+02399	QVX:SCMI1	SCMI1=+00000 SCMI1=+02399	0 1199	
SCREEN MARKER - LOWER	min. max.		VXX:SCMI2=+00000 VXX:SCMI2=+02399	QVX:SCMI2	SCMI2=+00000 SCMI2=+02399	0 1199	
SCREEN MARKER - LEFT	min. max.		VXX:SCMI3=+00000 VXX:SCMI3=+03839	QVX:SCMI3	SCMI3=+00000 SCMI3=+03839	0 1919	
SCREEN MARKER - RIGHT	min. max.		VXX:SCMI4=+00000 VXX:SCMI4=+03839	QVX:SCMI4	SCMI4=+00000 SCMI4=+03839	0 1919	
STARTUP LOGO	OFF USER LOGO DEFAULT LOGO		MLO:0 MLO:1 MLO:2	QLO	0 1 2	✓ ✓ ✓	
UNIFORMITY-FLEXIBLE CORRECTION *	OFF ON(PRE) ON(POST)		VXX:UFMI1=+00000 VXX:UFMI1=+00011 VXX:UFMI1=+00021	QVX:UFMI1	UFMI1=+00000 UFMI1=+00011 *	✓ ✓ ✓	
UNIFORMITY-INITILIZE	EXECUTE		VXX:UFMI2=+00001			✓	
UNIFORMITY-MODE	CHROMA ONLY LUMINACE/CHROMA		VXX:UFMI3=+00001 VXX:UFMI3=+00011	QVX:UFMI3	UFMI3=+00001 UFMI3=+00011	✓ ✓	
UNIFORMITY-WHITE/RED/GREEN/RED	* PARAMETER * PARAMETER 1 * PARAMETER 2 * PARAMETER 3	WHITE RED GREEN BLUE VERTICAL(-127) VERTICAL(+127) HORIZONTAL(-127) HOROZONTAL(+127) L1(ON) L2(OFF)	E\$w:* ,***** E\$w:W ,****,**** E\$w:R ,****,**** E\$w:G ,****,**** E\$w:B ,****,**** E\$w:* , -127,**** E\$w:* ,+127,**** E\$w:* ,****, -127 E\$w:* ,****, +127	E\$R:* E\$R:W E\$R:R E\$R:G E\$R:B	** ,****,**** ** ,****,**** ** ,****,**** ** ,****,**** ** ,****,**** ** , -127,**** ** ,+127,**** ** ,****, -127 ** ,****, +127 1* ,****,**** *0,****,****	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓	
SHUTTER SETTING-FADE IN	0.0s(OFF) 0.5s 1.0s 1.5s 2.0s 2.5s 3.0s 3.5s 4.0s 5.0s 7.0s 10.0s		VXX:SEFS1=0.0 VXX:SEFS1=0.5 VXX:SEFS1=1.0 VXX:SEFS1=1.5 VXX:SEFS1=2.0 VXX:SEFS1=2.5 VXX:SEFS1=3.0 VXX:SEFS1=3.5 VXX:SEFS1=4.0 VXX:SEFS1=5.0 VXX:SEFS1=7.0 VXX:SEFS1=10.0	QVX:SEFS1	SEFS1=0.0 SEFS1=0.5 SEFS1=1.0 SEFS1=1.5 SEFS1=2.0 SEFS1=2.5 SEFS1=3.0 SEFS1=3.5 SEFS1=4.0 SEFS1=5.0 SEFS1=7.0 SEFS1=10.0	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓	
SHUTTER SETTING-FADE OUT	0.0s(OFF) 0.5s 1.0s		VXX:SEFS2=0.0 VXX:SEFS2=0.5 VXX:SEFS2=1.0	QVX:SEFS2	SEFS2=0.0 SEFS2=0.5 SEFS2=1.0	✓ ✓ ✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ24K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RZ14K
		1.5s		VXX:SEFS2=1.5		SEFS2=1.5	✓
		2.0s		VXX:SEFS2=2.0		SEFS2=2.0	✓
		2.5s		VXX:SEFS2=2.5		SEFS2=2.5	✓
		3.0s		VXX:SEFS2=3.0		SEFS2=3.0	✓
		3.5s		VXX:SEFS2=3.5		SEFS2=3.5	✓
		4.0s		VXX:SEFS2=4.0		SEFS2=4.0	✓
		5.0s		VXX:SEFS2=5.0		SEFS2=5.0	✓
		7.0s		VXX:SEFS2=7.0		SEFS2=7.0	✓
		10.0s		VXX:SEFS2=10.0		SEFS2=10.0	✓
	SHUTTER SETTING -MECHANICAL SHUTTER	DISABLE		VXX:SEFI5=+00000	QVX:SEFI5	SEFS5=+00000	✓
		ENABLE		VXX:SEFI5=+00001		SEFS5=+00001	✓
	SHUTTER SETTING-STARTUP	OPEN		VXX:SEFI3=+00000	QVX:SEFI3	SEFI3=+00000	✓
		CLOSE		VXX:SEFI3=+00001		SEFI3=+00001	✓
	SHUTTER SETTING-SHUT OFF	OPEN		VXX:SEFI4=+00000	QVX:SEFI4	SEFI4=+00000	✓
		CLOSE		VXX:SEFI4=+00001		SEFI4=+00001	✓
		KEEP CURRENT STATE		VXX:SEFI4=+00002		SEFI4=+00002	✓
	BACK COLOR	BLUE		OBC:0	QBC	0	✓
		BLACK		OBC:1		1	✓
		USER LOGO		OBC:2		2	✓
		DEFAULT LOGO		OBC:3		3	✓
	WAVEFORM MONITOR	OFF		OWM:0	QWM	0	✓
		LUMINANCE		OWM:5		5	✓
		RED		OWM:6		6	✓
		GREEN		OWM:7		7	✓
		BLUE		OWM:8		8	✓
	WAVEFORM MONITOR-LINE ADJ.	0		VXX:WMLIO=+00000	QVX:WMLIO	WMLIO=+00000	✓
		+2159		VXX:WMLIO=+02159		WMLIO=+02159	✓
	AC VOLTAGE				QVX:VMOI2	VMOI2=+00000	✓
						VMOI2=+99999	✓
	CUT OFF-RED	OFF		VXX:CUTI1=+00000	QVX:CUTI1	CUTI1=+00000	✓
		ON		VXX:CUTI1=+00001		CUTI1=+00001	✓
	CUT OFF-GREEN	OFF		VXX:CUTI2=+00000	QVX:CUTI2	CUTI2=+00000	✓
		ON		VXX:CUTI2=+00001		CUTI2=+00001	✓
	CUT OFF-BLUE	OFF		VXX:CUTI3=+00000	QVX:CUTI3	CUTI3=+00000	✓
		ON		VXX:CUTI3=+00001		CUTI3=+00001	✓
	PROJECTOR ID	0(ALL)		RIS:00			✓
		64		RIS:64			✓
	ID ALL	OFF		RVS:0	QVY	0	✓
		ON		RVS:1		1	✓
	PROJECTION METHOD	FRONT/DESK		OIL:0	QSP	0	✓
	INSTALLATION	REAR/DESK		OIL:1		1	✓
		FRONT/CEILING		OIL:2		2	✓
		REAR/CEILING		OIL:3		3	✓
		FRONT/AUTO		OIL:4		4	✓
		REAR/AUTO		OIL:5		5	✓
	AUTO COOLING CONDITION-STATUS	FLOOR			QVX:ADRI1	ADRI1=+00000	✓
		CEILING				ADRI1=+00001	✓
		VERTICAL UP				ADRI1=+00002	✓
		VERTICAL DOWN				ADRI1=+00003	✓
		PORTRAIT				ADRI1=+00004	✓
	OPERATING MODE	NORMAL		VXX:OPEI1=+00000	QVX:OPEI1	OPEI1=+00000	✓
		ECO		VXX:OPEI1=+00001		OPEI1=+00001	✓
		USER1(USER)		VXX:OPEI1=+00101		OPEI1=+00101	✓
		USER2		VXX:OPEI1=+00102		OPEI1=+00102	✓
		USER3		VXX:OPEI1=+00103		OPEI1=+00103	✓
	LIGHT OUTPUT	min.		VXX:LOPI2=+00050	QVX:LOPI2	LOPI2=+00050	8%
		max.		VXX:LOPI2=+01000		LOPI2=+01000	100%
	MAX LIGHT OUTPUT	min.		VXX:LOPI3=+00050	QVX:LOPI3	LOPI3=+00050	8%
		max.		VXX:LOPI3=+01000		LOPI3=+01000	100%
	BRIGHTNESS CONTROL-SETUP- CALIBRATION MESSAGE	OFF		VXX:BMGI1=+00000	QVX:BMGI1	BMGI1=+00000	✓
		ON		VXX:BMGI1=+00001		BMGI1=+00001	✓
	BRIGHTNESS CONTROL-SETUP-CONSTANT MODE	OFF		VXX:BCMI0=+00000	QVX:BCMI0	BCMI0=+00000	✓
		AUTO		VXX:BCMI0=+00001		BCMI0=+00001	✓
		PC		VXX:BCMI0=+00002		BCMI0=+00002	✓
	BRIGHTNESS CONTROL-SETUP-LINK	OFF		VXX:BCLIO=+00000	QVX:BCLIO	BCLIO=+00000	✓
		GROUP A		VXX:BCLIO=+00001		BCLIO=+00001	✓
		GROUP B		VXX:BCLIO=+00002		BCLIO=+00002	✓
		GROUP C		VXX:BCLIO=+00003		BCLIO=+00003	✓
		GROUP D		VXX:BCLIO=+00004		BCLIO=+00004	✓
	BRIGHTNESS CONTROL-SETUP APPLY	APPLY		VXX:BCSI0=+00001			✓
	BRIGHTNESS CONTROL- PREVIOUS TARGET BRIGHTNESS	***** : target brightness(00000~01 000(0.0~100.0%) yy : year mm : month dd : day hh : hour mm : minute ss : second			QVX:BCSS1	BCSS1=*****:yyymmddhhmmss	✓
	SLOT SETTING-SLOT STANDBY	DISABLE		VXX:SSBI1=+00000	QVX:SSBI1	SSBI1=+00000	✓
		ENABLE		VXX:SSBI1=+00001		SSBI1=+00001	✓
	SLOT SETTING-POWER ON			VXX:SSBI2=+00001			✓
	SLOT SETTING-FORCED TERMINATION			VXX:SSBI3=+00001			✓
	SCHEDULE	OFF		VXX:SCHIO=+00000	QVX:SCHIO	SCHIO=+00000	✓
		ON		VXX:SCHIO=+00001		SCHIO=+00001	✓
	SCHEDULE-PROGRAM ASSIGN	OFF		VXX:SPGI*=+00000	QVX:SPGI*	SPGI*=+00000	✓
		PROGRAM1		VXX:SPGI*=+00001		SPGI*=+00001	✓
		PROGRAM2		VXX:SPGI*=+00002		SPGI*=+00002	✓
		PROGRAM3		VXX:SPGI*=+00003		SPGI*=+00003	✓
		PROGRAM4		VXX:SPGI*=+00004		SPGI*=+00004	✓
		PROGRAM5		VXX:SPGI*=+00005		SPGI*=+00005	✓
		PROGRAM6		VXX:SPGI*=+00006		SPGI*=+00006	✓
		PROGRAM7		VXX:SPGI*=+00007		SPGI*=+00007	✓
			SUN	VXX:SPGI0=+0000*	QVX:SPGI0	SPGI0=+0000*	✓
			MON	VXX:SPGI1=+0000*	QVX:SPGI1	SPGI1=+0000*	✓
			TUE	VXX:SPGI2=+0000*	QVX:SPGI2	SPGI2=+0000*	✓
			WED	VXX:SPGI3=+0000*	QVX:SPGI3	SPGI3=+0000*	✓
			THU	VXX:SPGI4=+0000*	QVX:SPGI4	SPGI4=+0000*	✓
			FRI	VXX:SPGI5=+0000*	QVX:SPGI5	SPGI5=+0000*	✓
			SAT	VXX:SPGI6=+0000*	QVX:SPGI6	SPGI6=+0000*	✓
	SCHEDULE-COMMAND SETTING	COMMAND Del		VXX:SCCS*=**00****	QVX:SCCS*=**	SCCS*=**00****	✓
		STANDBY		VXX:SCCS*=**10****		SCCS*=**10****	✓
		POWER ON		VXX:SCCS*=**11****		SCCS*=**11****	✓
		SHUTTER OPEN		VXX:SCCS*=**20****		SCCS*=**20****	✓
		SHUTTER CLOSE		VXX:SCCS*=**21****		SCCS*=**21****	✓
		HDMI1 INPUT		VXX:SCCS*=**53****		SCCS*=**53****	✓
		HDMI2 INPUT		VXX:SCCS*=**54****		SCCS*=**54****	✓
		DisplayPort		VXX:SCCS*=**5D****		SCCS*=**5D****	✓
		SLOT1-1 INPUT		VXX:SCCS*=**68****		SCCS*=**68****	✓
		SLOT1 DIGITAL LINK		VXX:SCCS*=**G0****		SCCS*=**G0****	✓
		SLOT1-DIGITAL LINK-INPUT 1		VXX:SCCS*=**G1****		SCCS*=**G1****	✓
		SLOT1-DIGITAL LINK-INPUT 2		VXX:SCCS*=**G2****		SCCS*=**G2****	✓
		SLOT1-DIGITAL LINK-INPUT 3		VXX:SCCS*=**G3****		SCCS*=**G3****	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ24K SERIES			
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RZ14K			
PROJECTOR SETUP	SLOT1-DIGITAL LINK-INPUT 4 SLOT1-DIGITAL LINK-INPUT 5 SLOT1-DIGITAL LINK-INPUT 6 SLOT1-DIGITAL LINK-INPUT 7 SLOT1-DIGITAL LINK-INPUT 8 SLOT1-DIGITAL LINK-INPUT 9 SLOT1-DIGITAL LINK-INPUT 10 NORMAL ECO USER1(USER) USER2 USER3			VXX:SCCS*==*G4****	SCCS*==*G4****	✓				
				VXX:SCCS*==*G5****	SCCS*==*G5****	✓				
				VXX:SCCS*==*G6****	SCCS*==*G6****	✓				
				VXX:SCCS*==*G7****	SCCS*==*G7****	✓				
				VXX:SCCS*==*G8****	SCCS*==*G8****	✓				
				VXX:SCCS*==*G9****	SCCS*==*G9****	✓				
				VXX:SCCS*==*GA****	SCCS*==*GA****	✓				
				VXX:SCCS*==*70****	SCCS*==*70****	✓				
				VXX:SCCS*==*71****	SCCS*==*71****	✓				
				VXX:SCCS*==*75****	SCCS*==*75****	✓				
				VXX:SCCS*==*76****	SCCS*==*76****	✓				
				VXX:SCCS*==*77****	SCCS*==*77****	✓				
				* PARAMETER1	PROGRAM1	PROGRAM1	VXX:SCCS1=*****	QVX:SCCS1=**	SCCS1=*****	✓
					PROGRAM2	PROGRAM2	VXX:SCCS2=*****	QVX:SCCS2=**	SCCS2=*****	✓
					PROGRAM3	PROGRAM3	VXX:SCCS3=*****	QVX:SCCS3=**	SCCS3=*****	✓
					PROGRAM4	PROGRAM4	VXX:SCCS4=*****	QVX:SCCS4=**	SCCS4=*****	✓
					PROGRAM5	PROGRAM5	VXX:SCCS5=*****	QVX:SCCS5=**	SCCS5=*****	✓
	PROGRAM6	PROGRAM6	VXX:SCCS6=*****		QVX:SCCS6=**	SCCS6=*****	✓			
	PROGRAM7	PROGRAM7	VXX:SCCS7=*****		QVX:SCCS7=**	SCCS7=*****	✓			
	* PARAMETER2	COMMAND 1	COMMAND 1	VXX:SCCS*==01*****	QVX:SCCS*==01	SCCS*==01*****	✓			
		COMMAND 16	COMMAND 16	VXX:SCCS*==16*****	QVX:SCCS*==16	SCCS*==16*****	✓			
	* PARAMETER3	00:00		VXX:SCCS*==*****0000	VXX:SCCS*==*****0000	SCCS*==*****0000	✓			
		23:59		VXX:SCCS*==*****2359	VXX:SCCS*==*****2359	SCCS*==*****2359	✓			
							✓			
	STARTUP INPUT SELECT	HDMI1 HDMI2 DisplayPort SLOT1 : SDM : 12G SDI SLOT1 : SDM : Digital Link SLOT1 : SDM : PressIT SLOT1 : SDM : 3rd Party Board SLOT1 : SDM : 12G SDI OPT1 SLOT1 : SDM : 12G SDI OPT2 LAST USED		VXX:SISS1=HD1 VXX:SISS1=HD2 VXX:SISS1=DP1 VXX:SISS1=DM1,SD1 VXX:SISS1=DM1,DL1 VXX:SISS1=DM1,WP1 VXX:SISS1=DM1,TP1 VXX:SISS1=DM1,OP1 VXX:SISS1=DM1,OP2 VXX:SISS1=LSU	QVX:SISS1	SISS1=HD1 SISS1=HD2 SISS1=DP1 SISS1=DM1,SD1 SISS1=DM1,DL1 SISS1=DM1,WP1 SISS1=DM1,TP1 SISS1=DM1,OP1 SISS1=DM1,OP2 SISS1=LSU	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓			
	STARTUP INPUT SELECT (SLOT : DIGITAL LINK)	LAST USED INPUT1 INPUT2 INPUT3 INPUT4 INPUT5 INPUT6 INPUT7 INPUT8 INPUT9 INPT10		VXX:SLSS1=VXX:SISS12=+00000 VXX:SLSS1=VXX:SISS12=+00001 VXX:SLSS1=VXX:SISS12=+00002 VXX:SLSS1=VXX:SISS12=+00003 VXX:SLSS1=VXX:SISS12=+00004 VXX:SLSS1=VXX:SISS12=+00005 VXX:SLSS1=VXX:SISS12=+00006 VXX:SLSS1=VXX:SISS12=+00007 VXX:SLSS1=VXX:SISS12=+00008 VXX:SLSS1=VXX:SISS12=+00009 VXX:SLSS1=VXX:SISS12=+00010	QVX:SLSS1=QVX:SISS12	SLSS1=SISS12=+00000 SLSS1=SISS12=+00001 SLSS1=SISS12=+00002 SLSS1=SISS12=+00003 SLSS1=SISS12=+00004 SLSS1=SISS12=+00005 SLSS1=SISS12=+00006 SLSS1=SISS12=+00007 SLSS1=SISS12=+00008 SLSS1=SISS12=+00009 SLSS1=SISS12=+00010	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓			
	NO SIGNAL SHUT-OFF	DISABLE 10min 20min 30min 40min 50min 60min 70min 80min 90min		OAF:00 OAF:10 OAF:20 OAF:30 OAF:40 OAF:50 OAF:60 OAF:70 OAF:80 OAF:90	QAF	00 10 20 30 40 50 60 70 80 90	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓			
	NO SIGNAL LIGHTS-OUT	DISABLE 10SEC. 20SEC. 30SEC. 1MIN. 2MIN. 3MIN. 5MIN.		VXX:SLOI1=+00000 VXX:SLOI1=+00010 VXX:SLOI1=+00020 VXX:SLOI1=+00030 VXX:SLOI1=+00060 VXX:SLOI1=+00120 VXX:SLOI1=+00180 VXX:SLOI1=+00300	QVX:SLOI1	SLOI1=+00000 SLOI1=+00010 SLOI1=+00020 SLOI1=+00030 SLOI1=+00060 SLOI1=+00120 SLOI1=+00180 SLOI1=+00300	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓			
	NO SIGNAL SETTING - SECONDARY INPUT	OFF HDMI1 HDMI2 DisplayPort SLOT1 : SDM : 12G SDI SLOT1 : SDM : Digital Link SLOT1 : SDM : PressIT SLOT1 : SDM : 3rd Party Board SLOT1 : SDM : 12G SDI OPT1 SLOT1 : SDM : 12G SDI OPT2		VXX:SINS1=OFF VXX:SINS1=HD1 VXX:SINS1=HD2 VXX:SINS1=DP1 VXX:SINS1=DM1,SD1 VXX:SINS1=DM1,DL1 VXX:SINS1=DM1,WP1 VXX:SINS1=DM1,TP1 VXX:SINS1=DM1,OP1 VXX:SINS1=DM1,OP2	QVX:SINS1	SINS1=OFF SINS1=HD1 SINS1=HD2 SINS1=DP1 SINS1=DM1,SD1 SINS1=DM1,DL1 SINS1=DM1,WP1 SINS1=DM1,TP1 SINS1=DM1,OP1 SINS1=DM1,OP2	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓			
	REMOTE2 - MODE	DEFAULT USER		VXX:RMPIO=+00000 VXX:RMPIO=+00001	QVX:RMPIO	RMPIO=+00000 RMPIO=+00001	✓ ✓			
	REMOTE2 - PIN2	NONE POWER		VXX:RMPS1=P2<NONE VXX:RMPS1=P2<POWER	QVX:RMPS1=P2	RMPS1=P2<NONE RMPS1=P2<POWER	✓ ✓			
	REMOTE2 - PIN3 - 7	* PARAMETER		VXX:RMPS1=P* <*****	QVX:RMPS1=P*		✓			
	* PARAMETER1	PIN3		VXX:RMPS1=P3<*****		RMPS1=P3<*****	✓			
		PIN4		VXX:RMPS1=P4<*****		RMPS1=P4<*****	✓			
		PIN5		VXX:RMPS1=P5<*****		RMPS1=P5<*****	✓			
		PIN6		VXX:RMPS1=P6<*****		RMPS1=P6<*****	✓			
		PIN7		VXX:RMPS1=P7<*****		RMPS1=P7<*****	✓			
		* PARAMETER2	NONE		VXX:RMPS1=P* <NONE		RMPS1=P* <NONE	✓		
			HDMI		VXX:RMPS1=P* <HDMI		RMPS1=P* <HDMI	✓		
			HDMI1		VXX:RMPS1=P* <HDMI1		RMPS1=P* <HDMI1	✓		
			HDMI2		VXX:RMPS1=P* <HDMI2		RMPS1=P* <HDMI2	✓		
			DisplayPort		VXX:RMPS1=P* <DP1		RMPS1=P* <DP1	✓		
			SLOT1 : SDM : 12G SDI		VXX:RMPS1=P* <DM1,SD1		RMPS1=P* <DM1,SD1	✓		
			SLOT1 : SDM : Digital Link		VXX:RMPS1=P* <DM1,DL1		RMPS1=P* <DM1,DL1	✓		
			SLOT1 : SDM : PressIT		VXX:RMPS1=P* <DM1,WP1		RMPS1=P* <DM1,WP1	✓		
* PARAMETER3		SLOT1 : SDM : 3rd Party Board		VXX:RMPS1=P* <DM1,TP1		RMPS1=P* <DM1,TP1	✓			
	SLOT1 : SDM : 12G SDI OPT1		VXX:RMPS1=P* <DM1,OP1		RMPS1=P* <DM1,OP1	✓				
SLOT1 : SDM : 12G SDI OPT2		VXX:RMPS1=P* <DM1,OP2		RMPS1=P* <DM1,OP2	✓					
REMOTE2 - PIN8	NONE SHUTTER		VXX:RMPS1=P8<NONE VXX:RMPS1=P8<SHUTTER	QVX:RMPS1=P8	RMPS1=P8<NONE RMPS1=P8<SHUTTER	✓ ✓				
FUNCTION BUTTON	DISABLE SYSTEM SELECTOR SYSTEM DAYLIGHT VIEW SUB MEMORY FREEZE WAVEFORM MONITOR LENS MEMORY LOAD LEFT/RIGHT SWAP PROJECTION METHOD GEOMETRY		OFC:0 OFC:1 OFC:2 OFC:3 OFC:4 OFC:6 OFC:7 OFC:8 OFC:10 OFC:13	QFC	0 1 2 3 4 6 7 8 10 13	✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓				
DATE AND TIME-DATE SETTING	Year: yyyy Month: mm Date: dd Day:w(1~7:Mon~Sun)		TSD:201506151 TSD:yyyyymmddw	QGD	201506161 yyyyymmddw	✓ ✓ ✓ ✓				
DATE AND TIME-TIME SETTING	Hour: hh Minute: mm Second: ss		TST:154503 TST:hmmss	QGT	154503 hmmss	✓ ✓ ✓				
DATE AND TIME-NTP SYNCHRONIZATION	OFF		VXX:NTPIO=+00000	QVX:NTPIO	NTPIO=+00000	✓				

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ24K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RZ14K
LENS TYPE	ON			VXX: NTP10=+00001		NTP10=+00001	✓
	ET-D75LE6			VXX: LNEI1=+00001	QVX: LNEI1	LNEI1=+00001	✓
	ET-D75LE10			VXX: LNEI1=+00002		LNEI1=+00002	✓
	ET-D75LE20			VXX: LNEI1=+00003		LNEI1=+00003	✓
	ET-D75LE30			VXX: LNEI1=+00004		LNEI1=+00004	✓
	ET-D75LE40			VXX: LNEI1=+00005		LNEI1=+00005	✓
	ET-D75LE8			VXX: LNEI1=+00006		LNEI1=+00006	✓
	ET-D75LE95			VXX: LNEI1=+00007		LNEI1=+00007	✓
	ET-D75LE50			VXX: LNEI1=+00009		LNEI1=+00009	✓
	LENS ID	All			VXX: LNEI4=+00000	QVX: LNEI4	LNEI4=+00000
1				VXX: LNEI4=+00001		LNEI4=+00001	✓
255				VXX: LNEI4=+00255		LNEI4=+00255	✓
LENS NAME			VXX: LNES5=LENSNAME	QVX: LNES5	LNES5=LENSNAME	✓	
LENS CALIBRATION	EXECUTE (ALL)			VXX: LNSI0=+00001			✓
	EXECUTE (SHIFT)			VXX: LNSI0=+00011			✓
	EXECUTE (FOCUS)			VXX: LNSI0=+00012			✓
	EXECUTE (ZOOM)			VXX: LNSI0=+00013			✓
	EXECUTE (SHIFT/FOCUS)			VXX: LNSI0=+00021			✓
	EXECUTE (SHIFT/ZOOM)			VXX: LNSI0=+00022			✓
	EXECUTE (FOCUS/ZOOM)			VXX: LNSI0=+00023			✓
LENS MEMORY1 NAME CHANGE	LENSMEMORY1			VXX: NCGS5=LENSMEMORY1	QVX: NCGS5	NCGS5=LENSMEMORY1	✓
LENS MEMORY2 NAME CHANGE	LENSMEMORY2			VXX: NCGS6=LENSMEMORY2	QVX: NCGS6	NCGS6=LENSMEMORY2	✓
LENS MEMORY3 NAME CHANGE	LENSMEMORY3			VXX: NCGS7=LENSMEMORY3	QVX: NCGS7	NCGS7=LENSMEMORY3	✓
LENS MEMORY4 NAME CHANGE	LENSMEMORY4			VXX: NCGS9=LENSMEMORY4	QVX: NCGS9	NCGS9=LENSMEMORY4	✓
LENS MEMORY5 NAME CHANGE	LENSMEMORY5			VXX: NCGSA=LENSMEMORY5	QVX: NCGSA	NCGSA=LENSMEMORY5	✓
LENS MEMORY6 NAME CHANGE	LENSMEMORY6			VXX: NCGSB=LENSMEMORY6	QVX: NCGSB	NCGSB=LENSMEMORY6	✓
LENS MEMORY7 NAME CHANGE	LENSMEMORY7			VXX: NCGSC=LENSMEMORY7	QVX: NCGSC	NCGSC=LENSMEMORY7	✓
LENS MEMORY8 NAME CHANGE	LENSMEMORY8			VXX: NCGSD=LENSMEMORY8	QVX: NCGSD	NCGSD=LENSMEMORY8	✓
LENS MEMORY9 NAME CHANGE	LENSMEMORY9			VXX: NCGSE=LENSMEMORY9	QVX: NCGSE	NCGSE=LENSMEMORY9	✓
LENS MEMORY10 NAME CHANGE	LENSMEMORY10			VXX: NCGSF=LENSMEMORY10	QVX: NCGSF	NCGSF=LENSMEMORY10	✓
LENS MEMORY-LOAD	LENS MEMORY1			VXX: LNMI1=+00000			✓
	LENS MEMORY2			VXX: LNMI1=+00001			✓
	LENS MEMORY3			VXX: LNMI1=+00002			✓
	LENS MEMORY4			VXX: LNMI1=+00003			✓
	LENS MEMORY5			VXX: LNMI1=+00004			✓
	LENS MEMORY6			VXX: LNMI1=+00005			✓
	LENS MEMORY7			VXX: LNMI1=+00006			✓
	LENS MEMORY8			VXX: LNMI1=+00007			✓
	LENS MEMORY9			VXX: LNMI1=+00008			✓
	LENS MEMORY10			VXX: LNMI1=+00009			✓
LENS MEMORY-SAVE	LENS MEMORY1			VXX: LNMI2=+00000			✓
	LENS MEMORY2			VXX: LNMI2=+00001			✓
	LENS MEMORY3			VXX: LNMI2=+00002			✓
	LENS MEMORY4			VXX: LNMI2=+00003			✓
	LENS MEMORY5			VXX: LNMI2=+00004			✓
	LENS MEMORY6			VXX: LNMI2=+00005			✓
	LENS MEMORY7			VXX: LNMI2=+00006			✓
	LENS MEMORY8			VXX: LNMI2=+00007			✓
	LENS MEMORY9			VXX: LNMI2=+00008			✓
	LENS MEMORY10			VXX: LNMI2=+00009			✓
LENS MEMORY-DELETE	LENS MEMORY1			VXX: LNMI3=+00000			✓
	LENS MEMORY2			VXX: LNMI3=+00001			✓
	LENS MEMORY3			VXX: LNMI3=+00002			✓
	LENS MEMORY4			VXX: LNMI3=+00003			✓
	LENS MEMORY5			VXX: LNMI3=+00004			✓
	LENS MEMORY6			VXX: LNMI3=+00005			✓
	LENS MEMORY7			VXX: LNMI3=+00006			✓
	LENS MEMORY8			VXX: LNMI3=+00007			✓
	LENS MEMORY9			VXX: LNMI3=+00008			✓
	LENS MEMORY10			VXX: LNMI3=+00009			✓
LENS MEMORY1-DEFAULT NAME	LENSMEMORY1			VXX: NCLI5=+00000			✓
LENS MEMORY2-DEFAULT NAME	LENSMEMORY2			VXX: NCLI6=+00000			✓
LENS MEMORY3-DEFAULT NAME	LENSMEMORY3			VXX: NCLI7=+00000			✓
LENS MEMORY4-DEFAULT NAME	LENSMEMORY4			VXX: NCLI9=+00000			✓
LENS MEMORY5-DEFAULT NAME	LENSMEMORY5			VXX: NCLIA=+00000			✓
LENS MEMORY6-DEFAULT NAME	LENSMEMORY6			VXX: NCLIB=+00000			✓
LENS MEMORY7-DEFAULT NAME	LENSMEMORY7			VXX: NCLIC=+00000			✓
LENS MEMORY8-DEFAULT NAME	LENSMEMORY8			VXX: NCLID=+00000			✓
LENS MEMORY9-DEFAULT NAME	LENSMEMORY9			VXX: NCLIE=+00000			✓
LENS MEMORY10-DEFAULT NAME	LENSMEMORY10			VXX: NCLIF=+00000			✓
INITIALIZE-ALL USER DATA	USER INITILIZE			VXX: RSTS1=0password			✓
	USER RESTORE			VXX: RSTS1=1password			✓
INITIAL START UP	STANDBY			OPY: 0	QPY	0	✓
	ON			OPY: 1		1	✓
	LAST MEMORY			OPY: 2		2	✓
MODEL NAME	MODEL NAME			QID	MODEL NAME	✓	
SERIAL NUMBER	SW0101234			QSN	SW0101234	✓	
PROJECTOR RUNTIME	7864320H			QVX: RTMS1	RTMS1=7864320	✓	
LAMP1(LIGHT1) RUNTIME	9999H			Q\$L: 1	9999	✓	
LIGHT1 RUNTIME	7864320H			QVX: LRTS3=00	LRTS3=00:7864320	✓	
LIGHT STATUS	ALL OFF			QLS	0	✓	
	1:ON, 2:OFF				1	✓	
CONTINUOUS LIGHTING TIME	7864320H00M			QVX: CLTS1	CLTS1=7864320:00	✓	
CONSOLIDATED RUNTIME	7864320H			QVX: CRTS1	CRTS1=7864320	✓	
LAMP(LIGHT) CONTROL STATUS	LAMP OFF			Q\$S	0	✓	
	In turning ON				1	✓	
	LAMP ON				2	✓	
	LAMP Cooling				3	✓	
POWER STATUS	POWER OFF			QVX: POWI1	POWI1=+00001	✓	
	In turning ON				POWI1=+00002	✓	
	POWER ON				POWI1=+00003	✓	
	Cooling				POWI1=+00004	✓	
MAC ADDRESS	AB0102030405			QMA	AB0102030405	✓	
MAIN FIRMWARE VERSION	V1.00.01			QVX: SVRS0	SVRS0=1.00.01	✓	
NETWORK FIRMWARE VERSION	V1.00			QVX: SVRS1	SVRS1=1.00	✓	
SUB FIRMWARE VERSION	V1.00.01			QVX: SVRS2	SVRS2=1.00.01	✓	
FIRMWARE VERSION	V1.00			QVX: SVRSE	SVRSE=1.00	✓	
INPUT SIGNAL NAME	CHANNEL1 (MAIN CH)			QVX: NSGS1	NSGS1=*****	✓	
TEMPERATURE (INTAKE)	0030/0080			QTM: 0	0030/0080	✓	
TEMPERATURE (EXHAUST AIR)	0030/0080			QTM: 1	0030/0080	✓	
SDI ERROR STATUS	--			QVX: SESI1	SESI1=+00000	✓	
	NOT ID				SESI1=+00001	✓	
	ID				SESI1=+00002	✓	
	CRCC				SESI1=+00003	✓	
LAN data Cloning Write protect	OFF			LCL: WRP0	QCL: WRP0	✓	
	ON			LCL: WRP1	QCL: WRP1	✓	
MECH. SHUTTER COUNT				QVX: MSCIO	MSCIO=+*****	✓	
INFO MONITOR SETTING - DEFAULT	OFF			QVX: INF11	INF11=+00000	✓	
	USER VIEW			VXX: INF11=+00001	INF11=+00001	✓	
INFO MONITOR SETTING - USER VIEW	INPUT			VXX: INFS2=01:*****	QVX: INFS2=01	INFS2=01:*****	✓
	SIGNAL			VXX: INFS2=02:*****	QVX: INFS2=02	INFS2=02:*****	✓
	AC VOLTAGE			VXX: INFS2=03:*****	QVX: INFS2=03	INFS2=03:*****	✓
	INTAKE AIR TEMP.			VXX: INFS2=04:*****	QVX: INFS2=04	INFS2=04:*****	✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ24K SERIES	
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RZ14K	
		EXHAUST AIR TEMP.		VXX: INFS2=05:*****	QVX: INFS2=05	INFS2=05:*****	✓	
		SHUTTER		VXX: INFS2=06:*****	QVX: INFS2=06	INFS2=06:*****	✓	
		OSD		VXX: INFS2=07:*****	QVX: INFS2=07	INFS2=07:*****	✓	
		IP ADDRESS		VXX: INFS2=08:*****	QVX: INFS2=08	INFS2=08:*****	✓	
		FREEZE		VXX: INFS2=09:*****	QVX: INFS2=09	INFS2=09:*****	✓	
		OFF		VXX: INFS2=** :00000			✓	
		ON		VXX: INFS2=** :00001			✓	
		INFO MONITOR SETTING - DIRECTION	AUTO		VXX: INFI3=+00000	QVX: INFI3	INFI3=+00000	✓
			NORMAL		VXX: INFI3=+00001		INFI3=+00001	✓
			FLIPPED		VXX: INFI3=+00002		INFI3=+00002	✓
INFO MONITOR SETTING - BRIGHTNESS	30%		VXX: INFI4=+00030	QVX: INFI4	INFI4=+00030	✓		
	100%		VXX: INFI4=+00100		INFI4=+00100	✓		
TEST PATTERN	TEST PATTERN	Off		OTS:00	QTS	00	✓	
		White		OTS:01		01	✓	
		Black		OTS:02		02	✓	
		Window		OTS:05		05	✓	
		Reversed Window		OTS:06		06	✓	
		Cross Hatch		OTS:07		07	✓	
		Color Bar V		OTS:08		08	✓	
		Focus (Level 0%)		OTS:32		32	✓	
		Focus (Level 50%)		OTS:33		33	✓	
		Focus (Level 100%)		OTS:34		34	✓	
		Color Bar Side		OTS:51		51	✓	
		16:9/4:3		OTS:59		59	✓	
		Focus Red		OTS:70		70	✓	
		Focus Green		OTS:71		71	✓	
		Focus Blue		OTS:72		72	✓	
		Focus Cyan		OTS:73		73	✓	
		Focus Magenta		OTS:74		74	✓	
		Focus Yellow		OTS:75		75	✓	
		Focus		OTS:78		78	✓	
		3D-1		OTS:80		80	✓	
		3D-2		OTS:81		81	✓	
		3D-3		OTS:82		82	✓	
		3D-4		OTS:83		83	✓	
		CIRCLE		OTS:87		87	✓	
		USER TEST PATTERN 1		OTS:A1		A1	✓	
		USER TEST PATTERN 2		OTS:A2		A2	✓	
		USER TEST PATTERN 3		OTS:A3		A3	✓	
		USER TEST PATTERN - RENAME USER TEST PATTERN	USER TEST PATTERN 1 - NAME		VXX: TPNS1=01: <i>USERTESTPATTERN1</i>	QVX: TPNS1=01	TPNS1=01: <i>USERTESTPATTERN1</i>	✓
			USER TEST PATTERN 2 - NAME		VXX: TPNS1=02: <i>USERTESTPATTERN2</i>	QVX: TPNS1=02	TPNS1=02: <i>USERTESTPATTERN2</i>	✓
			USER TEST PATTERN 3 - NAME		VXX: TPNS1=03: <i>USERTESTPATTERN3</i>	QVX: TPNS1=03	TPNS1=03: <i>USERTESTPATTERN3</i>	✓
		USER TEST PATTERN - DELETE USER TEST PATTERN	USER TEST PATTERN 1 - DELETE		VXX: TPNS2=01			✓
			USER TEST PATTERN 2 - DELETE		VXX: TPNS2=02			✓
			USER TEST PATTERN 3 - DELETE		VXX: TPNS2=03			✓
		SIGNAL LIST-REGISTRATION			OEM			✓
		SIGNAL LIST-DELETE	A1		ODM:A1			✓
	A2		ODM:A2			✓		
	A7		ODM:A7			✓		
	A8		ODM:A8			✓		
	L1		ODM:L1			✓		
	L2		ODM:L2			✓		
	L7		ODM:L7			✓		
	L8		ODM:L8			✓		
SUB MEMORY LIST-CHANGEOVER	01		OCS:01			✓		
	96		OCS:96			✓		
SUB MEMORY LIST-CHANGEOVER (EXTENDED)	01		OCS:01-01			✓		
	96		OCS:95-96			✓		
SUB MEMORY LIST-REGISTRATION			OES			✓		
SUB MEMORY LIST-DELETE	01		ODS:01-01			✓		
	96		ODS:95-96			✓		
SUB MEMORY USAGE STATE	01			QSB	01	✓		
	96				96	✓		
SECURITY	SECURITY SETTING	OFF		QVX: SPWI1	SPWI1=+00000	✓		
		ON			SPWI1=+00001	✓		
	CONTROL DEVICE SETUP-CONTROL PANEL	DISABLE		VXX: CDSI1=+00000	QVX: CDSI1	CDSI1=+00000	✓	
		ENABLE		VXX: CDSI1=+00001		CDSI1=+00001	✓	
		USER		VXX: CDSI1=+00002		CDSI1=+00002	✓	
	CONTROL DEVICE SETUP-REMOTE CONTROL	DISABLE		VXX: CDSI2=+00000	QVX: CDSI2	CDSI2=+00000	✓	
	ENABLE		VXX: CDSI2=+00001		CDSI2=+00001	✓		
	USER		VXX: CDSI2=+00002		CDSI2=+00002	✓		
NETWORK	ETHERNET TYPE	LAN		VXX: ETHI1=+00001	QVX: ETHI1	ETHI1=+00001	✓	
		DIGITAL LINK		VXX: ETHI1=+00002		ETHI1=+00002	✓	
		LAN & DIGITAL LINK		VXX: ETHI1=+00003		ETHI1=+00003	✓	
	WIRED LAN-IP VERSION	IPv4		VXX: IPVI1=+00001	QVX: IPVI1	IPVI1=+00001	✓	
		IPv6		VXX: IPVI1=+00002		IPVI1=+00002	✓	
		IPv4 & IPv6		VXX: IPVI1=+00003		IPVI1=+00003	✓	
	WIRELESS LAN	OFF(DISABLE)		ONS:0	QVX: WLSI1	WLSI1=+00000	✓	
		ON(ENABLE)		ONS:14		WLSI1=+00014	✓	
	SLOT : DIGITAL LINK MODE	AUTO		VXX: SLSS1=VXX:DKMI1=+00001	QVX: SLSS1=QVX:DKMI1	SLSS1=DKMI1=+00001	✓	
		DIGITAL LINK		VXX: SLSS1=VXX:DKMI1=+00002		SLSS1=DKMI1=+00002	✓	
		ETHERNET		VXX: SLSS1=VXX:DKMI1=+00003		SLSS1=DKMI1=+00003	✓	
		LONG REACH MODE		VXX: SLSS1=VXX:DKMI1=+00004		SLSS1=DKMI1=+00004	✓	
	DIGITAL LINK-EXTRON XTP	OFF		VXX: EXTI1=+00000	QVX: EXTI1	EXTI1=+00000	✓	
		ON		VXX: EXTI1=+00001		EXTI1=+00001	✓	
	SLOT : DIGITAL LINK STATUS-LINK	NO LINK			QVX: SLSS1=QVX:DKSI1	SLSS1=DKSI1=+00000	✓	
		DIGITAL LINK				SLSS1=DKSI1=+00001	✓	
		LPM				SLSS1=DKSI1=+00002	✓	
		ETHERNET				SLSS1=DKSI1=+00003	✓	
	SLOT : DIGITAL LINK STATUS-HDCP STATUS	NO SIGNAL			QVX: SLSS1=QVX:DKSI2	SLSS1=DKSI2=+00000	✓	
		OFF				SLSS1=DKSI2=+00001	✓	
	ON				SLSS1=DKSI2=+00002	✓		
SLOT : DIGITAL LINK STATUS-SIGNAL QUALITY (MIN)	-255			QVX: SLSS1=QVX:DKSI3	SLSS1=DKSI3=-00255	✓		
	0				SLSS1=DKSI3=+00000	✓		
SLOT : DIGITAL LINK STATUS-SIGNAL QUALITY (MAX)	-255			QVX: SLSS1=QVX:DKSI4	SLSS1=DKSI4=-00255	✓		
	0				SLSS1=DKSI4=+00000	✓		
SLOT : DIGITAL LINK INPUT CH LIST	HD1:HDMI1,HD2:HDMI2-...			QVX: SLSS1=QVX:DLIS1	SLSS1=DLIS1=HD1:HDMI1,****,***	✓		
PROJECTOR NAME SETTING	PROJECTOR1		VXX: NCGS8=PROJECTOR1	QVX: NCGS8	NCGS8=PROJECTOR1	✓		
NFC SETTING	OFF		VXX: NFCI1=+00000	QVX: NFCI1	NFCI1=+00000	✓		
	READ ONLY		VXX: NFCI1=+00001		NFCI1=+00001	✓		
	READ/WRITE		VXX: NFCI1=+00003		NFCI1=+00003	✓		
Art-Net SETUP	OFF		VXX: DANI1=+00000	QVX: DANI1	DANI1=+00000	✓		
	ON(2.*.*)		VXX: DANI1=+00002		DANI1=+00002	✓		
	ON(10.*.*)		VXX: DANI1=+00003		DANI1=+00003	✓		
	ON(MANUAL)		VXX: DANI1=+00004		DANI1=+00004	✓		
Art-Net SETUP-START ADDRESS	1		VXX: DANI3=+00001	QVX: DANI3	DANI3=+00001	✓		
	501		VXX: DANI3=+00501		DANI3=+00501	✓		
Art-Net SETUP-NET	0		VXX: DANI4=+00000	QVX: DANI4	DANI4=+00000	✓		
	127		VXX: DANI4=+00127		DANI4=+00127	✓		
Art-Net SETUP-SUB NET	0		VXX: DANI5=+00000	QVX: DANI5	DANI5=+00000	✓		
	15		VXX: DANI5=+00015		DANI5=+00015	✓		
Art-Net SETUP-UNIVERS	0		VXX: DANI6=+00000	QVX: DANI6	DANI6=+00000	✓		
	15		VXX: DANI6=+00015		DANI6=+00015	✓		

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL	QUERY		RZ24K SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	RZ14K
	Art-Net SETUP-CHANNEL SETTING	DEFAULT		VXX: DANI8=+0000	QVX: DANI8	DANI8=+0000	✓
		1		VXX: DANI8=+00001		DANI8=+00001	✓
		2		VXX: DANI8=+00002		DANI8=+00002	✓
		USER		VXX: DANI8=+00100		DANI8=+00100	✓
	PRESHOW MODE	OFF			QVX: PSMI1	PSMI1=+00000	✓
		ON				PSMI1=+00001	✓

Note: The commands or parameters with "*" shows available commands or parameters for the projector which has been activated by the Upgrade Kit.