

Control Commands

Model No. PT-REZ12
PT-FEZ120C
PT-REZ10
PT-FEZ100C
PT-REZ80
PT-FEZ080C



- Please refer to the Operating Instructions for the serial command format, limitations, connection and other details.
- シリアルコマンドのフォーマット、制限事項、接続方法およびその他詳細につきましては、各モデルの取扱説明書をご覧ください。
- 有关串行控制命令的格式、限制事项、连接方法以及其他详情、请参阅各机型的使用说明书。

Panasonic

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		REZ12 SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	REZ12 /10/80 FEZ120C /100C/080C	
BASIC OPERATION REMOTE CONTROL	POWER	ON		PON	QPW	001		✓
		OFF (STANDBY)		POF		000		✓
	INPUT SELECT	HDMI1		IIS:HD1	QIN	HD1		✓
		HDMI2		IIS:HD2		HD2		✓
		DisplayPort		IIS:DP1		DP1		✓
	INPUT SELECT (SDM SLOT)	SLOT1 : 12G SDI		IIS:DM1,SD1	QIN	DM1,SD1		✓
		SLOT1 : Digital Link		IIS:DM1,DL1		DM1,DL1		✓
		SLOT1 : PressIT		IIS:DM1,WP1		DM1,WP1		✓
		SLOT1 : 3rd Party Board		IIS:DM1,TP1		DM1,TP1		✓
		SLOT1 : 12G SDI OPT1		IIS:DM1,OP1		DM1,OP1		✓
		SLOT1 : 12G SDI OPT2		IIS:DM1,OP2		DM1,OP2		✓
	INPUT SELECT (SDM SLOT : DIGITAL LINK)	COMPUTER1		IIS:DM1,DL1:PC1	QIN	DM1,DL1:PC1		✓
		COMPUTER2		IIS:DM1,DL1:PC2		DM1,DL1:PC2		✓
		VIDEO		IIS:DM1,DL1:VID		DM1,DL1:VID		✓
		HDMI1		IIS:DM1,DL1:HD1		DM1,DL1:HD1		✓
		HDMI2		IIS:DM1,DL1:HD2		DM1,DL1:HD2		✓
		S-VIDEO		IIS:DM1,DL1:SVD		DM1,DL1:SVD		✓
	FREEZE	OFF		OFZ:0	QFZ	0		✓
		ON		OFZ:1		1		✓
	MENU KEY			OMN				✓
	ENTER KEY			OEN				✓
	UP KEY			OCU				✓
	DOWN KEY			OCD				✓
	LEFT KEY			OCL				✓
	RIGHT KEY			OCR				✓
	DEFAULT KEY			OST				✓
	SHUTTER	OFF		OSH:0	QSH	0		✓
		ON		OSH:1		1		✓
	SHUTTER(Toggle)	OFF		OSH	QSH	0		✓
		ON				1		✓
	FUNCTION KEY			FC1				✓
	SYSTEM SELCTOR KEY			OSL				✓
	ASPECT KEY			VS1				✓
	NUMERIC KEY	0		ONK:0				✓
		1		ONK:1				✓
		2		ONK:2				✓
		3		ONK:3				✓
		4		ONK:4				✓
		5		ONK:5				✓
		6		ONK:6				✓
		7		ONK:7				✓
		8		ONK:8				✓
		9		ONK:9				✓
	LENS HOME POSITION	EXECUTE		VXX:LNSI1=+00001				✓
	LENS SHIFT-HORIZONTAL	SLOW+		VXX:LNSI2=+00000				✓
	SLOW-		VXX:LNSI2=+00001				✓	
	NORMAL+		VXX:LNSI2=+00100				✓	
	NORMAL-		VXX:LNSI2=+00101				✓	
	FAST+		VXX:LNSI2=+00200				✓	
	FAST-		VXX:LNSI2=+00201				✓	
LENS SHIFT-VERTICAL	SLOW+		VXX:LNSI3=+00000				✓	
	SLOW-		VXX:LNSI3=+00001				✓	
	NORMAL+		VXX:LNSI3=+00100				✓	
	NORMAL-		VXX:LNSI3=+00101				✓	
	FAST+		VXX:LNSI3=+00200				✓	
	FAST-		VXX:LNSI3=+00201				✓	
LENS FOCUS	SLOW+		VXX:LNSI4=+00000				✓	
	SLOW-		VXX:LNSI4=+00001				✓	
	NORMAL+		VXX:LNSI4=+00100				✓	
	NORMAL-		VXX:LNSI4=+00101				✓	
	FAST+		VXX:LNSI4=+00200				✓	
	FAST-		VXX:LNSI4=+00201				✓	
LENS ZOOM	SLOW+		VXX:LNSI5=+00000				✓	
	SLOW-		VXX:LNSI5=+00001				✓	
	NORMAL+		VXX:LNSI5=+00100				✓	
	NORMAL-		VXX:LNSI5=+00101				✓	
	FAST+		VXX:LNSI5=+00200				✓	
	FAST-		VXX:LNSI5=+00201				✓	
LENS PERIPHERY FOCUS	SLOW+		VXX:LNSIG=+00000				✓	
	SLOW-		VXX:LNSIG=+00001				✓	
	NORMAL+		VXX:LNSIG=+00100				✓	
	NORMAL-		VXX:LNSIG=+00101				✓	
	FAST+		VXX:LNSIG=+00200				✓	
	FAST-		VXX:LNSIG=+00201				✓	
LENS POSITION	HORIZONTAL(H)		VXX:LNSI7=*HORIZONTAL	QVX:LNSI7	LNSI7=*HORIZONTAL		✓	
	VERTICAL(V)		VXX:LNSI8=*VERTICAL	QVX:LNSI8	LNSI8=*VERTICAL		✓	
	FOCUS(F)		VXX:LNSI9=*FOCUS	QVX:LNSI9	LNSI9=*FOCUS		✓	
	ZOOM(Z)		VXX:LNSIA=*ZOOM	QVX:LNSIA	LNSIA=*ZOOM		✓	
	PERIPHERY FOCUS(PF)		VXX:LNSIE=*PERIPHERY FOCUS	QVX:LNSIE	LNSIE=*PERIPHERY FOCUS		✓	
	H/V		VXX:LNSSB=*H*V	QVX:LNSSB	LNSSB=*H*V		✓	
	H/V F		VXX:LNSSC=*H*V*F	QVX:LNSSC	LNSSC=*H*V*F		✓	
	H/V F Z		VXX:LNSSD=*H*V*F*Z	QVX:LNSSD	LNSSD=*H*V*F*Z		✓	
	H/V F Z PF		VXX:LNSSF=*H*V*F*Z*PF	QVX:LNSSF	LNSIE=*H*V*F*Z*PF		✓	
	*HORIZONTAL(H)	min.	-*****		-*****		-5031	
		max.	+*****		+*****		+5031	
	*VERTICAL(V)	min.	-*****		-*****		-6043	
		max.	+*****		+*****		+6042	
	*FOCUS(F)	min.	+*****		+*****		0	
		max.	+*****		+*****		1023	
	*ZOOM(Z)	min.	+*****		+*****		0	
		max.	+*****		+*****		1023	
	*PERIPHERY FOCUS(PF)	min.	+*****		+*****		0	
		max.	+*****		+*****		1023	
STATUS KEY			STS				✓	
LENS FOCUS KEY			OLF				✓	
LENS SHIFT KEY			OLH				✓	
LENS ZOOM KEY			OLZ				✓	
DIGITAL LINK KEY			DLK				✓	
INPUT MENU KEY			IPT				✓	
SELF DIAGNOSIS				QVX:ERRS1	ERRS1=*****		✓	
				QVX:ERRS2	ERRS2=*****		✓	
PICTURE MODE	DYNAMIC		VPM:DYN	QPM	DYN		✓	
	NATURAL		VPM:NAT		NAT		✓	
	STANDARD		VPM:STD		STD		✓	
	CINEMA		VPM:CIN		CIN		✓	
	GRAPHIC		VPM:GRA		GRA		✓	
	DICOM SIM.		VPM:DIC		DIC		✓	
	REC709		VPM:709		709		✓	
CONTRAST	+1		VCN:001	QVR	001		✓	
	+63		VCN:063		063		✓	
BRIGHTNESS	+1		VBR:001	QVB	001		✓	
	+63		VBR:063		063		✓	
COLOR	+1		VCO:001	QVC	001		✓	
	+63		VCO:063		063		✓	
TINT	+1		VTN:001	QVT	001		✓	
	+63		VTN:063		063		✓	
SHARPNESS	0		VSR:000	QVS	000		✓	
	15		VSR:015		015		✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		REZ12 SERIES	
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	REZ12 /10/80 FEZ120C /100C/080C		
PICTURE	WHITE GAIN	0		VWH: 00	QWH	00		✓	
		10		VWH: 10		10		✓	
	COLOR TEMPERATURE	USER1(USER)		OTE: 04	QTE	4		✓	
		USER2		OTE: 09		9		✓	
		DEFAULT		OTE: 10		10		✓	
		3200K		OTE: 3200		3200		✓	
		3300K		OTE: 3300		3300		✓	
		9200K		OTE: 9200		9200		✓	
		9300K		OTE: 9300		9300		✓	
		9400K		OTE: 9400		9400		✓	
		12900K		OTE: 12900		12900		✓	
		13000K		OTE: 13000		13000		✓	
	COLOR TEMP-NAME SETTING USER1	COLORTEMP1		VXX: NCGS1=COLORTEMP1	QVX: NCGS1		NCGS1=COLORTEMP1		✓
	COLOR TEMP-NAME SETTING USER2	COLORTEMP2		VXX: NCGS3=COLORTEMP2	QVX: NCGS3		NCGS3=COLORTEMP2		✓
	COLOR TEMP-NAME CLEAR USER1	COLORTEMP1		VXX: NCLI1=+00000					✓
	COLOR TEMP-NAME CLEAR USER2	COLORTEMP2		VXX: NCLI3=+00000					✓
	WHITE BALANCE LOW-RED	-127		VOR: 001	QOR	001		✓	
		+127		VOR: 255		255		✓	
	WHITE BALANCE LOW-GREEN	-127		VOG: 001	QOG	001		✓	
		+127		VOG: 255		255		✓	
	WHITE BALANCE LOW-BLUE	-127		VOB: 001	QOB	001		✓	
		+127		VOB: 255		255		✓	
	WHITE BALANCE HIGH-RED	0		VHR: 000	QHR	000		✓	
		+255		VHR: 255		255		✓	
	WHITE BALANCE HIGH-GREEN	0		VHG: 000	QHG	000		✓	
		+255		VHG: 255		255		✓	
	WHITE BALANCE HIGH-BLUE	0		VHB: 000	QHB	000		✓	
		+255		VHB: 255		255		✓	
	GAMMA	1.8		VGA: 1.8	QGA	1.8		✓	
		2.0		VGA: 2.0		2.0		✓	
		2.2		VGA: 2.2		2.2		✓	
		USER1		VGA: US1		US1		✓	
		HDR HLG		VGA: HD1		HD1		✓	
		HDR ST2048-500		VGA: HD2		HD2		✓	
		HDR ST2048-1000		VGA: HD3		HD3		✓	
		DEFAULT		VGA: DEF		DEF		✓	
	GAMMA-HDR HLG SYSTEM GAMMA	min.	(0.1step)	VXX: HLG1=+1.00	QVX: HLG1		HLG1=1.00		✓
		max.		VXX: HLG1=+1.62			HLG1=1.62		✓
	GAMMA-NAME SETTING USER1	GAMMAUSER1		VXX: NCGS2=GAMMAUSER1	QVX: NCGS2		NCGS2=GAMMAUSER1		✓
	GAMMA-NAME CLEAR USER1	GAMMAUSER1		VXX: NCLI2=+00000					✓
	DAYLIGHT VIEW FRONT INSTALL	OFF		VXX: DLVI0=+00000	QVX: DLVI0		DLVI0=+00000		✓
		AUTO(1)		VXX: DLVI0=+00001			DLVI0=+00001		✓
		ON(2)		VXX: DLVI0=+00002			DLVI0=+00002		✓
		ON(3)		VXX: DLVI0=+00003			DLVI0=+00003		✓
		4		VXX: DLVI0=+00004			DLVI0=+00004		✓
		5		VXX: DLVI0=+00005			DLVI0=+00005		✓
		6		VXX: DLVI0=+00006			DLVI0=+00006		✓
		7		VXX: DLVI0=+00007			DLVI0=+00007		✓
		8		VXX: DLVI0=+00008			DLVI0=+00008		✓
		9		VXX: DLVI0=+00009			DLVI0=+00009		✓
NOISE REDUCTION	OFF		VNS: 0	QNS	0		✓		
	1		VNS: 1		1		✓		
	2		VNS: 2		2		✓		
	3		VNS: 3		3		✓		
	4		VNS: 4		4		✓		
	5		VNS: 5		5		✓		
	6		VNS: 6		6		✓		
DYNAMIC CONTRAST/IRIS	OFF		OAI: 0	QAI	0		✓		
	1		OAI: 1		1		✓		
	2		OAI: 2		2		✓		
	3		OAI: 3		3		✓		
	USER		OAI: 4		4		✓		
DYNAMIC CONTRAST/AUTO IRIS (AUTO CONTRAST)	OFF		OAI: A000	QAI: A	000		✓		
	1		OAI: A001		001		✓		
	255		OAI: A255		255		✓		
DYNAMIC CONTRAST (BRIGHT SIGNAL LEVEL)	6%		VXX: DYCI1=+00006	QVX: DYCI1		00006		✓	
	50%		VXX: DYCI1=+00050			00050		✓	
DYNAMIC CONTRAST (LIGHTS OUT TIMER)	DISABLE		VXX: DYCS2=OFF	QVX: DYCS2		OFF		✓	
	0.0s		VXX: DYCS2=0.0			0.0		✓	
	10.0s		VXX: DYCS2=10.0			10.0		✓	
DYNAMIC CONTRAST (LIGHTS OUT SIGNAL LEVEL)	0		VXX: DYCI3=+00000	QVX: DYCI3		00000		✓	
	5		VXX: DYCI3=+00005			00005		✓	
DYNAMIC CONTRAST (LIGHTS OUT FADE-IN)	0.0s(OFF)		VXX: DYCS4=0.0	QVX: DYCS4		DYCS4=0.0		✓	
	0.5s		VXX: DYCS4=0.5			DYCS4=0.5		✓	
	1.0s		VXX: DYCS4=1.0			DYCS4=1.0		✓	
	1.5s		VXX: DYCS4=1.5			DYCS4=1.5		✓	
	2.0s		VXX: DYCS4=2.0			DYCS4=2.0		✓	
	2.5s		VXX: DYCS4=2.5			DYCS4=2.5		✓	
	3.0s		VXX: DYCS4=3.0			DYCS4=3.0		✓	
	3.5s		VXX: DYCS4=3.5			DYCS4=3.5		✓	
	4.0s		VXX: DYCS4=4.0			DYCS4=4.0		✓	
	5.0s		VXX: DYCS4=5.0			DYCS4=5.0		✓	
	7.0s		VXX: DYCS4=7.0			DYCS4=7.0		✓	
	10.0s		VXX: DYCS4=10.0			DYCS4=10.0		✓	
DYNAMIC CONTRAST (LIGHTS OUT FADE-OUT)	0.0s(OFF)		VXX: DYCS5=0.0	QVX: DYCS5		DYCS5=0.0		✓	
	0.5s		VXX: DYCS5=0.5			DYCS5=0.5		✓	
	1.0s		VXX: DYCS5=1.0			DYCS5=1.0		✓	
	1.5s		VXX: DYCS5=1.5			DYCS5=1.5		✓	
	2.0s		VXX: DYCS5=2.0			DYCS5=2.0		✓	
	2.5s		VXX: DYCS5=2.5			DYCS5=2.5		✓	
	3.0s		VXX: DYCS5=3.0			DYCS5=3.0		✓	
	3.5s		VXX: DYCS5=3.5			DYCS5=3.5		✓	
	4.0s		VXX: DYCS5=4.0			DYCS5=4.0		✓	
	5.0s		VXX: DYCS5=5.0			DYCS5=5.0		✓	
	7.0s		VXX: DYCS5=7.0			DYCS5=7.0		✓	
	10.0s		VXX: DYCS5=10.0			DYCS5=10.0		✓	
DYNAMIC CONTRAST (CONTRAST MODE)	CONTRAST MODE 1		VXX: DYCI6=+00001	QVX: DYCI6		DYCI6=+00001		✓	
	CONTRAST MODE 2		VXX: DYCI6=+00002			DYCI6=+00002		✓	
DYNAMIC CONTRAST (BRILLIANT CORRECTION)	OFF		VXX: DYCI7=+00000	QVX: DYCI7		DYCI7=+00000		✓	
	BRILLIANT CORRECTION 1		VXX: DYCI7=+00001			DYCI7=+00001		✓	
	BRILLIANT CORRECTION 2		VXX: DYCI7=+00002			DYCI7=+00002		✓	
	BRILLIANT CORRECTION 3		VXX: DYCI7=+00003			DYCI7=+00003		✓	
DYNAMIC CONTRAST/MANUAL IRIS (MANUAL INTENSITY)	OFF		OAI: M000	QAI: M	000		✓		
	1		OAI: M001		001		✓		
	255		OAI: M255		255		✓		
DYNAMIC CONTRAST (DYNAMIC GAMMA)	OFF		OAI: D0	QAI: D	0		✓		
	1		OAI: D1		1		✓		
	2		OAI: D2		2		✓		
	3		OAI: D3		3		✓		
COLOR SPACE	NATIVE		VXX: CSPI1=+00000	QVX: CSPI1		CSPI1=+00000		✓	
	ITU-709		VXX: CSPI1=+00001			CSPI1=+00001		✓	
	DCI-P3		VXX: CSPI1=+00002			CSPI1=+00002		✓	
	ITU2020		VXX: CSPI1=+00003			CSPI1=+00003		✓	
SYSTEM SELECTOR	RGB		ORF: 0	QRF	0		✓		
HDMI/DIGITAL LINK/DisplayPort/	YPbPr		ORF: 1		1		✓		
SLOT-HDMI/SLOT-DIGITAL LINK/	AUTO		ORF: 2		2		✓		
DEFAULT PICTURE MODE	AUTO		VXX: DPMS1=AUT	QVX: DPMS1		DPMS1=AUT		✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		REZ12 SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	REZ12 /10/80 FEZ120C /100C/080C	
POSITION		STANDARD		VXX:DPMS1=STD		DPMS1=STD		✓
		DYNAMIC		VXX:DPMS1=DYN		DPMS1=DYN		✓
		NATURAL		VXX:DPMS1=NAT		DPMS1=NAT		✓
		CINEMA		VXX:DPMS1=CIN		DPMS1=CIN		✓
		GRAPHIC		VXX:DPMS1=GRA		DPMS1=GRA		✓
		DICOM SIM./DICOM REC709		VXX:DPMS1=DIC VXX:DPMS1=709		DPMS1=DIC DPMS1=709		✓ ✓
		GEOMETRY		VXX:GMMI0=+00000	QVX:GMMI0	GMMI0=+00000		✓
		KEYSTONE		VXX:GMMI0=+00001		GMMI0=+00001		✓
		CURVED		VXX:GMMI0=+00002		GMMI0=+00002		✓
		PC-1		VXX:GMMI0=+00003		GMMI0=+00003		✓
		PC-2		VXX:GMMI0=+00004		GMMI0=+00004		✓
		PC-3		VXX:GMMI0=+00005		GMMI0=+00005		✓
		CORNER-CORRECTION		VXX:GMMI0=+00010		GMMI0=+00010		✓
		GEOMETRY-KEYSTONE-LENS THROW RATIO	0.7 16.5	0.1 step VXX:GMKS0=+00.7 VXX:GMKS0=+16.5	QVX:GMKS0	GMKS0=+00.7 GMKS0=+16.5		✓ ✓
		GEOMETRY-KEYSTONE-VERTICAL BALANCE	-60 +60	VXX:GMKI4=-00060 VXX:GMKI4=+00060	QVX:GMKI4	GMKI4=-00060 GMKI4=+00060		✓ ✓
		GEOMETRY-KEYSTONE-HORIZONTAL BALANCE	-30 +30	VXX:GMKI7=-00030 VXX:GMKI7=+00030	QVX:GMKI7	GMKI7=-00030 GMKI7=+00030		✓ ✓
		GEOMETRY-KEYSTONE-VERTICAL KEYSTONE	-40.0 (-45.0)* +40.0 (+45.0)*	0.2 step VXX:GMKS8=-40.0 VXX:GMKS8=+40.0	QVX:GMKS8	GMKS8=-40.0 GMKS8=+40.0		✓ ✓
		GEOMETRY-KEYSTONE-HORIZONTAL KEYSTONE	-15.0 (-40.0)* +15.0 (+40.0)*	0.2 step VXX:GMKS9=-15.0 VXX:GMKS9=+15.0	QVX:GMKS9	GMKS9=-15.0 GMKS9=+15.0		✓ ✓
		GEOMETRY-CURVED-LENS THROW RATIO	0.7 16.5	0.1 step VXX:GMCS0=+00.7 VXX:GMCS0=+16.5	QVX:GMCS0	GMCS0=+00.7 GMCS0=+16.5		✓ ✓
		GEOMETRY-CURVED-VERTICAL ARC	-50 (-100)* +50 (+100)*	VXX:GMCI3=-00050 VXX:GMCI3=+00050	QVX:GMCI3	GMCI3=-00050 GMCI3=+00050		✓ ✓
		GEOMETRY-CURVED-HORIZONTAL ARC	-50 (-100)* +50 (+100)*	VXX:GMCI7=-00050 VXX:GMCI7=+00050	QVX:GMCI7	GMCI7=-00050 GMCI7=+00050		✓ ✓
		GEOMETRY-CURVED-VERTICAL BALANCE	-60 +60	VXX:GMCI2=-00060 VXX:GMCI2=+00060	QVX:GMCI2	GMCI2=-00060 GMCI2=+00060		✓ ✓
		GEOMETRY-CURVED-HORIZONTAL BALANCE	-30 +30	VXX:GMCI6=-00030 VXX:GMCI6=+00030	QVX:GMCI6	GMCI6=-00030 GMCI6=+00030		✓ ✓
		GEOMETRY-CURVED-VERTICAL KEYSTONE	-40.0 (-45.0)* +40.0 (+45.0)*	0.2 step VXX:GMCS8=-40.0 VXX:GMCS8=+40.0	QVX:GMCS8	GMCS8=-40.0 GMCS8=+40.0		✓ ✓
		GEOMETRY-CURVED-HORIZONTAL KEYSTONE	-15.0 (-40.0)* +15.0 (+40.0)*	0.2 step VXX:GMCS9=-15.0 VXX:GMCS9=+15.0	QVX:GMCS9	GMCS9=-15.0 GMCS9=+15.0		✓ ✓
	GEOMETRY-CURVED-MAINTAIN ASPECT RATIO	OFF ON	VXX:GMCIA=+00000 VXX:GMCIA=+00001	QVX:GMCIA	GMCIA=+00000 GMCIA=+00001		✓ ✓	
	GEOMETRY-CORNER CORRECTION-UPPER LEFT(V)	min. max.	VXX:GMFI1=+00000 VXX:GMFI1=+00300	QVX:GMFI1	GMFI1=+00000 GMFI1=+00300		-240 +600	
	GEOMETRY-CORNER CORRECTION-UPPER RIGHT(V)	min. max.	VXX:GMFI2=+00000 VXX:GMFI2=+00300	QVX:GMFI2	GMFI2=+00000 GMFI2=+00300		-240 +600	
	GEOMETRY-CORNER CORRECTION-LOWER LEFT(V)	min. max.	VXX:GMFI3=-00300 VXX:GMFI3=+00000	QVX:GMFI3	GMFI3=-00300 GMFI3=+00000		-600 +240	
	GEOMETRY-CORNER CORRECTION-LOWER RIGHT(V)	min. max.	VXX:GMFI4=-00300 VXX:GMFI4=+00000	QVX:GMFI4	GMFI4=-00300 GMFI4=+00000		-600 +240	
	GEOMETRY-CORNER CORRECTION-LINEARITY(V)	min. max.	VXX:GMFI5=-00127 VXX:GMFI5=+00127	QVX:GMFI5	GMFI5=-00127 GMFI5=+00127		-127 +127	
	GEOMETRY-CORNER CORRECTION-UPPER LEFT(H)	min. max.	VXX:GMFI6=+00000 VXX:GMFI6=+00480	QVX:GMFI6	GMFI6=+00000 GMFI6=+00480		-384 +960	
	GEOMETRY-CORNER CORRECTION-UPPER RIGHT(H)	min. max.	VXX:GMFI7=-00480 VXX:GMFI7=+00000	QVX:GMFI7	GMFI7=-00480 GMFI7=+00000		-960 +384	
	GEOMETRY-CORNER CORRECTION-LOWER LEFT(H)	min. max.	VXX:GMFI8=+00000 VXX:GMFI8=+00480	QVX:GMFI8	GMFI8=+00000 GMFI8=+00480		-384 +960	
	GEOMETRY-CORNER CORRECTION-LOWER RIGHT(H)	min. max.	VXX:GMFI9=-00480 VXX:GMFI9=+00000	QVX:GMFI9	GMFI9=-00480 GMFI9=+00000		-960 +384	
	GEOMETRY-CORNER CORRECTION-LINEARITY(H)	min. max.	VXX:GMFIA=-00127 VXX:GMFIA=+00127	QVX:GMFIA	GMFIA=-00127 GMFIA=+00127		-127 +127	
	GEOMETRY-CORNER/PINCUSHION-LINEARITY	AUTO MANUAL	VXX:GMFIF=+00000 VXX:GMFIF=+00001	QVX:GMFIF	GMFIF=+00000 GMFIF=+00001		✓ ✓	
	GEOMETRY - FREE GRID(ON/OFF)	OFF ON	VXX:GMGI1=+00000 VXX:GMGI1=+00001	QVX:GMGI1	GMGI1=+00000 GMGI1=+00001		✓ ✓	
	GEOMETRY - FREE GRID - INITIALIZE		VXX:GMGI2=+00001				✓	
	GEOMETRY - FREE GRID - GRID RESOLUTION	2x2 3x3 5x5 9x9 17x17	VXX:GMGI3=+00002 VXX:GMGI3=+00003 VXX:GMGI3=+00005 VXX:GMGI3=+00009 VXX:GMGI3=+00017	QVX:GMGI3	GMGI3=+00002 GMGI3=+00003 GMGI3=+00005 GMGI3=+00009 GMGI3=+00017		✓ ✓ ✓ ✓ ✓	
	GEOMETRY - FREE GRID - GRID COLOR	OFF WHITE BLACK RED GREEN BLUE CYAN MAGENTA YELLOW	VXX:GMGI4=+00000 VXX:GMGI4=+00001 VXX:GMGI4=+00002 VXX:GMGI4=+00003 VXX:GMGI4=+00004 VXX:GMGI4=+00005 VXX:GMGI4=+00006 VXX:GMGI4=+00007 VXX:GMGI4=+00008	QVX:GMGI4	GMGI4=+00000 GMGI4=+00001 GMGI4=+00002 GMGI4=+00003 GMGI4=+00004 GMGI4=+00005 GMGI4=+00006 GMGI4=+00007 GMGI4=+00008		✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓	
	GEOMETRY - FREE GRID - CONTROL POINTS	POINT HORIZONTAL LINE VERTICAL LINE	VXX:GMGI5=+00000 VXX:GMGI5=+00001 VXX:GMGI5=+00002	QVX:GMGI5	GMGI5=+00000 GMGI5=+00001 GMGI5=+00002		✓ ✓ ✓	
	GEOMETRY - FREE GRID - GRID WIDTH	1 10	VXX:GMGI7=+00001 VXX:GMGI7=+00010	QVX:GMGI7	GMGI7=+00001 GMGI7=+00010		✓ ✓	
	GEOMETRY - FREE GRID - CONTROL POINTS COLOR	WHITE BLACK RED GREEN BLUE CYAN MAGENTA YELLOW	VXX:GMGI8=+00001 VXX:GMGI8=+00002 VXX:GMGI8=+00003 VXX:GMGI8=+00004 VXX:GMGI8=+00005 VXX:GMGI8=+00006 VXX:GMGI8=+00007 VXX:GMGI8=+00008	QVX:GMGI8	GMGI8=+00001 GMGI8=+00002 GMGI8=+00003 GMGI8=+00004 GMGI8=+00005 GMGI8=+00006 GMGI8=+00007 GMGI8=+00008		✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓	
	SHIFT-HORIZONTAL	0 +4095	VTH:0000 VTH:4095	QTH	0000 4095		✓ ✓	
	SHIFT-VERTICAL	0 +4094	VTV:0000 VTV:4094	QTV	0000 4094		✓ ✓	
	ASPECT	AUTO/VID AUTO/DEFAULT NORMAL(4:3) WIDE(16:9) NATIVE(through) FULL(HV FIT) H-FIT V-FIT	VSE:0 VSE:1 VSE:2 VSE:5 VSE:6 VSE:9 VSE:10	QSE	0 1 2 5 6 9 10		✓ ✓ ✓ ✓ ✓ ✓ ✓	
	ZOOM-HORIZONTAL	50 999	OZH:050 OZH:999	QZH	050 999		✓ ✓	
	ZOOM-VERTICAL	50 999	OZV:050 OZV:999	QZV	050 999		✓ ✓	
	ZOOM-BOTH	50 999	OZO:050 OZO:999	QZO	050 999		✓ ✓	
	ZOOM-INTERLOCKED	OFF ON	OZS:0 OZS:1	QZS	0 1		✓ ✓	
	ZOOM-MODE	INTERNAL FULL	OZT:0 OZT:1	QZT	0 1		✓ ✓	
	DIGITAL CINEMA REALITY	AUTO OFF 30p/25p FIXED	OPD:0 OPD:1 OPD:2	QPD	0 1 2		✓ ✓ ✓	
	GRADATION SMOOTHER	OFF 1	VXX:GRS11=+00000 VXX:GRS11=+00001	QVX:GRS11	GRS11=+00000 GRS11=+00001		✓ ✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		REZ12 SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	REZ12 /10/80 FEZ120C /100C/080C	
ADVANCED		2		VXX:GRS11=+00002		GRS11=+00002		✓
		3		VXX:GRS11=+00003		GRS11=+00003		✓
	BLANKING-UPPER	min. max.		DBU:0000 DBU:2398	QLU	0000 2398		0 2398
	BLANKING-LOWER	min. max.		DBB:0000 DBB:2398	QLB	0000 2398		0 2398
	BLANKING-RIGHT	min. max.		DBR:0000 DBR:3838	QLR	0000 3838		0 3838
	BLANKING-LEFT	min. max.		DBL:0000 DBL:3838	QLL	0000 3838		0 3838
	CUSTOM MASKING *	OFF PC-1 PC-2 PC-3		VXX:MSKI1=+00000 VXX:MSKI1=+00001 VXX:MSKI1=+00002 VXX:MSKI1=+00003	QVX:MSKI1	MSKI1=+00000 MSKI1=+00001 MSKI1=+00002 MSKI1=+00003		✓ ✓ ✓ ✓
	EDGE BLENDING	OFF ON USER		VXX:EDBI0=+00000 VXX:EDBI0=+00001 VXX:EDBI0=+00002	QVX:EDBI0	EDBI0=+00000 EDBI0=+00001 EDBI0=+00002		✓ ✓ ✓
	EDGE BLENDING-UPPER ON/OFF	OFF ON		VGU:0 VGU:1	QGU	0 1		✓ ✓
	EDGE BLENDING-LOWER ON/OFF	OFF ON		VGB:0 VGB:1	QGB	0 1		✓ ✓
	EDGE BLENDING-LEFT ON/OFF	OFF ON		VGL:0 VGL:1	QGL	0 1		✓ ✓
	EDGE BLENDING-RIGHT ON/OFF	OFF ON		VGR:0 VGR:1	QGR	0 1		✓ ✓
	EDGE BLENDING-START-UPPER	min. max.		VEU:0000 VEU:2272	QEU	0000 2272		0 2397
	EDGE BLENDING-START-LOWER	min. max.		VEB:0000 VEB:2272	QEB	0000 2272		0 2397
	EDGE BLENDING-START-LEFT	min. max.		VEL:0000 VEL:3712	QEL	0000 3712		0 3788
	EDGE BLENDING-START-RIGHT	min. max.		VER:0000 VER:3712	QER	0000 3712		0 3788
	EDGE BLENDING-WIDTH-UPPER	min. max.		VXX:EUWI0=+00000 VXX:EUWI0=+02272	QVX:EUWI0	EUWI0=+00000 EUWI0=+02272		0 2400
	EDGE BLENDING-WIDTH-LOWER	min. max.		VXX:EBWI0=+00000 VXX:EBWI0=+02272	QVX:EBWI0	EBWI0=+00000 EBWI0=+02272		0 2400
	EDGE BLENDING-WIDTH-LEFT	min. max.		VXX:ELWI0=+00000 VXX:ELWI0=+03712	QVX:ELWI0	ELWI0=+00000 ELWI0=+03712		0 3840
	EDGE BLENDING-WIDTH-RIGHT	min. max.		VXX:ERWI0=+00000 VXX:ERWI0=+03712	QVX:ERWI0	ERWI0=+00000 ERWI0=+03712		0 3840
	EDGE BLENDING-MARKER-ON/OFF	OFF ON		VGM:0 VGM:1	QGM	0 1		✓ ✓
	EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL	0 (W,R,G,B) 255 (W,R,G,B)		VJI:000,000,000,000 VJI:255,255,255,255	QJI	000,000,000,000 255,255,255,255		✓ ✓
	EDGE BLENDING-NON-OVERLAPPED BLACK LEVEL-INTERLOCKED	OFF ON		VXX:EBII1=+00000 VXX:EBII1=+00001	QVX:EBII1	EBII1=+00000 EBII1=+00001		✓ ✓
	EDGE BLENDING-BLACK BORDER LEVEL	0 (W,R,G,B) 255 (W,R,G,B)		VJO:000,000,000,000 VJO:255,255,255,255	QJO	000,000,000,000 255,255,255,255		✓ ✓
	EDGE BLENDING-BLACK BORDER LEVEL-INTERLOCKED	OFF ON		VXX:EBII2=+00000 VXX:EBII2=+00001	QVX:EBII2	EBII2=+00000 EBII2=+00001		✓ ✓
	EDGE BLENDING-BLACK BORDER WIDTH-UPPER	min. max.		VJU:0000 VJU:2272	QJU	0000 2272		0 2400
	EDGE BLENDING-BLACK BORDER WIDTH-LOWER	min. max.		VJB:0000 VJB:2272	QJB	0000 2272		0 2400
	EDGE BLENDING-BLACK BORDER WIDTH-LEFT	min. max.		VJL:0000 VJL:3712	QJL	0000 3712		0 3840
	EDGE BLENDING-BLACK BORDER WIDTH-RIGHT	min. max.		VJR:0000 VJR:3712	QJR	0000 3712		0 3840
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE -	OFF ON		VXX:EBFI1=+00000 VXX:EBFI1=+00001	QVX:EBFI1	EBFI1=+00000 EBFI1=+00001		✓ ✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE -	OFF ON		VXX:EBFI2=+00000 VXX:EBFI2=+00001	QVX:EBFI2	EBFI2=+00000 EBFI2=+00001		✓ ✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - LEFT	OFF ON		VXX:EBFI3=+00000 VXX:EBFI3=+00001	QVX:EBFI3	EBFI3=+00000 EBFI3=+00001		✓ ✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE -	OFF ON		VXX:EBFI4=+00000 VXX:EBFI4=+00001	QVX:EBFI4	EBFI4=+00000 EBFI4=+00001		✓ ✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - UPPER - ADJUSTMENT POINTS	2 3 5 9 17		VXX:EFPI1=+00002 VXX:EFPI1=+00003 VXX:EFPI1=+00005 VXX:EFPI1=+00009 VXX:EFPI1=+00017	QVX:EFPI1	EFPI1=+00002 EFPI1=+00003 EFPI1=+00005 EFPI1=+00009 EFPI1=+00017		✓ ✓ ✓ ✓ ✓
	- UPPER - INITIALIZE	EXECUTE		VXX:EFII1=+00001				✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - LEFT - ADJUSTMENT POINTS	2 3 5 9 17		VXX:EFPI2=+00002 VXX:EFPI2=+00003 VXX:EFPI2=+00005 VXX:EFPI2=+00009 VXX:EFPI2=+00017	QVX:EFPI2	EFPI2=+00002 EFPI2=+00003 EFPI2=+00005 EFPI2=+00009 EFPI2=+00017		✓ ✓ ✓ ✓ ✓
	- LEFT - INITIALIZE	EXECUTE		VXX:EFII2=+00001				✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - LEFT - ADJUSTMENT POINTS	2 3 5 9 17		VXX:EFPI3=+00002 VXX:EFPI3=+00003 VXX:EFPI3=+00005 VXX:EFPI3=+00009 VXX:EFPI3=+00017	QVX:EFPI3	EFPI3=+00002 EFPI3=+00003 EFPI3=+00005 EFPI3=+00009 EFPI3=+00017		✓ ✓ ✓ ✓ ✓
	- LEFT - INITIALIZE	EXECUTE		VXX:EFII3=+00001				✓
	EDGE BLENDING - BLACK LEVEL ADJUST - BLACK BORDER AREA - FREE SHAPE - RIGHT - ADJUSTMENT POINTS	2 3 5 9 17		VXX:EFPI4=+00002 VXX:EFPI4=+00003 VXX:EFPI4=+00005 VXX:EFPI4=+00009 VXX:EFPI4=+00017	QVX:EFPI4	EFPI4=+00002 EFPI4=+00003 EFPI4=+00005 EFPI4=+00009 EFPI4=+00017		✓ ✓ ✓ ✓ ✓
	- RIGHT - INITIALIZE	EXECUTE		VXX:EFII4=+00001				✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-UPPER	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS0=000,000,000,000 VXX:EBBS0=255,255,255,255	QVX:EBBS0	EBBS0=000,000,000,000 EBBS0=255,255,255,255		✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LOWER	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS1=000,000,000,000 VXX:EBBS1=255,255,255,255	QVX:EBBS1	EBBS1=000,000,000,000 EBBS1=255,255,255,255		✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LEFT	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS2=000,000,000,000 VXX:EBBS2=255,255,255,255	QVX:EBBS2	EBBS2=000,000,000,000 EBBS2=255,255,255,255		✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-RIGHT	0 (W,R,G,B) 255 (W,R,G,B)		VXX:EBBS3=000,000,000,000 VXX:EBBS3=255,255,255,255	QVX:EBBS3	EBBS3=000,000,000,000 EBBS3=255,255,255,255		✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-UPPER INTERLOCKED	OFF ON		VXX:EBII3=+00000 VXX:EBII3=+00001	QVX:EBII3	EBII3=+00000 EBII3=+00001		✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LOWER INTERLOCKED	OFF ON		VXX:EBII4=+00000 VXX:EBII4=+00001	QVX:EBII4	EBII4=+00000 EBII4=+00001		✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-LEFT INTERLOCKED	OFF ON		VXX:EBII5=+00000 VXX:EBII5=+00001	QVX:EBII5	EBII5=+00000 EBII5=+00001		✓ ✓
	EDGE BLENDING-OVERLAPPED BLACK LEVEL-RIGHT INTERLOCKED	OFF ON		VXX:EBII6=+00000 VXX:EBII6=+00001	QVX:EBII6	EBII6=+00000 EBII6=+00001		✓ ✓
	EDGE BLENDING-MODE	SOFTEDGE/BLACK LEVEL BLACK LEVEL ONLY		VXX:EBMI1=+00000 VXX:EBMI1=+00001	QVX:EBMI1	EBMI1=+00000 EBMI1=+00001		✓ ✓
	EDGE BLENDING-AUTO TESTPATTERN	OFF ON		VXX:EATI1=+00000 VXX:EATI1=+00001	QVX:EATI1	EATI1=+00000 EATI1=+00001		✓ ✓
	FRAME RESPONSE	NORMAL FIXED		VXX:FDYI0=+00000 VXX:FDYI0=+00005	QVX:FDYI0	FDYI0=+00000 FDYI0=+00005		✓ ✓
	RASTER POSITION-HORIZONTAL	-2048 +2047		VRH:2952 VRH:7047	QRH	2952 7047		✓ ✓
	RASTER POSITION-VERTICAL	-2048 +2047		VRV:2952 VRV:7047	QRV	2952 7047		✓ ✓
LANGUAGE	English		OLG:ENG	QLG	ENG		✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		REZ12 SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	REZ12 /10/80 FEZ120C /100C/080C	
DISPLAY LANGUAGE		German		OLG: DEU		DEU		✓
		French		OLG: FRA		FRA		✓
		Spanish		OLG: ESP		ESP		✓
		Italian		OLG: ITL		ITL		✓
		Japanese		OLG: JPN		JPN		✓
		Chinese		OLG: CHI		CHI		✓
		Russian		OLG: RUS		RUS		✓
		Korea		OLG: KOR		KOR		✓
	Portuguse		OLG: POR		POR		✓	
	COLOR MATCHING	OFF		VXX: CMAI0=+00000	QVX: CMAI0	CMAI0=+00000		✓
		3COLORS		VXX: CMAI0=+00001		CMAI0=+00001		✓
		7COLORS		VXX: CMAI0=+00002		CMAI0=+00002		✓
		MEASURED		VXX: CMAI0=+00004		CMAI0=+00004		✓
	COLOR MATCHING-RESET MODE	NATIVE		VXX: CRMI1=+00000	QVX: CRMI1	CRMI1=+00000		✓
		PICTURE		VXX: CRMI1=+00001		CRMI1=+00001		✓
	COLOR MATCHING-3COLORS-RED	0 (R,G,B)		VMR: 0000,0000,0000	QMR	0000,0000,0000		✓
		2048,2048,2048(R,G,B)		VMR: 2048,2048,2048		2048,2048,2048		✓
	COLOR MATCHING-3COLORS-GREEN	0 (R,G,B)		VMG: 0000,0000,0000	QMG	0000,0000,0000		✓
		2048,2048,2048(R,G,B)		VMG: 2048,2048,2048		2048,2048,2048		✓
	COLOR MATCHING-3COLORS-BLUE	0 (R,G,B)		VMB: 0000,0000,0000	QMB	0000,0000,0000		✓
		2048,2048,2048(R,G,B)		VMB: 2048,2048,2048		2048,2048,2048		✓
	COLOR MATCHING-3COLORS-WHITE	256 (GAIN)		VMW: 0256	QMW	0256		✓
		2048(GAIN)		VMW: 2048		2048		✓
	COLOR MATCHING-3COLORS-AUTO TESTPATTERN	OFF		VXX: CATI0=+00000	QVX: CATI0	CATI0=+00000		✓
		ON		VXX: CATI0=+00001		CATI0=+00001		✓
	COLOR MATCHING-3COLORS-RESET	EXECUTE		VXX: CREI1=+00001				✓
	COLOR MATCHING-7COLORS-RED	0 (R,G,B)		VXX: C7CS0=0000,0000,0000	QVX: C7CS0	C7CS0=0000,0000,0000		✓
		2048(R,G,B)		VXX: C7CS0=2048,2048,2048		C7CS0=2048,2048,2048		✓
	COLOR MATCHING-7COLORS-GREEN	0 (R,G,B)		VXX: C7CS1=0000,0000,0000	QVX: C7CS1	C7CS1=0000,0000,0000		✓
		2048(R,G,B)		VXX: C7CS1=2048,2048,2048		C7CS1=2048,2048,2048		✓
	COLOR MATCHING-7COLORS-BLUE	0 (R,G,B)		VXX: C7CS2=0000,0000,0000	QVX: C7CS2	C7CS2=0000,0000,0000		✓
		2048(R,G,B)		VXX: C7CS2=2048,2048,2048		C7CS2=2048,2048,2048		✓
	COLOR MATCHING-7COLORS-CYAN	0 (R,G,B)		VXX: C7CS3=0000,0000,0000	QVX: C7CS3	C7CS3=0000,0000,0000		✓
		2048(R,G,B)		VXX: C7CS3=2048,2048,2048		C7CS3=2048,2048,2048		✓
	COLOR MATCHING-7COLORS-MAGENTA	0 (R,G,B)		VXX: C7CS4=0000,0000,0000	QVX: C7CS4	C7CS4=0000,0000,0000		✓
		2048(R,G,B)		VXX: C7CS4=2048,2048,2048		C7CS4=2048,2048,2048		✓
	COLOR MATCHING-7COLORS-YELLOW	0 (R,G,B)		VXX: C7CS5=0000,0000,0000	QVX: C7CS5	C7CS5=0000,0000,0000		✓
		2048(R,G,B)		VXX: C7CS5=2048,2048,2048		C7CS5=2048,2048,2048		✓
	COLOR MATCHING-7COLORS-WHITE	0 (R,G,B)		VXX: C7CS6=0000,0000,0000	QVX: C7CS6	C7CS6=0000,0000,0000		✓
		2048(R,G,B)		VXX: C7CS6=2048,2048,2048		C7CS6=2048,2048,2048		✓
	COLOR MATCHING-7COLORS-AUTO TESTPATTERN	OFF		VXX: CATI1=+00000	QVX: CATI1	CATI1=+00000		✓
		ON		VXX: CATI1=+00001		CATI1=+00001		✓
	COLOR MATCHING-7COLORS-RESET	EXECUTE		VXX: CREI2=+00001				✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA BLACK	0,1,1 (Y,x,y)		VXX: CMMS0=00000,0001,0001	QVX: CMMS0	CMMS0=00000,0001,0001		✓
		65535,999,999(Y,x,y)		VXX: CMMS0=65535,0999,0999		CMMS0=65535,0999,0999		✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA RED	0,1,1 (Y,x,y)		VXX: CMMS1=00000,0001,0001	QVX: CMMS1	CMMS1=00000,0001,0001		✓
		65535,999,999(Y,x,y)		VXX: CMMS1=65535,0999,0999		CMMS1=65535,0999,0999		✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA GREEN	0,1,1 (Y,x,y)		VXX: CMMS2=00000,0001,0001	QVX: CMMS2	CMMS2=00000,0001,0001		✓
		65535,999,999(Y,x,y)		VXX: CMMS2=65535,0999,0999		CMMS2=65535,0999,0999		✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA BLUE	0,1,1 (Y,x,y)		VXX: CMMS3=00000,0001,0001	QVX: CMMS3	CMMS3=00000,0001,0001		✓
		65535,999,999(Y,x,y)		VXX: CMMS3=65535,0999,0999		CMMS3=65535,0999,0999		✓
	COLOR MATCHING-MEASURED MODE-MEASURED DATA WHITE	0,1,1 (Y,x,y)		VXX: CMMS4=00000,0001,0001	QVX: CMMS4	CMMS4=00000,0001,0001		✓
		65535,999,999(Y,x,y)		VXX: CMMS4=65535,0999,0999		CMMS4=65535,0999,0999		✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA RED	0,1,1 (Y,x,y)		VXX: CMTS0=00000,0001,0001	QVX: CMTS0	CMTS0=00000,0001,0001		✓
		65535,999,999(Y,x,y)		VXX: CMTS0=65535,0999,0999		CMTS0=65535,0999,0999		✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA GREEN	0,1,1 (Y,x,y)		VXX: CMTS1=00000,0001,0001	QVX: CMTS1	CMTS1=00000,0001,0001		✓
		65535,999,999(Y,x,y)		VXX: CMTS1=65535,0999,0999		CMTS1=65535,0999,0999		✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA BLUE	0,1,1 (Y,x,y)		VXX: CMTS2=00000,0001,0001	QVX: CMTS2	CMTS2=00000,0001,0001		✓
		65535,999,999(Y,x,y)		VXX: CMTS2=65535,0999,0999		CMTS2=65535,0999,0999		✓
	COLOR MATCHING-MEASURED MODE-TARGET DATA CYAN	0,1,1 (Y,x,y)		VXX: CMTS3=00000,0001,0001	QVX: CMTS3	CMTS3=00000,0001,0001		✓
		65535,999,999(Y,x,y)		VXX: CMTS3=65535,0999,0999		CMTS3=65535,0999,0999		✓
COLOR MATCHING-MEASURED MODE-TARGET DATA MAGENTA	0,1,1 (Y,x,y)		VXX: CMTS4=00000,0001,0001	QVX: CMTS4	CMTS4=00000,0001,0001		✓	
	65535,999,999(Y,x,y)		VXX: CMTS4=65535,0999,0999		CMTS4=65535,0999,0999		✓	
COLOR MATCHING-MEASURED MODE-TARGET DATA YELLOW	0,1,1 (Y,x,y)		VXX: CMTS5=00000,0001,0001	QVX: CMTS5	CMTS5=00000,0001,0001		✓	
	65535,999,999(Y,x,y)		VXX: CMTS5=65535,0999,0999		CMTS5=65535,0999,0999		✓	
COLOR MATCHING-MEASURED MODE-TARGET DATA WHITE	0,1,1 (Y,x,y)		VXX: CMTS6=00000,0001,0001	QVX: CMTS6	CMTS6=00000,0001,0001		✓	
	65535,999,999(Y,x,y)		VXX: CMTS6=65535,0999,0999		CMTS6=65535,0999,0999		✓	
COLOR MATCHING-MEASURED MODE-AUTO TESTPATTERN	OFF		VXX: CATI3=+00000	QVX: CATI3	CATI3=+00000		✓	
	ON		VXX: CATI3=+00001		CATI3=+00001		✓	
COLOR MATCHING-MEASURED MODE-RESET	EXECUTE		VXX: CREI3=+00001				✓	
COLOR CORRECTION	OFF		VCM: 0	QMC	0		✓	
	USER		VCM: 1		1		✓	
COLOR CORRECTION-RED	-30		VXX: CCRI0=-00030	QVX: CCRI0	CCRI0=-00030		✓	
	+30		VXX: CCRI0=+00030		CCRI0=+00030		✓	
COLOR CORRECTION-GREEN	-30		VXX: CCRI1=-00030	QVX: CCRI1	CCRI1=-00030		✓	
	+30		VXX: CCRI1=+00030		CCRI1=+00030		✓	
COLOR CORRECTION-BLUE	-30		VXX: CCRI2=-00030	QVX: CCRI2	CCRI2=-00030		✓	
	+30		VXX: CCRI2=+00030		CCRI2=+00030		✓	
COLOR CORRECTION-CYAN	-30		VXX: CCRI3=-00030	QVX: CCRI3	CCRI3=-00030		✓	
	+30		VXX: CCRI3=+00030		CCRI3=+00030		✓	
COLOR CORRECTION-MAGENTA	-30		VXX: CCRI4=-00030	QVX: CCRI4	CCRI4=-00030		✓	
	+30		VXX: CCRI4=+00030		CCRI4=+00030		✓	
COLOR CORRECTION-YELLOW	-30		VXX: CCRI5=-00030	QVX: CCRI5	CCRI5=-00030		✓	
	+30		VXX: CCRI5=+00030		CCRI5=+00030		✓	
BACKUP INPUT SETTING-BACKUP INPUT	PRIMARY		VXX: BACI1=+00001	QVX: BACI1	BACI1=+00001		✓	
	SECONDARY		VXX: BACI1=+00002		BACI1=+00002		✓	
	TOGGLE		VXX: BACI1=+00010		BACI1=+00010		✓	
BACKUP INPUT SETTING-BACKUP INPUT MODE	OFF		VXX: BACI2=+00000	QVX: BACI2	BACI2=+00000		✓	
	ON/1		VXX: BACI2=+00001		BACI2=+00001		✓	
BACKUP INPUT SETTING-AUTOMATIC SWITCHING	DISABLE		VXX: BACI3=+00001	QVX: BACI3	BACI3=+00001		✓	
	ENABLE		VXX: BACI3=+00002		BACI3=+00002		✓	
BACKUP INPUT SETTING-BACKUP INPUT STATUS	INACTIVE			QVX: BACI4	BACI4=+00000		✓	
	ACTIVE				BACI4=+00001		✓	
HDMI IN-HDMI1 SIGNAL LEVEL	0-1023		VXX: HSLI1=+00000	QVX: HSLI1	HSLI1=+00000		✓	
	64-940		VXX: HSLI1=+00001		HSLI1=+00001		✓	
	AUTO		VXX: HSLI1=+00002		HSLI1=+00002		✓	
HDMI IN-HDMI2 SIGNAL LEVEL	0-1023		VXX: HSLI2=+00000	QVX: HSLI2	HSLI2=+00000		✓	
	64-940		VXX: HSLI2=+00001		HSLI2=+00001		✓	
	AUTO		VXX: HSLI2=+00002		HSLI2=+00002		✓	
HDMI IN-HDMI1 AUTO GAMMA SELECT	DISABLE		VXX: HAGI1=+00000	QVX: HAGI1	HAGI1=+00000		✓	
	ENABLE		VXX: HAGI1=+00001		HAGI1=+00001		✓	
HDMI IN-HDMI2 AUTO GAMMA SELECT	DISABLE		VXX: HAGI2=+00000	QVX: HAGI2	HAGI2=+00000		✓	
	ENABLE		VXX: HAGI2=+00001		HAGI2=+00001		✓	
HDMI IN-HDMI1 AUTO COLOR SPACE SELECT	DISABLE		VXX: HACI1=+00000	QVX: HACI1	HACI1=+00000		✓	
	ENABLE		VXX: HACI1=+00001		HACI1=+00001		✓	
HDMI IN-HDMI2 AUTO COLOR SPACE SELECT	DISABLE		VXX: HACI2=+00000	QVX: HACI2	HACI2=+00000		✓	
	ENABLE		VXX: HACI2=+00001		HACI2=+00001		✓	
HDMI IN-HDMI1 EQUALIZER	0		VXX: HEQI1=+00000	QVX: HEQI1	HEQI1=+00000		✓	
	1		VXX: HEQI1=+00001		HEQI1=+00001		✓	
	2		VXX: HEQI1=+00002		HEQI1=+00002		✓	
	3		VXX: HEQI1=+00003		HEQI1=+00003		✓	
	4		VXX: HEQI1=+00004		HEQI1=+00004		✓	
	5		VXX: HEQI1=+00005		HEQI1=+00005		✓	
	6		VXX: HEQI1=+00006		HEQI1=+00006		✓	
	7		VXX: HEQI1=+00007		HEQI1=+00007		✓	
HDMI IN-HDMI2 EQUALIZER	0		VXX: HEQI2=+00000	QVX: HEQI2	HEQI2=+00000		✓	
	1		VXX: HEQI2=+00001		HEQI2=+00001		✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		REZ12 SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	REZ12 /10/80 FEZ120C /100C/080C	
				VXX: HEQI2=+00002		HEQI2=+00002		✓
				VXX: HEQI2=+00003		HEQI2=+00003		✓
				VXX: HEQI2=+00004		HEQI2=+00004		✓
				VXX: HEQI2=+00005		HEQI2=+00005		✓
				VXX: HEQI2=+00006		HEQI2=+00006		✓
				VXX: HEQI2=+00007		HEQI2=+00007		✓
	HDMI IN-HDMI1 EDID SELECT	4K/60p 4K/30p 2K 4K/60p/HDR		VXX: HESI1=+00000 VXX: HESI1=+00001 VXX: HESI1=+00002 VXX: HESI1=+00010	QVX: HESI1	HESI1=+00000 HESI1=+00001 HESI1=+00002 HESI1=+00010		✓ ✓ ✓ ✓
	HDMI IN-HDMI2 EDID SELECT	4K/60p 4K/30p 2K 4K/60p/HDR		VXX: HESI2=+00000 VXX: HESI2=+00001 VXX: HESI2=+00002 VXX: HESI2=+00010	QVX: HESI2	HESI2=+00000 HESI2=+00001 HESI2=+00002 HESI2=+00010		✓ ✓ ✓ ✓
	HDMI IN-HDMI1 EDID MODE	DEFAULT USER		VXX: EDMI3=+00000 VXX: EDMI3=+00010	QVX: EDMI3	EDMI3=+00000 EDMI3=+00010		✓ ✓
	HDMI IN-HDMI2 EDID MODE	DEFAULT USER		VXX: EDMI6=+00000 VXX: EDMI6=+00010	QVX: EDMI6	EDMI6=+00000 EDMI6=+00010		✓ ✓
	HDMI IN-HDMI* EDID RESOLUTION	HDMI1 HDMI2		VXX: EDRS3=****:****:*	QVX: EDRS3	EDRS3=****:****:*		✓
				VXX: EDRS6=****:****:*	QVX: EDRS6	EDRS6=****:****:*		✓
		* PARAMETER	1024x768p 1280x720p 1280x800p 1280x1024p 1366x768p 1400x1050p 1440x900p 1600x900p 1600x1200p 1680x1050p 1920x1080p 1920x1080i 1920x1200p 2048x1080p 2560x1080p 2560x1440p 2560x1600p 3440x1440p 3840x2400p	VXX: *****=1024:0768:p VXX: *****=1280:0720:p VXX: *****=1280:0800:p VXX: *****=1280:1024:p VXX: *****=1366:0768:p VXX: *****=1400:1050:p VXX: *****=1440:0900:p VXX: *****=1600:0900:p VXX: *****=1600:1200:p VXX: *****=1680:1050:p VXX: *****=1920:1080:p VXX: *****=1920:1080:i VXX: *****=1920:1200:p VXX: *****=2048:1080:p VXX: *****=2560:1080:p VXX: *****=2560:1440:p VXX: *****=2560:1600:p VXX: *****=3440:1440:p VXX: *****=3840:2400:p		*****=1024:0768:p *****=1280:0720:p *****=1280:0800:p *****=1280:1024:p *****=1366:0768:p *****=1400:1050:p *****=1440:0900:p *****=1600:0900:p *****=1600:1200:p *****=1680:1050:p *****=1920:1080:p *****=1920:1080:i *****=1920:1200:p *****=2048:1080:p *****=2560:1080:p *****=2560:1440:p *****=2560:1600:p *****=3440:1440:p *****=3840:2400:p		✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	HDMI IN-HDMI* EDID VERTICAL SCAN FREQUENCY	HDMI1 HDMI2		VXX: EDVI3=***** VXX: EDVI6=*****	QVX: EDVI3 QVX: EDVI6	EDVI3=***** EDVI6=*****		✓ ✓
		* PARAMETER	240Hz 120Hz 60Hz 50Hz 48Hz 30Hz 25Hz 24Hz	VXX: *****=+24000 VXX: *****=+12000 VXX: *****=+06000 VXX: *****=+05000 VXX: *****=+04800 VXX: *****=+03000 VXX: *****=+02500 VXX: *****=+02400		*****=+24000 *****=+12000 *****=+06000 *****=+05000 *****=+04800 *****=+03000 *****=+02500 *****=+02400		✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	HDMI IN-HDMI* EDID RESOLUTION / VERTICAL SCAN FREQUENCY	HDMI1 HDMI2		VXX: EDHS1=*****:*.***** VXX: EDHS2=*****:*.*****	QVX: EDHS1 QVX: EDHS2	EDHS1=*****:*.***** EDHS2=*****:*.*****		✓ ✓
		* PARAMETER1	1024x768 1280x720 1280x800 1280x1024 1366x768 1400x1050 1440x900 1600x900 1600x1200 1680x1050 1920x1080 1920x1200 2048x1080 2560x1080 2560x1440 2560x1600 3440x1440 3840x2400	VXX: *****=1024:0768:*.***** VXX: *****=1280:0720:*.***** VXX: *****=1280:0800:*.***** VXX: *****=1280:1024:*.***** VXX: *****=1366:0768:*.***** VXX: *****=1400:1050:*.***** VXX: *****=1440:0900:*.***** VXX: *****=1600:0900:*.***** VXX: *****=1600:1200:*.***** VXX: *****=1680:1050:*.***** VXX: *****=1920:1080:*.***** VXX: *****=1920:1200:*.***** VXX: *****=2048:1080:*.***** VXX: *****=2560:1080:*.***** VXX: *****=2560:1440:*.***** VXX: *****=2560:1600:*.***** VXX: *****=3440:1440:*.***** VXX: *****=3840:2400:*.*****		*****=1024:0768:*.***** *****=1280:0720:*.***** *****=1280:0800:*.***** *****=1280:1024:*.***** *****=1366:0768:*.***** *****=1400:1050:*.***** *****=1440:0900:*.***** *****=1600:0900:*.***** *****=1600:1200:*.***** *****=1680:1050:*.***** *****=1920:1080:*.***** *****=1920:1200:*.***** *****=2048:1080:*.***** *****=2560:1080:*.***** *****=2560:1440:*.***** *****=2560:1600:*.***** *****=3440:1440:*.***** *****=3840:2400:*.*****		✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
		* PARAMETER2	Progressive Interlace	VXX: *****:*.*****:p:***** VXX: *****:*.*****:j:*****		*****:*.*****:p:***** *****:*.*****:j:*****		✓ ✓
		* PARAMETER3	240Hz 120Hz 60Hz 50Hz 48Hz 30Hz 25Hz 24Hz	VXX: *****:*.*****:*.24000 VXX: *****:*.*****:*.12000 VXX: *****:*.*****:*.06000 VXX: *****:*.*****:*.05000 VXX: *****:*.*****:*.04800 VXX: *****:*.*****:*.03000 VXX: *****:*.*****:*.02500 VXX: *****:*.*****:*.02400		*****:*.*****:*.24000 *****:*.*****:*.12000 *****:*.*****:*.06000 *****:*.*****:*.05000 *****:*.*****:*.04800 *****:*.*****:*.03000 *****:*.*****:*.02500 *****:*.*****:*.02400		✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	HDMI IN-HDMI* EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	HDMI1 HDMI2		VXX: ESLS1=*****:*.***** VXX: ESLS2=*****:*.*****	QVX: ESLS1 QVX: ESLS2	ESLS1=*****:*.***** ESLS2=*****:*.*****		✓ ✓
		* PARAMETER1	1024x768 1280x720 1280x800 1280x1024 1366x768 1400x1050 1440x900 1600x900 1600x1200 1680x1050 1920x1080 1920x1200 2048x1080 2560x1080 2560x1440 2560x1600 3440x1440 3840x2400	VXX: *****=1024:0768:*.***** VXX: *****=1280:0720:*.***** VXX: *****=1280:0800:*.***** VXX: *****=1280:1024:*.***** VXX: *****=1366:0768:*.***** VXX: *****=1400:1050:*.***** VXX: *****=1440:0900:*.***** VXX: *****=1600:0900:*.***** VXX: *****=1600:1200:*.***** VXX: *****=1680:1050:*.***** VXX: *****=1920:1080:*.***** VXX: *****=1920:1200:*.***** VXX: *****=2048:1080:*.***** VXX: *****=2560:1080:*.***** VXX: *****=2560:1440:*.***** VXX: *****=2560:1600:*.***** VXX: *****=3440:1440:*.***** VXX: *****=3840:2400:*.*****		*****=1024:0768:*.***** *****=1280:0720:*.***** *****=1280:0800:*.***** *****=1280:1024:*.***** *****=1366:0768:*.***** *****=1400:1050:*.***** *****=1440:0900:*.***** *****=1600:0900:*.***** *****=1600:1200:*.***** *****=1680:1050:*.***** *****=1920:1080:*.***** *****=1920:1200:*.***** *****=2048:1080:*.***** *****=2560:1080:*.***** *****=2560:1440:*.***** *****=2560:1600:*.***** *****=3440:1440:*.***** *****=3840:2400:*.*****		✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
		* PARAMETER2	Progressive Interlace	VXX: *****:*.*****:p:***** VXX: *****:*.*****:j:*****		*****:*.*****:p:***** *****:*.*****:j:*****		✓ ✓
		* PARAMETER3	240Hz 120Hz 60Hz 50Hz 48Hz 30Hz 25Hz 24Hz	VXX: *****:*.*****:*.24000 VXX: *****:*.*****:*.12000 VXX: *****:*.*****:*.06000 VXX: *****:*.*****:*.05000 VXX: *****:*.*****:*.04800 VXX: *****:*.*****:*.03000 VXX: *****:*.*****:*.02500 VXX: *****:*.*****:*.02400		*****:*.*****:*.24000 *****:*.*****:*.12000 *****:*.*****:*.06000 *****:*.*****:*.05000 *****:*.*****:*.04800 *****:*.*****:*.03000 *****:*.*****:*.02500 *****:*.*****:*.02400		✓ ✓ ✓ ✓ ✓ ✓ ✓ ✓
	DisplayPort IN-SIGNAL LEVEL	AUTO 0-1023 64-940		VXX: DPLI1=+00000 VXX: DPLI1=+00001 VXX: DPLI1=+00002	QVX: DPLI1	DPLI1=+00000 DPLI1=+00001 DPLI1=+00002		✓ ✓ ✓
	DisplayPort IN -AUTO GAMMA SELECT	DISABLE ENABLE		VXX: DAGI1=+00000 VXX: DAGI1=+00001	QVX: DAGI1	DAGI1=+00000 DAGI1=+00001		✓ ✓
	DisplayPort IN - AUTO COLOR SPACE SELECT	DISABLE ENABLE		VXX: DACI1=+00000 VXX: DACI1=+00001	QVX: DACI1	DACI1=+00000 DACI1=+00001		✓ ✓
	DisplayPort IN-EDID SELECT	4K/60p 4K/30p		VXX: DESI1=+00000 VXX: DESI1=+00001	QVX: DESI1	DESI1=+00000 DESI1=+00001		✓ ✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		REZ12 SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	REZ12 /10/80 FEZ120C /100C/080C	
DisplayPort IN-EDID MODE	DisplayPort IN-EDID MODE	2K		VXX: DESI1=+00002		DESI1=+00002		✓
		4K/60p/HDR		VXX: DESI1=+00010		DESI1=+00010		✓
	DisplayPort IN-EDID RESOLUTION	DEFAULT USER		VXX: EDMIS=+00000	QVX: EDMIS	EDMIS=+00000		✓
		1024x768p		VXX: EDRS8=1024:0768:p	QVX: EDRS8	EDRS8=1024:0768:p		✓
		1280x720p		VXX: EDRS8=1280:0720:p		EDRS8=1280:0720:p		✓
		1280x800p		VXX: EDRS8=1280:0800:p		EDRS8=1280:0800:p		✓
		1400x1050p		VXX: EDRS8=1400:1050:p		EDRS8=1400:1050:p		✓
		1600x900p		VXX: EDRS8=1600:0900:p		EDRS8=1600:0900:p		✓
		1600x1200p		VXX: EDRS8=1600:1200:p		EDRS8=1600:1200:p		✓
		1920x1080p		VXX: EDRS8=1920:1080:p		EDRS8=1920:1080:p		✓
		1920x1200p		VXX: EDRS8=1920:1200:p		EDRS8=1920:1200:p		✓
		2048x1080p		VXX: EDRS8=2048:1080:p		EDRS8=2048:1080:p		✓
	2560x1080p		VXX: EDRS8=2560:1080:p		EDRS8=2560:1080:p		✓	
	2560x1440p		VXX: EDRS8=2560:1440:p		EDRS8=2560:1440:p		✓	
	2560x1600p		VXX: EDRS8=2560:1600:p		EDRS8=2560:1600:p		✓	
	3440x1440p		VXX: EDRS8=3440:1440:p		EDRS8=3440:1440:p		✓	
	3840x2400p		VXX: EDRS8=3840:2400:p		EDRS8=3840:2400:p		✓	
	DisplayPort IN-EDID VERTICAL SCAN FREQUENCY	240Hz		VXX: EDVI8=+24000	QVX: EDVI8	EDVI8=+24000		✓
		120Hz		VXX: EDVI8=+12000		EDVI8=+12000		✓
		60Hz		VXX: EDVI8=+06000		EDVI8=+06000		✓
		50Hz		VXX: EDVI8=+05000		EDVI8=+05000		✓
48Hz			VXX: EDVI8=+04800		EDVI8=+04800		✓	
30Hz			VXX: EDVI8=+03000		EDVI8=+03000		✓	
25Hz			VXX: EDVI8=+02500		EDVI8=+02500		✓	
24Hz			VXX: EDVI8=+02400		EDVI8=+02400		✓	
DisplayPort IN-EDID RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX: EDPS1=*****:*.*****	QVX: EDPS1	EDPS1=*****:*.*****		✓	
	* PARAMETER1	1024x768	VXX: EDPS1=1024:0768:*.*****		EDPS1=1024:0768:*.*****		✓	
		1280x720	VXX: EDPS1=1280:0720:*.*****		EDPS1=1280:0720:*.*****		✓	
		1280x800	VXX: EDPS1=1280:0800:*.*****		EDPS1=1280:0800:*.*****		✓	
		1400x1050	VXX: EDPS1=1400:1050:*.*****		EDPS1=1400:1050:*.*****		✓	
		1600x900	VXX: EDPS1=1600:0900:*.*****		EDPS1=1600:0900:*.*****		✓	
		1600x1200	VXX: EDPS1=1600:1200:*.*****		EDPS1=1600:1200:*.*****		✓	
		1920x1080	VXX: EDPS1=1920:1080:*.*****		EDPS1=1920:1080:*.*****		✓	
		1920x1200	VXX: EDPS1=1920:1200:*.*****		EDPS1=1920:1200:*.*****		✓	
		2048x1080	VXX: EDPS1=2048:1080:*.*****		EDPS1=2048:1080:*.*****		✓	
		2560x1080	VXX: EDPS1=2560:1080:*.*****		EDPS1=2560:1080:*.*****		✓	
		2560x1440	VXX: EDPS1=2560:1440:*.*****		EDPS1=2560:1440:*.*****		✓	
		2560x1600	VXX: EDPS1=2560:1600:*.*****		EDPS1=2560:1600:*.*****		✓	
		3440x1440	VXX: EDPS1=3440:1440:*.*****		EDPS1=3440:1440:*.*****		✓	
		3840x2400	VXX: EDPS1=3840:2400:*.*****		EDPS1=3840:2400:*.*****		✓	
	* PARAMETER2	Progressive	VXX: EDPS1=*****:p:*****		EDPS1=*****:p:*****		✓	
	* PARAMETER3	240Hz	VXX: EDPS1=*****:*.24000		EDPS1=*****:*.24000		✓	
		120Hz	VXX: EDPS1=*****:*.12000		EDPS1=*****:*.12000		✓	
		60Hz	VXX: EDPS1=*****:*.06000		EDPS1=*****:*.06000		✓	
		50Hz	VXX: EDPS1=*****:*.05000		EDPS1=*****:*.05000		✓	
		48Hz	VXX: EDPS1=*****:*.04800		EDPS1=*****:*.04800		✓	
	30Hz	VXX: EDPS1=*****:*.03000		EDPS1=*****:*.03000		✓		
	25Hz	VXX: EDPS1=*****:*.02500		EDPS1=*****:*.02500		✓		
	24Hz	VXX: EDPS1=*****:*.02400		EDPS1=*****:*.02400		✓		
DisplayPort IN-EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY	* PARAMETER		VXX: ESHP1=*****:*.*****	QVX: ESHP1	ESHP1=*****:*.*****		✓	
	* PARAMETER1	1024x768	VXX: ESHP1=1024:0768:*.*****		ESHP1=1024:0768:*.*****		✓	
		1280x720	VXX: ESHP1=1280:0720:*.*****		ESHP1=1280:0720:*.*****		✓	
		1280x800	VXX: ESHP1=1280:0800:*.*****		ESHP1=1280:0800:*.*****		✓	
		1400x1050	VXX: ESHP1=1400:1050:*.*****		ESHP1=1400:1050:*.*****		✓	
		1600x900	VXX: ESHP1=1600:0900:*.*****		ESHP1=1600:0900:*.*****		✓	
		1600x1200	VXX: ESHP1=1600:1200:*.*****		ESHP1=1600:1200:*.*****		✓	
		1920x1080	VXX: ESHP1=1920:1080:*.*****		ESHP1=1920:1080:*.*****		✓	
		1920x1200	VXX: ESHP1=1920:1200:*.*****		ESHP1=1920:1200:*.*****		✓	
		2048x1080	VXX: ESHP1=2048:1080:*.*****		ESHP1=2048:1080:*.*****		✓	
		2560x1080	VXX: ESHP1=2560:1080:*.*****		ESHP1=2560:1080:*.*****		✓	
		2560x1440	VXX: ESHP1=2560:1440:*.*****		ESHP1=2560:1440:*.*****		✓	
		2560x1600	VXX: ESHP1=2560:1600:*.*****		ESHP1=2560:1600:*.*****		✓	
		3440x1440	VXX: ESHP1=3440:1440:*.*****		ESHP1=3440:1440:*.*****		✓	
		3840x2400	VXX: ESHP1=3840:2400:*.*****		ESHP1=3840:2400:*.*****		✓	
	* PARAMETER2	Progressive	VXX: ESHP1=*****:p:*****		ESHP1=*****:p:*****		✓	
	* PARAMETER3	240Hz	VXX: ESHP1=*****:*.24000		ESHP1=*****:*.24000		✓	
		120Hz	VXX: ESHP1=*****:*.12000		ESHP1=*****:*.12000		✓	
		60Hz	VXX: ESHP1=*****:*.06000		ESHP1=*****:*.06000		✓	
		50Hz	VXX: ESHP1=*****:*.05000		ESHP1=*****:*.05000		✓	
		48Hz	VXX: ESHP1=*****:*.04800		ESHP1=*****:*.04800		✓	
	30Hz	VXX: ESHP1=*****:*.03000		ESHP1=*****:*.03000		✓		
	25Hz	VXX: ESHP1=*****:*.02500		ESHP1=*****:*.02500		✓		
	24Hz	VXX: ESHP1=*****:*.02400		ESHP1=*****:*.02400		✓		
SLOT : SDI RESOLUTION	* PARAMETER		VXX: *****=VXX: *****+*****	QVX: *****=QVX: *****	*****=*****+*****		✓	
	* PARAMETER1, 2	SDI1	VXX: SLSS1=VXX: SRSI1=+*****		SLSS1=SRSI1=+*****		✓	
		AUTO	VXX: *****=VXX: *****+00000		*****=*****+00000		✓	
	* PARAMETER3	1920x1080i	VXX: *****=VXX: *****+00005		*****=*****+00005		✓	
		1920x1080p	VXX: *****=VXX: *****+00006		*****=*****+00006		✓	
		2048x1080p	VXX: *****=VXX: *****+00009		*****=*****+00009		✓	
		3840x2160p	VXX: *****=VXX: *****+00011		*****=*****+00011		✓	
		4096x2160p	VXX: *****=VXX: *****+00013		*****=*****+00013		✓	
	SLOT - SDI IN - AUTO GAMMA SELECT	DISABLE		VXX: SLSS1=VXX: SAGI1=+00000	QVX: SLSS1=SAGI1	SLSS1=SAGI1=+00000		✓
		ENABLE		VXX: SLSS1=VXX: SAGI1=+00001		SLSS1=SAGI1=+00001		✓
	SLOT - SDI IN - AUTO COLOR SPACE SELECT	DISABLE		VXX: SLSS1=VXX: SACI1=+00000	QVX: SLSS1=SACI1	SLSS1=SACI1=+00000		✓
		ENABLE		VXX: SLSS1=VXX: SACI1=+00001		SLSS1=SACI1=+00001		✓
	SLOT : SDI : SDI 4K DIVISION	* PARAMETER		VXX: *****=VXX: *****+*****	QVX: *****=QVX: *****	*****=*****+*****		✓
	* PARAMETER1, 2 (ET-MDN12G10)	SINGLE LINK(SLOT1:SDI1)		VXX: SLSS1=VXX: SKSI1=+*****		SLSS1=SKSI1=+*****		✓
		AUTO		VXX: *****=VXX: *****+00000		*****=*****+00000		✓
	* PARAMETER3	SQUARE INTERLEAVE		VXX: *****=VXX: *****+00001		*****=*****+00001		✓
				VXX: *****=VXX: *****+00002		*****=*****+00002		✓
	SLOT : SDI : SDI SYSTEM SELECTOR	* PARAMETER		VXX: *****=VXX: *****+*****	QVX: *****=QVX: *****+*****	*****=*****+*****		✓
	* PARAMETER1, 2	SDI1		VXX: SLSS1=VXX: SYSS1=1:1:*****	QVX: SLSS1=VXX: SYSS1=1:1	SLSS1=SYSS1=1:1:*****		✓
		AUTO		VXX: *****=VXX: SYSS1=*.*****:00000		*****=SYSS1=*.*****:00000		✓
	* PARAMETER3	RGB		VXX: *****=VXX: SYSS1=*.*****:00001		*****=SYSS1=*.*****:00001		✓
	YPbPr4:4:4		VXX: *****=VXX: SYSS1=*.*****:00002		*****=SYSS1=*.*****:00002		✓	
	YPbPr4:2:2		VXX: *****=VXX: SYSS1=*.*****:00003		*****=SYSS1=*.*****:00003		✓	
SLOT : SDI : BIT DEPTH	* PARAMETER		VXX: *****=VXX: *****+*****	QVX: *****=QVX: *****	*****=*****+*****		✓	
* PARAMETER1, 2	SDI1		VXX: SLSS1=VXX: SBTI1=+*****		SLSS1=SBTI1=+*****		✓	
	AUTO		VXX: *****=VXX: *****+00000		*****=*****+00000		✓	
* PARAMETER3	12-bit		VXX: *****=VXX: *****+00001		*****=*****+00001		✓	
	10-bit		VXX: *****=VXX: *****+00002		*****=*****+00002		✓	
SLOT : SDI : SIGNAL LEVEL	* PARAMETER		VXX: *****=VXX: *****+*****	QVX: *****=QVX: *****	*****=*****+*****		✓	
* PARAMETER1, 2	SDI1		VXX: SLSS1=VXX: SSLI1=+*****		SLSS1=SSLI1=+*****		✓	
	64-940		VXX: *****=VXX: *****+00000		*****=*****+00000		✓	
* PARAMETER3	4-1019		VXX: *****=VXX: *****+00001		*****=*****+00001		✓	
	AUTO		VXX: *****=VXX: *****+00002		*****=*****+00002		✓	
SLOT : DIGITAL LINK : SIGNAL LEVEL	0-1023		VXX: SLSS1=VXX: DKLI1=+00000	QVX: SLSS1=VXX: DKLI1	SLSS1=DKLI1=+00000		✓	
	64-940		VXX: SLSS1=VXX: DKLI1=+00001		SLSS1=DKLI1=+00001		✓	
	AUTO		VXX: SLSS1=VXX: DKLI1=+00002		SLSS1=DKLI1=+00002		✓	
SLOT : DIGITAL LINK : AUTO GAMMA SELECT	DISABLE		VXX: SLSS1=VXX: LAGI1=+00000	QVX: SLSS1=VXX: LAGI1	SLSS1=LAGI1=+00000		✓	
	ENABLE		VXX: SLSS1=VXX: LAGI1=+00001		SLSS1=LAGI1=+00001		✓	
SLOT : DIGITAL LINK : AUTO COLOR SPACE SELECT	DISABLE		VXX: SLSS1=VXX: LACI1=+00000	QVX: SLSS1=VXX: LACI1	SLSS1=LACI1=+00000		✓	
	ENABLE		VXX: SLSS1=VXX: LACI1=+00001		SLSS1=LACI1=+00001		✓	
SLOT : DIGITAL LINK : EDID SELECT	4K/60p/SDR		VXX: SLSS1=VXX: LESI1=+00000	QVX: SLSS1=VXX: LESI1	SLSS1=LESI1=+00000		✓	
	4K/30p		VXX: SLSS1=VXX: LESI1=+00001		SLSS1=LESI1=+00001		✓	
	2K		VXX: SLSS1=VXX: LESI1=+00002		SLSS1=LESI1=+00002		✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		REZ12 SERIES	
				COMMANDS/CALL BACK	COMMANDS	CALL BACK			
DISPLAY OPTION	4K/30p/HDR			VXX:SLSS1=VXX:LESI1=+00011		SLSS1=LESI1=+00011		✓	
	SLOT : DIGITAL LINK : EDID MODE	DEFAULT		VXX:SLSS1=VXX:EDMI4=+00000	QVX:SLSS1=QVX:EDMI4	SLSS1=EDMI4=+00000		✓	
		USER		VXX:SLSS1=VXX:EDMI4=+00010		SLSS1=EDMI4=+00010		✓	
	SLOT : DIGITAL LINK : EDID RESOLUTION			VXX:SLSS1=VXX:EDRS4=1024:0768:*	QVX:SLSS1=QVX:EDRS4	SLSS1=EDRS4=1024:0768:*		✓	
			1024x768	VXX:SLSS1=VXX:EDRS4=1280:0720:*		SLSS1=EDRS4=1280:0720:*		✓	
			1280x800	VXX:SLSS1=VXX:EDRS4=1280:0800:*		SLSS1=EDRS4=1280:0800:*		✓	
			1280x1024	VXX:SLSS1=VXX:EDRS4=1280:1024:*		SLSS1=EDRS4=1280:1024:*		✓	
			1366x768	VXX:SLSS1=VXX:EDRS4=1366:0768:*		SLSS1=EDRS4=1366:0768:*		✓	
			1400x1050	VXX:SLSS1=VXX:EDRS4=1400:1050:*		SLSS1=EDRS4=1400:1050:*		✓	
			1440x900	VXX:SLSS1=VXX:EDRS4=1440:0900:*		SLSS1=EDRS4=1440:0900:*		✓	
			1600x900	VXX:SLSS1=VXX:EDRS4=1600:0900:*		SLSS1=EDRS4=1600:0900:*		✓	
			1600x1200	VXX:SLSS1=VXX:EDRS4=1600:1200:*		SLSS1=EDRS4=1600:1200:*		✓	
			1680x1050	VXX:SLSS1=VXX:EDRS4=1680:1050:*		SLSS1=EDRS4=1680:1050:*		✓	
			1920x1080	VXX:SLSS1=VXX:EDRS4=1920:1080:*		SLSS1=EDRS4=1920:1080:*		✓	
			1920x1200	VXX:SLSS1=VXX:EDRS4=1920:1200:*		SLSS1=EDRS4=1920:1200:*		✓	
			2048x1080	VXX:SLSS1=VXX:EDRS4=2048:1080:*		SLSS1=EDRS4=2048:1080:*		✓	
			2560x1080	VXX:SLSS1=VXX:EDRS4=2560:1080:*		SLSS1=EDRS4=2560:1080:*		✓	
			2560x1440	VXX:SLSS1=VXX:EDRS4=2560:1440:*		SLSS1=EDRS4=2560:1440:*		✓	
			2560x1600	VXX:SLSS1=VXX:EDRS4=2560:1600:*		SLSS1=EDRS4=2560:1600:*		✓	
			3840x2400	VXX:SLSS1=VXX:EDRS4=3840:2400:*		SLSS1=EDRS4=3840:2400:*		✓	
			* PARAMETER1	Progressive Interlace	VXX:SLSS1=VXX:EDRS4=*****:p VXX:SLSS1=VXX:EDRS4=*****:i		SLSS1=EDRS4=*****:p SLSS1=EDRS4=*****:i		✓
	SLOT : DIGITAL LINK : EDID VERTICAL SCAN FREQUENCY		* PARAMETER		VXX:SLSS1=VXX:EDVI4=+*****	QVX:SLSS1=QVX:EDVI4	SLSS1=EDVI4=+*****		✓
			* PARAMETER1	120Hz	VXX:SLSS1=VXX:EDVI4=+12000		SLSS1=EDVI4=+12000		✓
				60Hz	VXX:SLSS1=VXX:EDVI4=+06000		SLSS1=EDVI4=+06000		✓
				50Hz	VXX:SLSS1=VXX:EDVI4=+05000		SLSS1=EDVI4=+05000		✓
				48Hz	VXX:SLSS1=VXX:EDVI4=+04800		SLSS1=EDVI4=+04800		✓
				30Hz	VXX:SLSS1=VXX:EDVI4=+03000		SLSS1=EDVI4=+03000		✓
				25Hz	VXX:SLSS1=VXX:EDVI4=+02500		SLSS1=EDVI4=+02500		✓
				24Hz	VXX:SLSS1=VXX:EDVI4=+02400		SLSS1=EDVI4=+02400		✓
	SLOT : DIGITAL LINK : EDID RESOLUTION / VERTICAL SCAN FREQUENCY		* PARAMETER		VXX:SLSS1=VXX:EDLS1=1024:0768:*:*****	QVX:SLSS1=QVX:EDLS1	SLSS1=EDLS1=1024:0768:*:*****		✓
				1280x720	VXX:SLSS1=VXX:EDLS1=1280:0720:*:*****		SLSS1=EDLS1=1280:0720:*:*****		✓
				1280x800	VXX:SLSS1=VXX:EDLS1=1280:0800:*:*****		SLSS1=EDLS1=1280:0800:*:*****		✓
				1280x1024	VXX:SLSS1=VXX:EDLS1=1280:1024:*:*****		SLSS1=EDLS1=1280:1024:*:*****		✓
				1366x768	VXX:SLSS1=VXX:EDLS1=1366:0768:*:*****		SLSS1=EDLS1=1366:0768:*:*****		✓
				1400x1050	VXX:SLSS1=VXX:EDLS1=1400:1050:*:*****		SLSS1=EDLS1=1400:1050:*:*****		✓
				1440x900	VXX:SLSS1=VXX:EDLS1=1440:0900:*:*****		SLSS1=EDLS1=1440:0900:*:*****		✓
				1600x900	VXX:SLSS1=VXX:EDLS1=1600:0900:*:*****		SLSS1=EDLS1=1600:0900:*:*****		✓
				1600x1200	VXX:SLSS1=VXX:EDLS1=1600:1200:*:*****		SLSS1=EDLS1=1600:1200:*:*****		✓
				1680x1050	VXX:SLSS1=VXX:EDLS1=1680:1050:*:*****		SLSS1=EDLS1=1680:1050:*:*****		✓
				1920x1080	VXX:SLSS1=VXX:EDLS1=1920:1080:*:*****		SLSS1=EDLS1=1920:1080:*:*****		✓
				1920x1200	VXX:SLSS1=VXX:EDLS1=1920:1200:*:*****		SLSS1=EDLS1=1920:1200:*:*****		✓
				2048x1080	VXX:SLSS1=VXX:EDLS1=2048:1080:*:*****		SLSS1=EDLS1=2048:1080:*:*****		✓
				2560x1080	VXX:SLSS1=VXX:EDLS1=2560:1080:*:*****		SLSS1=EDLS1=2560:1080:*:*****		✓
				2560x1440	VXX:SLSS1=VXX:EDLS1=2560:1440:*:*****		SLSS1=EDLS1=2560:1440:*:*****		✓
				2560x1600	VXX:SLSS1=VXX:EDLS1=2560:1600:*:*****		SLSS1=EDLS1=2560:1600:*:*****		✓
			3840x2400	VXX:SLSS1=VXX:EDLS1=3840:2400:*:*****		SLSS1=EDLS1=3840:2400:*:*****		✓	
		* PARAMETER1	Progressive Interlace	VXX:SLSS1=VXX:EDLS1=*****:p VXX:SLSS1=VXX:EDLS1=*****:i		SLSS1=EDLS1=*****:p SLSS1=EDLS1=*****:i		✓	
		* PARAMETER2	120Hz	VXX:SLSS1=VXX:EDLS1=*****:*:12000		SLSS1=EDLS1=*****:*:12000		✓	
			60Hz	VXX:SLSS1=VXX:EDLS1=*****:*:06000		SLSS1=EDLS1=*****:*:06000		✓	
			50Hz	VXX:SLSS1=VXX:EDLS1=*****:*:05000		SLSS1=EDLS1=*****:*:05000		✓	
			48Hz	VXX:SLSS1=VXX:EDLS1=*****:*:04800		SLSS1=EDLS1=*****:*:04800		✓	
			30Hz	VXX:SLSS1=VXX:EDLS1=*****:*:03000		SLSS1=EDLS1=*****:*:03000		✓	
			25Hz	VXX:SLSS1=VXX:EDLS1=*****:*:02500		SLSS1=EDLS1=*****:*:02500		✓	
			24Hz	VXX:SLSS1=VXX:EDLS1=*****:*:02400		SLSS1=EDLS1=*****:*:02400		✓	
SLOT : DIGITAL LINK : EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY		* PARAMETER			QVX:SLSS1=QVX:ESLS1	SLSS1=ESLS1=1024:0768:*:*****		✓	
			1280x720			SLSS1=ESLS1=1280:0720:*:*****		✓	
			1280x800			SLSS1=ESLS1=1280:0800:*:*****		✓	
			1280x1024			SLSS1=ESLS1=1280:1024:*:*****		✓	
			1366x768			SLSS1=ESLS1=1366:0768:*:*****		✓	
			1400x1050			SLSS1=ESLS1=1400:1050:*:*****		✓	
			1440x900			SLSS1=ESLS1=1440:0900:*:*****		✓	
			1600x900			SLSS1=ESLS1=1600:0900:*:*****		✓	
			1600x1200			SLSS1=ESLS1=1600:1200:*:*****		✓	
			1680x1050			SLSS1=ESLS1=1680:1050:*:*****		✓	
			1920x1080			SLSS1=ESLS1=1920:1080:*:*****		✓	
			1920x1200			SLSS1=ESLS1=1920:1200:*:*****		✓	
			2048x1080			SLSS1=ESLS1=2048:1080:*:*****		✓	
			2560x1440			SLSS1=ESLS1=2560:1440:*:*****		✓	
			2560x1080			SLSS1=ESLS1=2560:1080:*:*****		✓	
			2560x1600			SLSS1=ESLS1=2560:1600:*:*****		✓	
			3840x2400			SLSS1=ESLS1=3840:2400:*:*****		✓	
		* PARAMETER1	Progressive Interlace			SLSS1=ESLS1=*****:p SLSS1=ESLS1=*****:i		✓	
		* PARAMETER2	120Hz			SLSS1=ESLS1=*****:*:12000		✓	
			60Hz			SLSS1=ESLS1=*****:*:06000		✓	
			50Hz			SLSS1=ESLS1=*****:*:05000		✓	
			48Hz			SLSS1=ESLS1=*****:*:04800		✓	
			30Hz			SLSS1=ESLS1=*****:*:03000		✓	
			25Hz			SLSS1=ESLS1=*****:*:02500		✓	
			24Hz			SLSS1=ESLS1=*****:*:02400		✓	
SLOT : DIGITAL LINK : DIGITAL LINK OUT	DISABLE			VXX:SLSS1=VXX:DLOI1=+00000	QVX:SLSS1=QVX:DLOI1	SLSS1=DLOI1=+00000		✓	
	ENABLE			VXX:SLSS1=VXX:DLOI1=+00001		SLSS1=DLOI1=+00001		✓	
SLOT : 12G SDI OPT : RESOLUTION		* PARAMETER		VXX:*****=VXX:*****=*****	QVX:*****=QVX:*****	*****=*****=+*****		✓	
		* PARAMETER1, 2	12G SDI OPT1	VXX:SLSS1=VXX:OREI1=*****		SLSS1=OREI1=+*****		✓	
			12G SDI OPT2	VXX:SLSS1=VXX:OREI2=*****		SLSS1=OREI2=+*****		✓	
		* PARAMETER3	AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000		✓	
			1280x720p	VXX:*****=VXX:*****=+00003		*****=*****=+00003		✓	
			1920x1080i	VXX:*****=VXX:*****=+00005		*****=*****=+00005		✓	
			1920x1080p	VXX:*****=VXX:*****=+00006		*****=*****=+00006		✓	
			1920x1080sF	VXX:*****=VXX:*****=+00007		*****=*****=+00007		✓	
			2048x1080p	VXX:*****=VXX:*****=+00009		*****=*****=+00009		✓	
			3840x2160p	VXX:*****=VXX:*****=+00011		*****=*****=+00011		✓	
			4096x2160p	VXX:*****=VXX:*****=+00013		*****=*****=+00013		✓	
SLOT : 12G SDI OPT : SYSTEM SELECTOR		* PARAMETER		VXX:*****=VXX:*****=*****	QVX:*****=QVX:*****	*****=*****=+*****		✓	
		* PARAMETER1, 2	12G SDI OPT1	VXX:SLSS1=VXX:OSYI1=*****		SLSS1=OSYI1=+*****		✓	
			12G SDI OPT2	VXX:SLSS1=VXX:OSYI2=*****		SLSS1=OSYI2=+*****		✓	
		* PARAMETER3	AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000		✓	
			RGB	VXX:*****=VXX:*****=+00001		*****=*****=+00001		✓	
			YPbPr 4:4:4	VXX:*****=VXX:*****=+00002		*****=*****=+00002		✓	
			YPbPr 4:2:2	VXX:*****=VXX:*****=+00003		*****=*****=+00003		✓	
SLOT : 12G SDI OPT : BIT DEPTH		* PARAMETER		VXX:*****=VXX:*****=*****	QVX:*****=QVX:*****	*****=*****=+*****		✓	
		* PARAMETER1, 2	12G SDI OPT1	VXX:SLSS1=VXX:OBTI1=*****		SLSS1=OBTI1=+*****		✓	
			12G SDI OPT2	VXX:SLSS1=VXX:OBTI2=*****		SLSS1=OBTI2=+*****		✓	
		* PARAMETER3	AUTO	VXX:*****=VXX:*****=+00000		*****=*****=+00000		✓	
			12-bit	VXX:*****=VXX:*****=+00001		*****=*****=+00001		✓	
			10-bit	VXX:*****=VXX:*****=+00002		*****=*****=+00002		✓	
SLOT : 12G SDI OPT : SIGNAL LEVEL		* PARAMETER		VXX:*****=VXX:*****=*****	QVX:*****=QVX:*****	*****=*****=+*****		✓	
		* PARAMETER1, 2	12G SDI OPT1	VXX:SLSS1=VXX:OSLI1=*****		SLSS1=OSLI1=+*****		✓	
			12G SDI OPT2	VXX:SLSS1=VXX:OSLI2=*****		SLSS1=OSLI2=+*****		✓	
		* PARAMETER3	64-940	VXX:*****=VXX:*****=+00000		*****=*****=+00000		✓	
			4-1019	VXX:*****=VXX:*****=+00001		*****=*****=+00001		✓	
			AUTO	VXX:*****=VXX:*****=+00002		*****=*****=+00002		✓	
SLOT : 12G SDI OPT : AUTO GAMMA SELECT	DISABLE			VXX:SLSS1=VXX:OAGI1=+00000	QVX:SLSS1=OAGI1	SLSS1=OAGI1=+00000		✓	
	ENABLE			VXX:SLSS1=VXX:OAGI1=+00001		SLSS1=OAGI1=+00001		✓	
SLOT : 12G SDI OPT : AUTO COLOR SPACE	DISABLE			VXX:SLSS1=VXX:OACI1=+00000	QVX:SLSS1=OACI1	SLSS1=OACI1=+00000		✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		REZ12 SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK		
	SELECT	ENABLE		VXX:SLSS1=VXX:OACI1=+00001		SLSS1=OACI1=+00001		✓
	SLOT : 12G SDI OPT : SDI OPT OUT	* PARAMETER		VXX:OOMS1=*:*:*****	QVX:OOMS1=*:*	OOMS1=*:*:*****		✓
		* PARAMETER1	SLOT1	VXX:OOMS1=1:*:*****		OOMS1=1:*:*****		✓
			SLOT2	VXX:OOMS1=2:*:*****		OOMS1=2:*:*****		✓
			SFP2	VXX:OOMS1=*:2:*****		OOMS1=*:2:*****		✓
		* PARAMETER3	DISABLE	VXX:OOMS1=*:*:00000		OOMS1=*:*:00000		✓
			ENABLE	VXX:OOMS1=*:*:00001		OOMS1=*:*:00001		✓
	SLOT : PressIT : SIGNAL LEVEL	64-940		VXX:SLSS1=VXX:WLSL1=+00000	QVX:SLSS1=QVX:WLSL1	SLSS1=WLSL1=+00000		✓
		0-1023		VXX:SLSS1=VXX:WLSL1=+00001		SLSS1=WLSL1=+00001		✓
		AUTO		VXX:SLSS1=VXX:WLSL1=+00002		SLSS1=WLSL1=+00002		✓
	SLOT : 3rd Party Board : SIGNAL LEVEL	64-940		VXX:SLSS1=VXX:USLI1=+00000	QVX:SLSS1=QVX:USLI1	SLSS1=USLI1=+00000		✓
		0-1023		VXX:SLSS1=VXX:USLI1=+00001		SLSS1=USLI1=+00001		✓
		AUTO		VXX:SLSS1=VXX:USLI1=+00002		SLSS1=USLI1=+00002		✓
	SLOT : 3rd Party Board : AUTO GAMMA SELECT	DISABLE		VXX:SLSS1=VXX:UAGI1=+00000	QVX:SLSS1=QVX:UAGI1	SLSS1=UAGI1=+00000		✓
		ENABLE		VXX:SLSS1=VXX:UAGI1=+00001		SLSS1=UAGI1=+00001		✓
	SLOT : 3rd Party Board : AUTO COLOR SPACE SELECT	DISABLE		VXX:SLSS1=VXX:UACI1=+00000	QVX:SLSS1=QVX:UACI1	SLSS1=UACI1=+00000		✓
		ENABLE		VXX:SLSS1=VXX:UACI1=+00001		SLSS1=UACI1=+00001		✓
	SLOT : 3rd Party Board : EQUALIZER	0		VXX:SLSS1=VXX:UEQI1=+00000	QVX:SLSS1=QVX:UEQI1	SLSS1=VXX:UEQI1=+00000		✓
		1		VXX:SLSS1=VXX:UEQI1=+00001		SLSS1=VXX:UEQI1=+00001		✓
		2		VXX:SLSS1=VXX:UEQI1=+00002		SLSS1=VXX:UEQI1=+00002		✓
		3		VXX:SLSS1=VXX:UEQI1=+00003		SLSS1=VXX:UEQI1=+00003		✓
		4		VXX:SLSS1=VXX:UEQI1=+00004		SLSS1=VXX:UEQI1=+00004		✓
		5		VXX:SLSS1=VXX:UEQI1=+00005		SLSS1=VXX:UEQI1=+00005		✓
		6		VXX:SLSS1=VXX:UEQI1=+00006		SLSS1=VXX:UEQI1=+00006		✓
		7		VXX:SLSS1=VXX:UEQI1=+00007		SLSS1=VXX:UEQI1=+00007		✓
	SLOT : 3rd Party Board : EDID SELECT	4K/60p/SDR		VXX:SLSS1=VXX:UESI1=+00000	QVX:SLSS1=QVX:UESI1	SLSS1=UESI1=+00000		✓
		4K/30p		VXX:SLSS1=VXX:UESI1=+00001		SLSS1=UESI1=+00001		✓
		2K		VXX:SLSS1=VXX:UESI1=+00002		SLSS1=UESI1=+00002		✓
		4K/60p/HDR		VXX:SLSS1=VXX:UESI1=+00010		SLSS1=UESI1=+00010		✓
	SLOT : 3rd Party Board : EDID MODE	DEFAULT		VXX:SLSS1=VXX:EDMIB=+00000	QVX:SLSS1=QVX:EDMIB	SLSS1=EDMIB=+00000		✓
		USER		VXX:SLSS1=VXX:EDMIB=+00010		SLSS1=EDMIB=+00010		✓
	SLOT : 3rd Party Board : EDID RESOLUTION		1024x768	VXX:SLSS1=VXX:EDRSB=1024:0768:*	QVX:SLSS1=QVX:EDRSB	SLSS1=EDRSB=1024:0768:*		✓
			1280x720	VXX:SLSS1=VXX:EDRSB=1280:0720:*		SLSS1=EDRSB=1280:0720:*		✓
			1280x800	VXX:SLSS1=VXX:EDRSB=1280:0800:*		SLSS1=EDRSB=1280:0800:*		✓
			1280x1024	VXX:SLSS1=VXX:EDRSB=1280:1024:*		SLSS1=EDRSB=1280:1024:*		✓
			1366x768	VXX:SLSS1=VXX:EDRSB=1366:0768:*		SLSS1=EDRSB=1366:0768:*		✓
			1400x1050	VXX:SLSS1=VXX:EDRSB=1400:1050:*		SLSS1=EDRSB=1400:1050:*		✓
			1440x900	VXX:SLSS1=VXX:EDRSB=1440:0900:*		SLSS1=EDRSB=1440:0900:*		✓
			1600x900	VXX:SLSS1=VXX:EDRSB=1600:0900:*		SLSS1=EDRSB=1600:0900:*		✓
			1600x1200	VXX:SLSS1=VXX:EDRSB=1600:1200:*		SLSS1=EDRSB=1600:1200:*		✓
			1680x1050	VXX:SLSS1=VXX:EDRSB=1680:1050:*		SLSS1=EDRSB=1680:1050:*		✓
			1920x1080	VXX:SLSS1=VXX:EDRSB=1920:1080:*		SLSS1=EDRSB=1920:1080:*		✓
			1920x1200	VXX:SLSS1=VXX:EDRSB=1920:1200:*		SLSS1=EDRSB=1920:1200:*		✓
			2048x1080	VXX:SLSS1=VXX:EDRSB=2048:1080:*		SLSS1=EDRSB=2048:1080:*		✓
			2560x1080	VXX:SLSS1=VXX:EDRSB=2560:1080:*		SLSS1=EDRSB=2560:1080:*		✓
			2560x1440	VXX:SLSS1=VXX:EDRSB=2560:1440:*		SLSS1=EDRSB=2560:1440:*		✓
			2560x1600	VXX:SLSS1=VXX:EDRSB=2560:1600:*		SLSS1=EDRSB=2560:1600:*		✓
			3440x1440	VXX:SLSS1=VXX:EDRSB=3440:1440:*		SLSS1=EDRSB=3440:1440:*		✓
			3840x2400	VXX:SLSS1=VXX:EDRSB=3840:2400:*		SLSS1=EDRSB=3840:2400:*		✓
		* PARAMETER1	Progressive Interlace	VXX:SLSS1=VXX:EDRSB=*****:p VXX:SLSS1=VXX:EDRSB=*****:i		SLSS1=EDRSB=*****:p SLSS1=EDRSB=*****:i		✓
	SLOT : 3rd Party Board : EDID VERTICAL SCAN FREQUENCY	* PARAMETER		VXX:SLSS1=VXX:EDVIB=+*****	QVX:SLSS1=QVX:EDVIB	SLSS1=EDVIB=+*****		✓
		* PARAMETER1	240Hz	VXX:SLSS1=VXX:EDVIB=+24000		SLSS1=EDVIB=+24000		✓
			120Hz	VXX:SLSS1=VXX:EDVIB=+12000		SLSS1=EDVIB=+12000		✓
			60Hz	VXX:SLSS1=VXX:EDVIB=+06000		SLSS1=EDVIB=+06000		✓
			50Hz	VXX:SLSS1=VXX:EDVIB=+05000		SLSS1=EDVIB=+05000		✓
			48Hz	VXX:SLSS1=VXX:EDVIB=+04800		SLSS1=EDVIB=+04800		✓
			30Hz	VXX:SLSS1=VXX:EDVIB=+03000		SLSS1=EDVIB=+03000		✓
			25Hz	VXX:SLSS1=VXX:EDVIB=+02500		SLSS1=EDVIB=+02500		✓
			24Hz	VXX:SLSS1=VXX:EDVIB=+02400		SLSS1=EDVIB=+02400		✓
	SLOT : 3rd Party Board : EDID RESOLUTION / VERTICAL SCAN FREQUENCY		1024x768	VXX:SLSS1=VXX:EDUS1=1024:0768:*:*****	QVX:SLSS1=QVX:EDUS1	SLSS1=EDUS1=1024:0768:*:*****		✓
			1280x720	VXX:SLSS1=VXX:EDUS1=1280:0720:*:*****		SLSS1=EDUS1=1280:0720:*:*****		✓
			1280x800	VXX:SLSS1=VXX:EDUS1=1280:0800:*:*****		SLSS1=EDUS1=1280:0800:*:*****		✓
			1280x1024	VXX:SLSS1=VXX:EDUS1=1280:1024:*:*****		SLSS1=EDUS1=1280:1024:*:*****		✓
			1366x768	VXX:SLSS1=VXX:EDUS1=1366:0768:*:*****		SLSS1=EDUS1=1366:0768:*:*****		✓
			1400x1050	VXX:SLSS1=VXX:EDUS1=1400:1050:*:*****		SLSS1=EDUS1=1400:1050:*:*****		✓
			1440x900	VXX:SLSS1=VXX:EDUS1=1440:0900:*:*****		SLSS1=EDUS1=1440:0900:*:*****		✓
			1600x900	VXX:SLSS1=VXX:EDUS1=1600:0900:*:*****		SLSS1=EDUS1=1600:0900:*:*****		✓
			1600x1200	VXX:SLSS1=VXX:EDUS1=1600:1200:*:*****		SLSS1=EDUS1=1600:1200:*:*****		✓
			1680x1050	VXX:SLSS1=VXX:EDUS1=1680:1050:*:*****		SLSS1=EDUS1=1680:1050:*:*****		✓
			1920x1080	VXX:SLSS1=VXX:EDUS1=1920:1080:*:*****		SLSS1=EDUS1=1920:1080:*:*****		✓
			1920x1200	VXX:SLSS1=VXX:EDUS1=1920:1200:*:*****		SLSS1=EDUS1=1920:1200:*:*****		✓
			2048x1080	VXX:SLSS1=VXX:EDUS1=2048:1080:*:*****		SLSS1=EDUS1=2048:1080:*:*****		✓
			2560x1080	VXX:SLSS1=VXX:EDUS1=2560:1080:*:*****		SLSS1=EDUS1=2560:1080:*:*****		✓
			2560x1440	VXX:SLSS1=VXX:EDUS1=2560:1440:*:*****		SLSS1=EDUS1=2560:1440:*:*****		✓
			2560x1600	VXX:SLSS1=VXX:EDUS1=2560:1600:*:*****		SLSS1=EDUS1=2560:1600:*:*****		✓
			3440x1440	VXX:SLSS1=VXX:EDUS1=3440:1440:*:*****		SLSS1=EDUS1=3440:1440:*:*****		✓
			3840x2400	VXX:SLSS1=VXX:EDUS1=3840:2400:*:*****		SLSS1=EDUS1=3840:2400:*:*****		✓
		* PARAMETER1	Progressive Interlace	VXX:SLSS1=VXX:EDUS1=*****:p VXX:SLSS1=VXX:EDUS1=*****:i		SLSS1=EDUS1=*****:p SLSS1=EDUS1=*****:i		✓
		* PARAMETER2	240Hz	VXX:SLSS1=VXX:EDUS1=*****:*:24000		SLSS1=EDUS1=*****:*:24000		✓
			120Hz	VXX:SLSS1=VXX:EDUS1=*****:*:12000		SLSS1=EDUS1=*****:*:12000		✓
			60Hz	VXX:SLSS1=VXX:EDUS1=*****:*:06000		SLSS1=EDUS1=*****:*:06000		✓
			50Hz	VXX:SLSS1=VXX:EDUS1=*****:*:05000		SLSS1=EDUS1=*****:*:05000		✓
			48Hz	VXX:SLSS1=VXX:EDUS1=*****:*:04800		SLSS1=EDUS1=*****:*:04800		✓
			30Hz	VXX:SLSS1=VXX:EDUS1=*****:*:03000		SLSS1=EDUS1=*****:*:03000		✓
			25Hz	VXX:SLSS1=VXX:EDUS1=*****:*:02500		SLSS1=EDUS1=*****:*:02500		✓
			24Hz	VXX:SLSS1=VXX:EDUS1=*****:*:02400		SLSS1=EDUS1=*****:*:02400		✓
	SLOT : 3rd Party Board : EDID STATUS RESOLUTION / VERTICAL SCAN FREQUENCY		1024x768		QVX:SLSS1=QVX:ESUS1	SLSS1=ESUS1=1024:0768:*:*****		✓
			1280x720			SLSS1=ESUS1=1280:0720:*:*****		✓
			1280x800			SLSS1=ESUS1=1280:0800:*:*****		✓
			1280x1024			SLSS1=ESUS1=1280:1024:*:*****		✓
			1366x768			SLSS1=ESUS1=1366:0768:*:*****		✓
			1400x1050			SLSS1=ESUS1=1400:1050:*:*****		✓
			1440x900			SLSS1=ESUS1=1440:0900:*:*****		✓
			1600x900			SLSS1=ESUS1=1600:0900:*:*****		✓
			1600x1200			SLSS1=ESUS1=1600:1200:*:*****		✓
			1680x1050			SLSS1=ESUS1=1680:1050:*:*****		✓
			1920x1080			SLSS1=ESUS1=1920:1080:*:*****		✓
			1920x1200			SLSS1=ESUS1=1920:1200:*:*****		✓
			2048x1080			SLSS1=ESUS1=2048:1080:*:*****		✓
			2560x1080			SLSS1=ESUS1=2560:1080:*:*****		✓
			2560x1440			SLSS1=ESUS1=2560:1440:*:*****		✓
			2560x1600			SLSS1=ESUS1=2560:1600:*:*****		✓
			3440x1440			SLSS1=ESUS1=3440:1440:*:*****		✓
			3840x2400			SLSS1=ESUS1=3840:2400:*:*****		✓
		* PARAMETER1	Progressive Interlace			SLSS1=ESUS1=*****:p SLSS1=ESUS1=*****:i		✓
		* PARAMETER2	240Hz			SLSS1=ESUS1=*****:*:24000		✓
			120Hz			SLSS1=ESUS1=*****:*:12000		✓
			60Hz			SLSS1=ESUS1=*****:*:06000		✓
			50Hz			SLSS1=ESUS1=*****:*:05000		✓
			48Hz			SLSS1=ESUS1=*****:*:04800		✓
			30Hz			SLSS1=ESUS1=*****:*:03000		✓
			25Hz			SLSS1=ESUS1=*****:*:02500		✓
			24Hz			SLSS1=ESUS1=*****:*:02400		✓
	MULTI PROJECTOR SYNC - MODE	OFF		VXX:MPSI1=+00000	QVX:MPSI1	MPSI1=+00000		✓

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		REZ12 SERIES			
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	REZ12 /10/80 FEZ120C /100C/080C				
		MAIN		VXX:MPSI1=+00001		MPSI1=+00001		✓			
		SUB		VXX:MPSI1=+00002		MPSI1=+00002		✓			
	MULTI PROJECTOR SYNC - LINK STATUS	NO LINK			QVX:MPSI2	MPSI2=+00000		✓			
		LINKED				MPSI2=+00001		✓			
	FRAME SYNC SETTING(MULTI PROJECTOR SYNC) - CONTRAST SYNC.	OFF		VXX:CSYI1=+00000	QVX:CSYI1	CSYI1=+00000		✓			
		ON		VXX:CSYI1=+00001		CSYI1=+00001		✓			
	MULTI PROJECTOR SYNC - SHUTTER SYNC.	OFF		VXX:SSYI1=+00000	QVX:SSYI1	SSYI1=+00000		✓			
		ON		VXX:SSYI1=+00001		SSYI1=+00001		✓			
	MULTI PROJECTOR SYNC - TERMINAL SELECT	BNC		VXX:TSLI1=+00000	QVX:TSLI1	TSLI1=+00000		✓			
		SERIAL		VXX:TSLI1=+00001		TSLI1=+00001		✓			
	INPUT GUIDE	OFF		OID:0	QDI	0		✓			
		ON (SIMPLE)		OID:1		1		✓			
	OSD POSITION	UPPER LEFT		ODP:1	QDP	1		✓			
		CETRE LEFT		ODP:2		2		✓			
		LOWER LEFT		ODP:3		3		✓			
		TOP CENTER		ODP:4		4		✓			
		CENTER		ODP:5		5		✓			
		LOEER CENTER		ODP:6		6		✓			
		UPPER RIGHT		ODP:7		7		✓			
		CENTER RIGHT		ODP:8		8		✓			
		LOWER RIGHT		ODP:9		9		✓			
	OSD ROTATION	OFF		VXX:OSRI1=+00000	QVX:OSRI1	OSRI1=+00000		✓			
		CLOCKWISE		VXX:OSRI1=+00001		OSRI1=+00001		✓			
		COUNTER CLOCKWISE		VXX:OSRI1=+00002		OSRI1=+00002		✓			
	OSD MEMORY	OFF		VXX:OMYI0=+00000	QVX:OMYI0	OMYI0=+00000		✓			
		ON		VXX:OMYI0=+00001		OMYI0=+00001		✓			
	ON SCREEN	OFF		OOS:0	QOS	0		✓			
		ON		OOS:1		1		✓			
	WARNING MESSAGE	OFF		VXX:WMDI0=+00000	QVX:WMDI0	WMDI0=+00000		✓			
		ON		VXX:WMDI0=+00001		WMDI0=+00001		✓			
	OSD DESIGN	1(YELLOW)		MOD:0	QOD	0		✓			
		2(BLUE)		MOD:1		1		✓			
		3(WHITE)		MOD:2		2		✓			
		4(GREEN)		MOD:3		3		✓			
		5(PEACH)		MOD:4		4		✓			
		6(BROWN)		MOD:5		5		✓			
	MENU MODE	NORMAL		VXX:MMDI1=+00000	QVX:MMDI1	MMDI1=+00000		✓			
		SIMPLE		VXX:MMDI1=+00001		MMDI1=+00001		✓			
	SCREEN SETTING	16:10		VSF:0	QSF	0		✓			
		16:9		VSF:1		1		✓			
		4:3		VSF:2		2		✓			
	SCREEN POSITION-VERTICAL	min.		VXX:VSPI0=-00120	QVX:VSPI0	VSPI0=-00120		-120			
		max.		VXX:VSPI0=+00120		VSPI0=+00120		+120			
	SCREEN POSITION-HORIZONTAL	min.		VXX:HSPI0=-00320	QVX:HSPI0	HSPI0=-00320		-320			
		max.		VXX:HSPI0=+00320		HSPI0=+00320		+320			
	STARTUP LOGO	OFF		MLO:0	QLO	0		✓			
		USER LOGO		MLO:1		1		✓			
		DEFAULT LOGO		MLO:2		2		✓			
	UNIFORMITY-FLEXIBLE CORRECTION *	OFF		VXX:UFMI1=+00000	QVX:UFMI1	UFMI1=+00000		✓			
		ON(PRE)		VXX:UFMI1=+00011		UFMI1=+00011		✓			
		ON(POST)		VXX:UFMI1=+00021		*		✓			
	UNIFORMITY-INITILIZE	EXECUTE		VXX:UFMI2=+00001				✓			
	UNIFORMITY-MODE	CHROMA ONLY		VXX:UFMI3=+00001	QVX:UFMI3	UFMI3=+00001		✓			
		LUMINACE/CHROMA		VXX:UFMI3=+00011		UFMI3=+00011		✓			
	UNIFORMITY-WHITE/RED/GREEN/RED	* PARAMETER		E\$W:*,****,****,**	E\$R:*,**	** ,****,****		✓			
		* PARAMETER 1	WHITE		E\$W:W,****,****,**	E\$R:W,**	** ,****,****		✓		
			RED		E\$W:R,****,****,**	E\$R:R,**	** ,****,****		✓		
			GREEN		E\$W:G,****,****,**	E\$R:G,**	** ,****,****		✓		
			BLUE		E\$W:B,****,****,**	E\$R:B,**	** ,****,****		✓		
		* PARAMETER 2	VERTICAL(-127)		E\$W:*,-127,****,**	E\$R:*,**	** ,-127,****		✓		
			VERTICAL(+127)		E\$W:*,+127,****,**	E\$R:*,**	** ,+127,****		✓		
		* PARAMETER 3	HORIZONTAL(-127)		E\$W:*,****,-127,**	E\$R:*,**	** ,****,-127		✓		
			HOROZONTAL(+127)		E\$W:*,****,+127,**	E\$R:*,**	** ,****,+127		✓		
		* PARAMETER 4	L1(OFF)		E\$W:*,****,****,0*	E\$R:*,0*	0* ,****,****		✓		
			L1(ON)		E\$W:*,****,****,1*	E\$R:*,1*	1* ,****,****		✓		
			L2(OFF)		E\$W:*,****,****,*0	E\$R:*,*0	*0 ,****,****		✓		
			L2(ON)		E\$W:*,****,****,*1	E\$R:*,*1	*1 ,****,****		✓		
			UNIFORMITY-WHITE/RED/GREEN/RED	* PARAMETER		E\$W:*,****,****	E\$R:*	** ,****,****		✓	
				* PARAMETER 1	WHITE		E\$W:W,****,****	E\$R:W	** ,****,****		✓
					RED		E\$W:R,****,****	E\$R:R	** ,****,****		✓
GREEN					E\$W:G,****,****	E\$R:G	** ,****,****		✓		
BLUE					E\$W:B,****,****	E\$R:B	** ,****,****		✓		
* PARAMETER 2	VERTICAL(-127)				E\$W:*,-127,****		** ,-127,****		✓		
	VERTICAL(+127)				E\$W:*,+127,****		** ,+127,****		✓		
* PARAMETER 3	HORIZONTAL(-127)				E\$W:*,****,-127		** ,****,-127		✓		
	HOROZONTAL(+127)				E\$W:*,****,+127		** ,****,+127		✓		
* PARAMETER 4	L1(OFF)						0* ,****,****		✓		
	L1(ON)						1* ,****,****		✓		
	L2(OFF)						*0 ,****,****		✓		
	L2(ON)						*1 ,****,****		✓		
	SHUTTER SETTING-FADE IN			0.0s(OFF)		VXX:SEFS1=0.0	QVX:SEFS1	SEFS1=0.0		✓	
				0.5s		VXX:SEFS1=0.5		SEFS1=0.5		✓	
				1.0s		VXX:SEFS1=1.0		SEFS1=1.0		✓	
		1.5s		VXX:SEFS1=1.5		SEFS1=1.5		✓			
		2.0s		VXX:SEFS1=2.0		SEFS1=2.0		✓			
		2.5s		VXX:SEFS1=2.5		SEFS1=2.5		✓			
		3.0s		VXX:SEFS1=3.0		SEFS1=3.0		✓			
		3.5s		VXX:SEFS1=3.5		SEFS1=3.5		✓			
		4.0s		VXX:SEFS1=4.0		SEFS1=4.0		✓			
		5.0s		VXX:SEFS1=5.0		SEFS1=5.0		✓			
		7.0s		VXX:SEFS1=7.0		SEFS1=7.0		✓			
10.0s		VXX:SEFS1=10.0		SEFS1=10.0		✓					
	SHUTTER SETTING-FADE OUT	0.0s(OFF)		VXX:SEFS2=0.0	QVX:SEFS2	SEFS2=0.0		✓			
		0.5s		VXX:SEFS2=0.5		SEFS2=0.5		✓			
		1.0s		VXX:SEFS2=1.0		SEFS2=1.0		✓			
		1.5s		VXX:SEFS2=1.5		SEFS2=1.5		✓			
		2.0s		VXX:SEFS2=2.0		SEFS2=2.0		✓			
		2.5s		VXX:SEFS2=2.5		SEFS2=2.5		✓			
		3.0s		VXX:SEFS2=3.0		SEFS2=3.0		✓			
		3.5s		VXX:SEFS2=3.5		SEFS2=3.5		✓			
		4.0s		VXX:SEFS2=4.0		SEFS2=4.0		✓			
		5.0s		VXX:SEFS2=5.0		SEFS2=5.0		✓			
		7.0s		VXX:SEFS2=7.0		SEFS2=7.0		✓			
10.0s		VXX:SEFS2=10.0		SEFS2=10.0		✓					
	SHUTTER SETTING-STARTUP	OPEN		VXX:SEFI3=+00000	QVX:SEFI3	SEFI3=+00000		✓			
		CLOSE		VXX:SEFI3=+00001		SEFI3=+00001		✓			
	BACK COLOR	BLUE		OBC:0	QBC	0		✓			
		BLACK		OBC:1		1		✓			
		USER LOGO		OBC:2		2		✓			
		DEFAULT LOGO		OBC:3		3		✓			
	WAVEFORM MONITOR	OFF		OWM:0	QWM	0		✓			
		LUMINANCE		OWM:5		5		✓			
		RED		OWM:6		6		✓			
		GREEN		OWM:7		7		✓			
		BLUE		OWM:8		8		✓			
	WAVEFORM MONITOR-LINE ADJ.	0		VXX:WMLI0=+00000	QVX:WMLI0	WMLI0=+00000		✓			
		+2159		VXX:WMLI0=+02159		WMLI0=+02159		✓			
	AC VOLTAGE				QVX:VMOI2	VMOI2=+00000		✓			

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		REZ12 SERIES	
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	REZ12 /10/80 FEZ120C /100C/080C		
CUT OFF-RED	OFF			VXX:CUTI1=+0000	QVX:CUTI1	VMOI2=+99999		✓	
	ON			VXX:CUTI1=+00001		CUTI1=+00000		✓	
						CUTI1=+00001		✓	
CUT OFF-GREEN	OFF			VXX:CUTI2=+00000	QVX:CUTI2	CUTI2=+00000		✓	
	ON			VXX:CUTI2=+00001		CUTI2=+00001		✓	
CUT OFF-BLUE	OFF			VXX:CUTI3=+00000	QVX:CUTI3	CUTI3=+00000		✓	
	ON			VXX:CUTI3=+00001		CUTI3=+00001		✓	
PROJECTOR ID	0(ALL)			RIS:00				✓	
	64			RIS:64				✓	
ID ALL	OFF			RVS:0	QVY	0		✓	
	ON			RVS:1		1		✓	
PROJECTION METHOD INSTALLATION	FRONT/DESK			OIL:0	QSP	0		✓	
	REAR/DESK			OIL:1		1		✓	
	FRONT/CEILING			OIL:2		2		✓	
	REAR/CEILING			OIL:3		3		✓	
	FRONT/AUTO			OIL:4		4		✓	
REAR/AUTO			OIL:5		5		✓		
PROJECTION METHOD(AUTO)	FRONT/DESK				QVX:PJMI2	PJMI2=+00000		✓	
	REAR/DESK					PJMI2=+00001		✓	
	FRONT/CEILING					PJMI2=+00002		✓	
	REAR/CEILING					PJMI2=+00003		✓	
AUTO COOLING CONDITION-STATUS	FLOOR				QVX:ADRI1	ADRI1=+00000		✓	
	CEILING					ADRI1=+00001		✓	
	VERTICAL UP					ADRI1=+00002		✓	
	VERTICAL DOWN					ADRI1=+00003		✓	
	PORTRAIT					ADRI1=+00004		✓	
OPERATING MODE	NORMAL			VXX:OPEI1=+00000	QVX:OPEI1	OPEI1=+00000		✓	
	ECO			VXX:OPEI1=+00001		OPEI1=+00001		✓	
	QUIET1(QUIET)			VXX:OPEI1=+00021		OPEI1=+00021		✓	
	USER1(USER)			VXX:OPEI1=+00101		OPEI1=+00101		✓	
	USER2			VXX:OPEI1=+00102		OPEI1=+00102		✓	
	USER3			VXX:OPEI1=+00103		OPEI1=+00103		✓	
LIGHT OUTPUT	min.			VXX:LOPI2=+00050	QVX:LOPI2	LOPI2=+00050		5%	
	max.			VXX:LOPI2=+01000		LOPI2=+01000		100%	
MAX LIGHT OUTPUT	min.			VXX:LOPI3=+00050	QVX:LOPI3	LOPI3=+00050		5%	
	max.			VXX:LOPI3=+01000		LOPI3=+01000		100%	
BRIGHTNESS CONTROL-SETUP-CALIBRATION TIME	OFF			VXX:BTMI1=+00000	QVX:BTMI1	BTMI1=+00000		✓	
	00:01			VXX:BTMI1=+00001		BTMI1=+00001		✓	
	23:59			VXX:BTMI1=+02359		BTMI1=+02359		✓	
	00:00			VXX:BTMI1=+02400		BTMI1=+02400		✓	
BRIGHTNESS CONTROL-SETUP-STARTUP CALIBRATION	OFF			VXX:BSCI1=+00000	QVX:BSCI1	BSCI1=+00000		✓	
	ON			VXX:BSCI1=+00001		BSCI1=+00001		✓	
BRIGHTNESS CONTROL-SETUP-CALIBRATION MESSAGE	OFF			VXX:BMGI1=+00000	QVX:BMGI1	BMGI1=+00000		✓	
	ON			VXX:BMGI1=+00001		BMGI1=+00001		✓	
BRIGHTNESS CONTROL-SETUP-CONSTANT MODE	OFF			VXX:BCMI0=+00000	QVX:BCMI0	BCMI0=+00000		✓	
	AUTO			VXX:BCMI0=+00001		BCMI0=+00001		✓	
	PC			VXX:BCMI0=+00002		BCMI0=+00002		✓	
BRIGHTNESS CONTROL-SETUP-LINK	OFF			VXX:BCLIO=+00000	QVX:BCLIO	BCLIO=+00000		✓	
	GROUP A			VXX:BCLIO=+00001		BCLIO=+00001		✓	
	GROUP B			VXX:BCLIO=+00002		BCLIO=+00002		✓	
	GROUP C			VXX:BCLIO=+00003		BCLIO=+00003		✓	
	GROUP D			VXX:BCLIO=+00004		BCLIO=+00004		✓	
BRIGHTNESS CONTROL-SETUP APPLY	APPLY			VXX:BCSI0=+00001				✓	
	APPLY(RESTART)			VXX:BCSI0=+00002				✓	
BRIGHTNESS CONTROL- PREVIOUS TARGET BRIGHTNESS	***** : target				QVX:BCSS1	BCSS1=*****:yyymmddhhmmss		✓	
	brightness(00000~0							✓	
	10000(0.0~100.0%)							✓	
	yy : year							✓	
	mm : month							✓	
	dd : day							✓	
	hh : hour							✓	
mm : minute							✓		
ss : second							✓		
STANDBY MODE	NORMAL			VXX:STMI0=+00000	QVX:STMI0	STMI0=+00000		✓	
	ECO			VXX:STMI0=+00003		STMI0=+00003		✓	
SLOT SETTING-SLOT STANDBY	DISABLE			VXX:SSBI1=+00000	QVX:SSBI1	SSBI1=+00000		✓	
	ENABLE			VXX:SSBI1=+00001		SSBI1=+00001		✓	
SLOT SETTING-POWER ON				VXX:SSBI2=+00001				✓	
SLOT SETTING-FORCED TERMINATION				VXX:SSBI3=+00001				✓	
QUICK STARTUP	OFF			VXX:QSUI1=+00000	QVX:QSUI1	QSUI1=+00000		✓	
	ON			VXX:QSUI1=+00001		QSUI1=+00001		✓	
QUICK STARTUP-VALID PERIOD	30MIN.			VXX:QSUI2=+00030	QVX:QSUI2	QSUI2=+00030		✓	
	60MIN.			VXX:QSUI2=+00060		QSUI2=+00060		✓	
	90MIN.			VXX:QSUI2=+00090		QSUI2=+00090		✓	
SCHEDULE	OFF			VXX:SCHI0=+00000	QVX:SCHI0	SCHI0=+00000		✓	
	ON			VXX:SCHI0=+00001		SCHI0=+00001		✓	
SCHEDULE-PROGRAM ASSIGN	OFF			VXX:SPGI*=+00000	QVX:SPGI*	SPGI*=+00000		✓	
	PROGRAM1			VXX:SPGI*=+00001		SPGI*=+00001		✓	
	PROGRAM2			VXX:SPGI*=+00002		SPGI*=+00002		✓	
	PROGRAM3			VXX:SPGI*=+00003		SPGI*=+00003		✓	
	PROGRAM4			VXX:SPGI*=+00004		SPGI*=+00004		✓	
	PROGRAM5			VXX:SPGI*=+00005		SPGI*=+00005		✓	
	PROGRAM6			VXX:SPGI*=+00006		SPGI*=+00006		✓	
	PROGRAM7			VXX:SPGI*=+00007		SPGI*=+00007		✓	
		SUN			VXX:SPGI0=+0000*	QVX:SPGI0	SPGI0=+0000*		✓
		MON			VXX:SPGI1=+0000*	QVX:SPGI1	SPGI1=+0000*		✓
		TUE			VXX:SPGI2=+0000*	QVX:SPGI2	SPGI2=+0000*		✓
		WED			VXX:SPGI3=+0000*	QVX:SPGI3	SPGI3=+0000*		✓
		THU			VXX:SPGI4=+0000*	QVX:SPGI4	SPGI4=+0000*		✓
	FRI			VXX:SPGI5=+0000*	QVX:SPGI5	SPGI5=+0000*		✓	
	SAT			VXX:SPGI6=+0000*	QVX:SPGI6	SPGI6=+0000*		✓	
SCHEDULE-COMMAND SETTING	COMMAND Del			VXX:SCCS*=**00****	QVX:SCCS*=**	SCCS*=**00****		✓	
	STANDBY			VXX:SCCS*=**10****		SCCS*=**10****		✓	
	POWER ON			VXX:SCCS*=**11****		SCCS*=**11****		✓	
	SHUTTER OPEN			VXX:SCCS*=**20****		SCCS*=**20****		✓	
	SHUTTER CLOSE			VXX:SCCS*=**21****		SCCS*=**21****		✓	
	HDMI1 INPUT			VXX:SCCS*=**53****		SCCS*=**53****		✓	
	HDMI2 INPUT			VXX:SCCS*=**54****		SCCS*=**54****		✓	
	DisplayPort			VXX:SCCS*=**5D****		SCCS*=**5D****		✓	
	SLOT1-1 INPUT			VXX:SCCS*=**68****		SCCS*=**68****		✓	
	SLOT1 DIGITAL LINK			VXX:SCCS*=**G0****		SCCS*=**G0****		✓	
	SLOT1-DIGITAL LINK-INPUT 1			VXX:SCCS*=**G1****		SCCS*=**G1****		✓	
	SLOT1-DIGITAL LINK-INPUT 2			VXX:SCCS*=**G2****		SCCS*=**G2****		✓	
	SLOT1-DIGITAL LINK-INPUT 3			VXX:SCCS*=**G3****		SCCS*=**G3****		✓	
	SLOT1-DIGITAL LINK-INPUT 4			VXX:SCCS*=**G4****		SCCS*=**G4****		✓	
	SLOT1-DIGITAL LINK-INPUT 5			VXX:SCCS*=**G5****		SCCS*=**G5****		✓	
	SLOT1-DIGITAL LINK-INPUT 6			VXX:SCCS*=**G6****		SCCS*=**G6****		✓	
	SLOT1-DIGITAL LINK-INPUT 7			VXX:SCCS*=**G7****		SCCS*=**G7****		✓	
	SLOT1-DIGITAL LINK-INPUT 8			VXX:SCCS*=**G8****		SCCS*=**G8****		✓	
	SLOT1-DIGITAL LINK-INPUT 9			VXX:SCCS*=**G9****		SCCS*=**G9****		✓	
	SLOT1-DIGITAL LINK-INPUT 10			VXX:SCCS*=**GA****		SCCS*=**GA****		✓	
	NORMAL			VXX:SCCS*=**70****		SCCS*=**70****		✓	
	ECO			VXX:SCCS*=**71****		SCCS*=**71****		✓	
	USER1(USER)			VXX:SCCS*=**75****		SCCS*=**75****		✓	
	USER2			VXX:SCCS*=**76****		SCCS*=**76****		✓	
	USER3			VXX:SCCS*=**77****		SCCS*=**77****		✓	
	SILENT1(QUIET1/QUIET)			VXX:SCCS*=**7A****		SCCS*=**7A****		✓	
	QUICK STARTUP OFF			VXX:SCCS*=**A2****		SCCS*=**A2****		✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		REZ12 SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	REZ12 /10/80 FEZ120C /100C/080C	
PROJECTOR SETUP	QUICK STARTUP ON			VXX:SCCS*=**A3****		SCCS*=**A3****		✓
	* PARAMETER1	PROGRAM1		VXX:SCCS1=*****	QVX:SCCS1=**	SCCS1=*****		✓
		PROGRAM2		VXX:SCCS2=*****	QVX:SCCS2=**	SCCS2=*****		✓
		PROGRAM3		VXX:SCCS3=*****	QVX:SCCS3=**	SCCS3=*****		✓
		PROGRAM4		VXX:SCCS4=*****	QVX:SCCS4=**	SCCS4=*****		✓
		PROGRAM5		VXX:SCCS5=*****	QVX:SCCS5=**	SCCS5=*****		✓
		PROGRAM6		VXX:SCCS6=*****	QVX:SCCS6=**	SCCS6=*****		✓
		PROGRAM7		VXX:SCCS7=*****	QVX:SCCS7=**	SCCS7=*****		✓
	* PARAMETER2	COMMAND 1		VXX:SCCS*=01*****	QVX:SCCS*=01	SCCS*=01*****		✓
		COMMAND 16		VXX:SCCS*=16*****	QVX:SCCS*=16	SCCS*=16*****		✓
	* PARAMETER3	00:00		VXX:SCCS*=****0000		SCCS*=****0000		✓
		23:59		VXX:SCCS*=****2359		SCCS*=****2359		✓
	STARTUP INPUT SELECT	HDMI1		VXX:SISS1=HD1	QVX:SISS1	SISS1=HD1		✓
		HDMI2		VXX:SISS1=HD2		SISS1=HD2		✓
		DisplayPort		VXX:SISS1=DP1		SISS1=DP1		✓
		SLOT1 : SDM : 12G SDI		VXX:SISS1=DM1,SD1		SISS1=DM1,SD1		✓
		SLOT1 : SDM : Digital Link		VXX:SISS1=DM1,DL1		SISS1=DM1,DL1		✓
		SLOT1 : SDM : PressIT		VXX:SISS1=DM1,WP1		SISS1=DM1,WP1		✓
		SLOT1 : SDM : 3rd Party Board		VXX:SISS1=DM1,TP1		SISS1=DM1,TP1		✓
		SLOT1 : SDM : 12G SDI OPT1		VXX:SISS1=DM1,OP1		SISS1=DM1,OP1		✓
		SLOT1 : SDM : 12G SDI OPT2		VXX:SISS1=DM1,OP2		SISS1=DM1,OP2		✓
		LAST USED		VXX:SISS1=LSU		SISS1=LSU		✓
	STARTUP INPUT SELECT (SLOT : DIGITAL LINK)	LAST USED		VXX:SLSS1=VXX:SISS12=+00000	QVX:SLSS1=QVX:SISS12	SLSS1=SISS12=+00000		✓
		INPUT1		VXX:SLSS1=VXX:SISS12=+00001		SLSS1=SISS12=+00001		✓
		INPUT2		VXX:SLSS1=VXX:SISS12=+00002		SLSS1=SISS12=+00002		✓
		INPUT3		VXX:SLSS1=VXX:SISS12=+00003		SLSS1=SISS12=+00003		✓
		INPUT4		VXX:SLSS1=VXX:SISS12=+00004		SLSS1=SISS12=+00004		✓
		INPUT5		VXX:SLSS1=VXX:SISS12=+00005		SLSS1=SISS12=+00005		✓
		INPUT6		VXX:SLSS1=VXX:SISS12=+00006		SLSS1=SISS12=+00006		✓
		INPUT7		VXX:SLSS1=VXX:SISS12=+00007		SLSS1=SISS12=+00007		✓
		INPUT8		VXX:SLSS1=VXX:SISS12=+00008		SLSS1=SISS12=+00008		✓
		INPUT9		VXX:SLSS1=VXX:SISS12=+00009		SLSS1=SISS12=+00009		✓
		INPT10		VXX:SLSS1=VXX:SISS12=+00010		SLSS1=SISS12=+00010		✓
	NO SIGNAL SHUT-OFF	DISABLE		OAF:00	QAF	00		✓
		10min		OAF:10		10		✓
		20min		OAF:20		20		✓
		30min		OAF:30		30		✓
		40min		OAF:40		40		✓
		50min		OAF:50		50		✓
		60min		OAF:60		60		✓
		70min		OAF:70		70		✓
		80min		OAF:80		80		✓
		90min		OAF:90		90		✓
	NO SIGNAL LIGHTS-OUT	DISABLE		VXX:SLOI1=+00000	QVX:SLOI1	SLOI1=+00000		✓
		10SEC.		VXX:SLOI1=+00010		SLOI1=+00010		✓
		20SEC.		VXX:SLOI1=+00020		SLOI1=+00020		✓
		30SEC.		VXX:SLOI1=+00030		SLOI1=+00030		✓
		1MIN.		VXX:SLOI1=+00060		SLOI1=+00060		✓
		2MIN.		VXX:SLOI1=+00120		SLOI1=+00120		✓
		3MIN.		VXX:SLOI1=+00180		SLOI1=+00180		✓
		5MIN.		VXX:SLOI1=+00300		SLOI1=+00300		✓
	NO SIGNAL SETTING - SECONDARY INPUT	OFF		VXX:SINS1=OFF	QVX:SINS1	SINS1=OFF		✓
		HDMI1		VXX:SINS1=HD1		SINS1=HD1		✓
		HDMI2		VXX:SINS1=HD2		SINS1=HD2		✓
		DisplayPort		VXX:SINS1=DP1		SINS1=DP1		✓
		SLOT1 : SDM : 12G SDI		VXX:SINS1=DM1,SD1		SINS1=DM1,SD1		✓
		SLOT1 : SDM : Digital Link		VXX:SINS1=DM1,DL1		SINS1=DM1,DL1		✓
		SLOT1 : SDM : PressIT		VXX:SINS1=DM1,WP1		SINS1=DM1,WP1		✓
		SLOT1 : SDM : 3rd Party Board		VXX:SINS1=DM1,TP1		SINS1=DM1,TP1		✓
		SLOT1 : SDM : 12G SDI OPT1		VXX:SINS1=DM1,OP1		SINS1=DM1,OP1		✓
		SLOT1 : SDM : 12G SDI OPT2		VXX:SINS1=DM1,OP2		SINS1=DM1,OP2		✓
	REMOTE2 - MODE	DEFAULT		VXX:RMPI0=+00000	QVX:RMPI0	RMPI0=+00000		✓
		USER		VXX:RMPI0=+00001		RMPI0=+00001		✓
	REMOTE2 - PIN2	NONE		VXX:RMPS1=P2<NONE	QVX:RMPS1=P2	RMPS1=P2<NONE		✓
		POWER		VXX:RMPS1=P2<POWER		RMPS1=P2<POWER		✓
	REMOTE2 - PIN3 - 7	* PARAMETER		VXX:RMPS1=P*<*****	QVX:RMPS1=P*			✓
	* PARAMETER1	PIN3		VXX:RMPS1=P3<*****		RMPS1=P3<*****		✓
		PIN4		VXX:RMPS1=P4<*****		RMPS1=P4<*****		✓
		PIN5		VXX:RMPS1=P5<*****		RMPS1=P5<*****		✓
		PIN6		VXX:RMPS1=P6<*****		RMPS1=P6<*****		✓
		PIN7		VXX:RMPS1=P7<*****		RMPS1=P7<*****		✓
		NONE		VXX:RMPS1=P*<NONE		RMPS1=P*<NONE		✓
		HDMI		VXX:RMPS1=P*<HDMI		RMPS1=P*<HDMI		✓
	* PARAMETER2	HDMI1		VXX:RMPS1=P*<HDMI1		RMPS1=P*<HDMI1		✓
		HDMI2		VXX:RMPS1=P*<HDMI2		RMPS1=P*<HDMI2		✓
		DisplayPort		VXX:RMPS1=P*<DP1		RMPS1=P*<DP1		✓
		SLOT1 : SDM : 12G SDI		VXX:RMPS1=P*<DM1,SD1		RMPS1=P*<DM1,SD1		✓
		SLOT1 : SDM : Digital Link		VXX:RMPS1=P*<DM1,DL1		RMPS1=P*<DM1,DL1		✓
		SLOT1 : SDM : PressIT		VXX:RMPS1=P*<DM1,WP1		RMPS1=P*<DM1,WP1		✓
		SLOT1 : SDM : 3rd Party Board		VXX:RMPS1=P*<DM1,TP1		RMPS1=P*<DM1,TP1		✓
		SLOT1 : SDM : 12G SDI OPT1		VXX:RMPS1=P*<DM1,OP1		RMPS1=P*<DM1,OP1		✓
		SLOT1 : SDM : 12G SDI OPT2		VXX:RMPS1=P*<DM1,OP2		RMPS1=P*<DM1,OP2		✓
		REMOTE2 - PIN8	NONE		VXX:RMPS1=P8<NONE	QVX:RMPS1=P8	RMPS1=P8<NONE	
		SHUTTER		VXX:RMPS1=P8<SHUTTER		RMPS1=P8<SHUTTER		✓
	FUNCTION BUTTON	DISABLE		OFC:0	QFC	0		✓
		SYSTEM SELECTOR		OFC:1		1		✓
		SYSTEM DAYLIGHT VIEW		OFC:2		2		✓
		SUB MEMORY		OFC:3		3		✓
		FREEZE		OFC:4		4		✓
		WAVEFORM MONITOR		OFC:6		6		✓
		LENS MEMORY LOAD		OFC:7		7		✓
		PROJECTION METHOD		OFC:10		10		✓
		GEOMETRY		OFC:13		13		✓
		ANGLE MONITOR		OFC:15		15		✓
	DATE AND TIME-DATE SETTING	Year: yyyy		TSD:201506151	QGD	201506161		✓
		Month: mm		TSD:yyyymmddw		yyyymmddw		✓
		Date: dd						✓
		Day:w(1~7:Mon~Sun)						✓
	DATE AND TIME-TIME SETTING	Hour: hh		TST:154503	QGT	154503		✓
		Minute: mm		TST:hmmss		hmmss		✓
	Second: ss						✓	
DATE AND TIME-NTP SYNCHRONIZATION	OFF		VXX:NTPI0=+00000	QVX:NTPI0	NTPI0=+00000		✓	
	ON		VXX:NTPI0=+00001		NTPI0=+00001		✓	
LENS ID	All		VXX:LNEI4=+00000	QVX:LNEI4	LNEI4=+00000		✓	
	1		VXX:LNEI4=+00001		LNEI4=+00001		✓	
	255		VXX:LNEI4=+00255		LNEI4=+00255		✓	
LENS NAME			VXX:LNES5=LENSNAME	QVX:LNES5	LNES5=LENSNAME		✓	
LENS CALIBRATION	EXECUTE (ALL)		VXX:LNIS0=+00001				✓	
LENS MEMORY1 NAME CHANGE	LENSMEMORY1		VXX:NCGS5=LENSMEMORY1	QVX:NCGS5	NCGS5=LENSMEMORY1		✓	
LENS MEMORY2 NAME CHANGE	LENSMEMORY2		VXX:NCGS6=LENSMEMORY2	QVX:NCGS6	NCGS6=LENSMEMORY2		✓	
LENS MEMORY3 NAME CHANGE	LENSMEMORY3		VXX:NCGS7=LENSMEMORY3	QVX:NCGS7	NCGS7=LENSMEMORY3		✓	
LENS MEMORY4 NAME CHANGE	LENSMEMORY4		VXX:NCGS9=LENSMEMORY4	QVX:NCGS9	NCGS9=LENSMEMORY4		✓	
LENS MEMORY5 NAME CHANGE	LENSMEMORY5		VXX:NCGSA=LENSMEMORY5	QVX:NCGSA	NCGSA=LENSMEMORY5		✓	
LENS MEMORY6 NAME CHANGE	LENSMEMORY6		VXX:NCGSB=LENSMEMORY6	QVX:NCGSB	NCGSB=LENSMEMORY6		✓	
LENS MEMORY7 NAME CHANGE	LENSMEMORY7		VXX:NCGSC=LENSMEMORY7	QVX:NCGSC	NCGSC=LENSMEMORY7		✓	
LENS MEMORY8 NAME CHANGE	LENSMEMORY8		VXX:NCGSD=LENSMEMORY8	QVX:NCGSD	NCGSD=LENSMEMORY8		✓	
LENS MEMORY9 NAME CHANGE	LENSMEMORY9		VXX:NCGSE=LENSMEMORY9	QVX:NCGSE	NCGSE=LENSMEMORY9		✓	
LENS MEMORY10 NAME CHANGE	LENSMEMORY10		VXX:NCGSF=LENSMEMORY10	QVX:NCGSF	NCGSF=LENSMEMORY10		✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		REZ12 SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	REZ12 /10/80 FEZ120C /100C/080C	
	LENS MEMORY-LOAD	LENS MEMORY1		VXX:LNMI1=+00000				✓
		LENS MEMORY2		VXX:LNMI1=+00001				✓
		LENS MEMORY3		VXX:LNMI1=+00002				✓
		LENS MEMORY4		VXX:LNMI1=+00003				✓
		LENS MEMORY5		VXX:LNMI1=+00004				✓
		LENS MEMORY6		VXX:LNMI1=+00005				✓
		LENS MEMORY7		VXX:LNMI1=+00006				✓
		LENS MEMORY8		VXX:LNMI1=+00007				✓
		LENS MEMORY9		VXX:LNMI1=+00008				✓
		LENS MEMORY10		VXX:LNMI1=+00009				✓
	LENS MEMORY-SAVE	LENS MEMORY1		VXX:LNMI2=+00000				✓
		LENS MEMORY2		VXX:LNMI2=+00001				✓
		LENS MEMORY3		VXX:LNMI2=+00002				✓
		LENS MEMORY4		VXX:LNMI2=+00003				✓
		LENS MEMORY5		VXX:LNMI2=+00004				✓
		LENS MEMORY6		VXX:LNMI2=+00005				✓
		LENS MEMORY7		VXX:LNMI2=+00006				✓
		LENS MEMORY8		VXX:LNMI2=+00007				✓
		LENS MEMORY9		VXX:LNMI2=+00008				✓
		LENS MEMORY10		VXX:LNMI2=+00009				✓
	LENS MEMORY-DELETE	LENS MEMORY1		VXX:LNMI3=+00000				✓
		LENS MEMORY2		VXX:LNMI3=+00001				✓
		LENS MEMORY3		VXX:LNMI3=+00002				✓
		LENS MEMORY4		VXX:LNMI3=+00003				✓
		LENS MEMORY5		VXX:LNMI3=+00004				✓
		LENS MEMORY6		VXX:LNMI3=+00005				✓
		LENS MEMORY7		VXX:LNMI3=+00006				✓
		LENS MEMORY8		VXX:LNMI3=+00007				✓
		LENS MEMORY9		VXX:LNMI3=+00008				✓
		LENS MEMORY10		VXX:LNMI3=+00009				✓
LENS MEMORY1-DEFAULT NAME	LENSMEMORY1		VXX:NCLI5=+00000				✓	
LENS MEMORY2-DEFAULT NAME	LENSMEMORY2		VXX:NCLI6=+00000				✓	
LENS MEMORY3-DEFAULT NAME	LENSMEMORY3		VXX:NCLI7=+00000				✓	
LENS MEMORY4-DEFAULT NAME	LENSMEMORY4		VXX:NCLI9=+00000				✓	
LENS MEMORY5-DEFAULT NAME	LENSMEMORY5		VXX:NCLIA=+00000				✓	
LENS MEMORY6-DEFAULT NAME	LENSMEMORY6		VXX:NCLIB=+00000				✓	
LENS MEMORY7-DEFAULT NAME	LENSMEMORY7		VXX:NCLIC=+00000				✓	
LENS MEMORY8-DEFAULT NAME	LENSMEMORY8		VXX:NCLID=+00000				✓	
LENS MEMORY9-DEFAULT NAME	LENSMEMORY9		VXX:NCLIE=+00000				✓	
LENS MEMORY10-DEFAULT NAME	LENSMEMORY10		VXX:NCLIF=+00000				✓	
INITIALIZE-ALL USER DATA	USER INITILIZE		VXX:RST1=0password				✓	
	USER RESTORE		VXX:RST1=1password				✓	
INITIAL START UP	STANDBY		OPY:0	QPY	0		✓	
	ON		OPY:1		1		✓	
	LAST MEMORY		OPY:2		2		✓	
MODEL NAME	MODEL NAME			QID	MODEL NAME		✓	
SERIAL NUMBER	SW0101234			QSN	Sw0101234		✓	
PROJECTOR RUNTIME	7864320H			QVX:RTMS1	RTMS1=7864320		✓	
LAMP1(LIGHT1) RUNTIME	9999H			Q\$L:1	9999		✓	
LAMP2(LIGHT2) RUNTIME	9999H			Q\$L:2	9999		✓	
LIGHT1 RUNTIME	7864320H			QVX:LRTS3=00	LRTS3=00:7864320		✓	
LIGHT2 RUNTIME	7864320H			QVX:LRTS3=01	LRTS3=01:7864320		✓	
LIGHT STATUS	ALL OFF			QLS	0		✓	
	1:ON, 2:OFF				1		✓	
	1:OFF, 2:ON				2		✓	
	ALL ON				3		✓	
CONTINUOUS LIGHTING TIME	7864320H00M			QVX:CLTS1	CLTS1=7864320:00		✓	
CONSOLIDATED RUNTIME	7864320H			QVX:CRTS1	CRTS1=7864320		✓	
LAMP(LIGHT) CONTROL STATUS	LAMP OFF			Q\$S	0		✓	
	In turning ON				1		✓	
	LAMP ON				2		✓	
	LAMP Cooling				3		✓	
POWER STATUS	POWER OFF			QVX:POWI1	POWI1=+00001		✓	
	In turning ON				POWI1=+00002		✓	
	POWER ON				POWI1=+00003		✓	
	Cooling				POWI1=+00004		✓	
MAC ADDRESS	AB0102030405			QMA	AB0102030405		✓	
FIRMWARE VERSION	V1.00			QVX:SVRSE	SVRSE=1.00		✓	
INPUT SIGNAL NAME	CHANNEL1 (MAIN CH)			QVX:NSGS1	NSGS1=*****		✓	
TEMPERATURE (INTAKE)	0030/0080			QTM:0	0030/0080		✓	
TEMPERATURE (EXHAUST AIR)	0030/0080			QTM:1	0030/0080		✓	
TEMPERATURE (OPTICS MODULE)	0030/0080			QTM:2	0030/0080		✓	
TEMPERATURE (LIGHT1 / LIGHT1-B)	0030/0080			QTM:11	0030/0080		✓	
TEMPERATURE (LIGHT2 / LIGHT1-S)	0030/0080			QTM:12	0030/0080		✓	
INDICATOR SETTING - INDICATOR MODE	OFF		VXX:ISMI1=+00000	QVX:ISMI1	ISMI1=+00000		✓	
	NORMAL		VXX:ISMI1=+00001		ISMI1=+00001		✓	
	TIMEOUT		VXX:ISMI1=+00002		ISMI1=+00002		✓	
INDICATOR SETTING - TIMEOUT (min)	min.		VXX:ISMI2=+00001	QVX:ISMI2	ISMI2=+00001	1	✓	
	max.		VXX:ISMI2=+00015		ISMI2=+00015	15	✓	
INDICATOR SETTING - NOTIFICATION	DISABLE		VXX:ISMI3=+00000	QVX:ISMI3	ISMI3=+00000	✓	✓	
	ENABLE		VXX:ISMI3=+00001		ISMI3=+00001	✓	✓	
LAN data Cloning Write protect	OFF		LCL:WRP0	QCL:WRP	QCL:WRP0	✓	✓	
	ON		LCL:WRP1		QCL:WRP1	✓	✓	
HDMI-CEC	OFF		SHC:FNC0	QHC:FNC	QHC:FNC0	✓	✓	
	ON		SHC:FNC1		QHC:FNC1	✓	✓	
HDMI-CEC HDMI1 (Change Device)	NEXT		SHC:HM1NXT			✓	✓	
	PREVIEW		SHC:HM1PRE			✓	✓	
HDMI-CEC HDMI1 (Get Device Name)	DEVICE NAME			QHC:HM1	QHC:HM1DEVICENAME	✓	✓	
HDMI-CEC HDMI2 (Change Device)	NEXT		SHC:HM2NXT			✓	✓	
	PREVIEW		SHC:HM2PRE			✓	✓	
HDMI-CEC HDMI2 (Get Device Name)	DEVICE NAME			QHC:HM2	QHC:HM2DEVICENAME	✓	✓	
HDMI-CEC - MENU CODE	0x09 (ROOT)		SHC:MNC1	QHC:MNC	QHC:MNC1	✓	✓	
	0x0A (SETUP)		SHC:MNC2		QHC:MNC2	✓	✓	
	0x0B (CONTENTS)		SHC:MNC3		QHC:MNC3	✓	✓	
	0x0C (FAVORITE)		SHC:MNC4		QHC:MNC4	✓	✓	
	0x10 (MEDIA TOP)		SHC:MNC5		QHC:MNC5	✓	✓	
	0x11 (MEDIA POP UP)		SHC:MNC6		QHC:MNC6	✓	✓	
HDMI-CEC - PROJECTOR -> DEVICE	DISABLE		SHC:PTSOFF	QHC:PTS	QHC:PTSOFF	✓	✓	
	POWER OFF		SHC:PTSPOF		QHC:PTSPOF	✓	✓	
	POWER ON/OFF		SHC:PTSPWR		QHC:PTSPWR	✓	✓	
HDMI-CEC - DEVICE -> PROJECTOR	DISABLE		SHC:STPOFF	QHC:STP	QHC:STPOFF	✓	✓	
	POWER ON		SHC:STPPON		QHC:STPPON	✓	✓	
	POWER ON/OFF		SHC:STPPWR		QHC:STPPWR	✓	✓	
TEST PATTERN	Off		OTS:00	QTS	00	✓	✓	
	White		OTS:01		01	✓	✓	
	Black		OTS:02		02	✓	✓	
	Window		OTS:05		05	✓	✓	
	Reversed Window		OTS:06		06	✓	✓	
	Cross Hatch		OTS:07		07	✓	✓	
	Color Bar V		OTS:08		08	✓	✓	
	Color Bar Side		OTS:51		51	✓	✓	
	16:9/4:3		OTS:59		59	✓	✓	
	Focus Red		OTS:70		70	✓	✓	
	Focus Green		OTS:71		71	✓	✓	
	Focus Blue		OTS:72		72	✓	✓	
	Focus Cyan		OTS:73		73	✓	✓	
	Focus Magenta		OTS:74		74	✓	✓	
	Focus Yellow		OTS:75		75	✓	✓	

CATEGORY	FUNCTION	Parameter/Name	Sub-Parameter	CONTROL		QUERY		REZ12 SERIES
				COMMANDS/CALL BACK	COMMANDS	CALL BACK	REZ12 /10/80 FEZ120C /100C/080C	
	Focus			OTS: 78		78		✓
	CIRCLE			OTS: 87		87		✓
	USER TEST PATTERN 1			OTS: A1		A1		✓
	USER TEST PATTERN 2			OTS: A2		A2		✓
	USER TEST PATTERN 3			OTS: A3		A3		✓
	USER TEST PATTERN - RENAME USER TEST PATTERN	USER TEST PATTERN 1 - NAME		VXX: TPNS1=01: USERTESTPATTERN1	QVX: TPNS1=01	TPNS1=01: USERTESTPATTERN1		✓
		USER TEST PATTERN 2 - NAME		VXX: TPNS1=02: USERTESTPATTERN2	QVX: TPNS1=02	TPNS1=02: USERTESTPATTERN2		✓
		USER TEST PATTERN 3 - NAME		VXX: TPNS1=03: USERTESTPATTERN3	QVX: TPNS1=03	TPNS1=03: USERTESTPATTERN3		✓
	USER TEST PATTERN - DELETE USER TEST PATTERN	USER TEST PATTERN 1 - DELETE		VXX: TPNS2=01				✓
		USER TEST PATTERN 2 - DELETE		VXX: TPNS2=02				✓
	USER TEST PATTERN 3 - DELETE		VXX: TPNS2=03				✓	
SIGNAL LIST	SIGNAL LIST-REGISTRATION			OEM				✓
	SIGNAL LIST-DELETE	A1		ODM: A1				✓
		A2		ODM: A2				✓
		A7		ODM: A7				✓
		A8		ODM: A8				✓
		L1		ODM: L1				✓
		L2		ODM: L2				✓
		L7		ODM: L7				✓
		L8		ODM: L8				✓
		SUB MEMORY LIST-CHANGEVER	01		OCS: 01			
		96		OCS: 96				✓
	SUB MEMORY LIST-CHANGEVER (EXTENDED)	01		OCS: 01-01				✓
		96		OCS: 95-96				✓
	SUB MEMORY LIST-REGISTRATION			OES				✓
	SUB MEMORY LIST-DELETE	01		ODS: 01-01				✓
		96		ODS: 95-96				✓
	SUB MEMORY USAGE STATE	01			QSB	01		✓
		96				96		✓
SECURITY	SECURITY SETTING	OFF			QVX: SPWI1	SPWI1+=00000		✓
		ON				SPWI1+=00001		✓
	CONTROL DEVICE SETUP-CONTROL PANEL	DISABLE		VXX: CDSI1+=00000	QVX: CDSI1	CDSI1+=00000		✓
		ENABLE		VXX: CDSI1+=00001		CDSI1+=00001		✓
		USER		VXX: CDSI1+=00002		CDSI1+=00002		✓
	CONTROL DEVICE SETUP-REMOTE CONTROL	DISABLE		VXX: CDSI2+=00000	QVX: CDSI2	CDSI2+=00000		✓
	ENABLE		VXX: CDSI2+=00001		CDSI2+=00001		✓	
	USER		VXX: CDSI2+=00002		CDSI2+=00002		✓	
NETWORK	ETHERNET TYPE	LAN		VXX: ETHI1+=00001	QVX: ETHI1	ETHI1+=00001		✓
		DIGITAL LINK		VXX: ETHI1+=00002		ETHI1+=00002		✓
		LAN & DIGITAL LINK		VXX: ETHI1+=00003		ETHI1+=00003		✓
	WIRED LAN-IP VERSION	IPv4		VXX: IPV11+=00001	QVX: IPV11	IPV11+=00001		✓
		IPv6		VXX: IPV11+=00002		IPV11+=00002		✓
		IPv4 & IPv6		VXX: IPV11+=00003		IPV11+=00003		✓
	WIRELESS LAN	OFF(DISABLE)		ONS: 0	QVX: WLSI1	WLSI1+=00000		✓
		ON(ENABLE)		ONS: 14		WLSI1+=00014		✓
	SLOT : DIGITAL LINK MODE	AUTO		VXX: SLSS1=VXX: DKMI1+=00001	QVX: SLSS1=QVX: DKMI1	SLSS1=DKMI1+=00001		✓
		DIGITAL LINK		VXX: SLSS1=VXX: DKMI1+=00002		SLSS1=DKMI1+=00002		✓
		ETHERNET		VXX: SLSS1=VXX: DKMI1+=00003		SLSS1=DKMI1+=00003		✓
		LONG REACH MODE		VXX: SLSS1=VXX: DKMI1+=00004		SLSS1=DKMI1+=00004		✓
	DIGITAL LINK-EXTRON XTP	OFF		VXX: EXTI1+=00000	QVX: EXTI1	EXTI1+=00000		✓
		ON		VXX: EXTI1+=00001		EXTI1+=00001		✓
	SLOT : DIGITAL LINK STATUS-LINK	NO LINK			QVX: SLSS1=QVX: DKSI1	SLSS1=DKSI1+=00000		✓
		DIGITAL LINK				SLSS1=DKSI1+=00001		✓
		LPM				SLSS1=DKSI1+=00002		✓
		ETHERNET				SLSS1=DKSI1+=00003		✓
	SLOT : DIGITAL LINK STATUS-HDCP STATUS	NO SIGNAL			QVX: SLSS1=QVX: DKSI2	SLSS1=DKSI2+=00000		✓
		OFF				SLSS1=DKSI2+=00001		✓
		ON				SLSS1=DKSI2+=00002		✓
	SLOT : DIGITAL LINK STATUS-SIGNAL QUALITY (MIN)	-255			QVX: SLSS1=QVX: DKSI3	SLSS1=DKSI3=-00255		✓
	0				SLSS1=DKSI3+=00000		✓	
SLOT : DIGITAL LINK STATUS-SIGNAL QUALITY (MAX)	-255			QVX: SLSS1=QVX: DKSI4	SLSS1=DKSI4=-00255		✓	
	0				SLSS1=DKSI4+=00000		✓	
SLOT : DIGITAL LINK INPUT CH LIST	HD1:HDMI1,HD2:HDMI2...			QVX: SLSS1=QVX: DL1S1	SLSS1=DL1S1=HD1:HDMI1,****:***		✓	
PROJECTOR NAME SETTING	PROJECTOR1		VXX: NCGS8=PROJECTOR1	QVX: NCGS8	NCGS8=PROJECTOR1		✓	
NFC SETTING	OFF		VXX: NFCI1+=00000	QVX: NFCI1	NFCI1+=00000		✓	
	READ ONLY		VXX: NFCI1+=00001		NFCI1+=00001		✓	
	READ/WRITE		VXX: NFCI1+=00003		NFCI1+=00003		✓	
Art-Net SETUP	OFF		VXX: DANI1+=00000	QVX: DANI1	DANI1+=00000		✓	
	ON(2.*.*)		VXX: DANI1+=00002		DANI1+=00002		✓	
	ON(10.*.*)		VXX: DANI1+=00003		DANI1+=00003		✓	
	ON(MANUAL)		VXX: DANI1+=00004		DANI1+=00004		✓	
Art-Net SETUP-START ADDRESS	1		VXX: DANI3+=00001	QVX: DANI3	DANI3+=00001		✓	
	501		VXX: DANI3+=00501		DANI3+=00501		✓	
Art-Net SETUP-NET	0		VXX: DANI4+=00000	QVX: DANI4	DANI4+=00000		✓	
	127		VXX: DANI4+=00127		DANI4+=00127		✓	
Art-Net SETUP-SUB NET	0		VXX: DANI5+=00000	QVX: DANI5	DANI5+=00000		✓	
	15		VXX: DANI5+=00015		DANI5+=00015		✓	
Art-Net SETUP-UNIVERS	0		VXX: DANI6+=00000	QVX: DANI6	DANI6+=00000		✓	
	15		VXX: DANI6+=00015		DANI6+=00015		✓	
Art-Net SETUP-CHANNEL SETTING	DEFAULT		VXX: DANI8+=00000	QVX: DANI8	DANI8+=00000		✓	
	1		VXX: DANI8+=00001		DANI8+=00001		✓	
	2		VXX: DANI8+=00002		DANI8+=00002		✓	
	USER		VXX: DANI8+=00100		DANI8+=00100		✓	
PRESHOW MODE	OFF			QVX: PSMI1	PSMI1+=00000		✓	
	ON				PSMI1+=00001		✓	

Note: The commands or parameters with "*" shows available commands or parameters for the projector which has been activated by the Upgrade Kit.